Questo manuale d'istruzione è fornito da trovaprezzi.it. Scopri tutte le offerte per StarTech.com SV431HU34K6 o cerca il tuo prodotto tra le migliori offerte di Switch

Questo manuale d'istruzione è fornito da trovaprezzi.it. Scopri tutte le offerte per StarTech.com SV431HU34K6 o cerca il tuo prodotto tra le migliori offerte di Switch

StarTech.com
Hard-to-find made easy®

Quick-Start Guide

4-Port USB 3.0 KVM Switch - HDMI - 4K 60Hz

Product Diagram (SV431HU34K6)

Front View



Rear View



	Port	Function
1	Port Selection LED Indicators	• Green: **PCs 1-4** connected (power on) • Red: **PCs 1-4** selected (power on)
2	Power LED	• Green: **Universal Power Adapter** connected
3	Console USB HID Ports	• Connect up to 4 **USB Human Interface Devices (HID)** (e.g. Keyboard, Mouse, Trackpad, Number Keypad, Drawing Tablet)
4	Console USB Hub Ports	• Connect up to 2 **SuperSpeed USB 5Gbps (USB 3.2 Gen 1) Peripheral Devices**
5	Port Selection Buttons	• Press the **Port Selection Button** to select **PCs 1-4**
6	HDCP Switch	• Control **HDCP Mode**
7	Console HDMI Output Port	• Connect the **Console HDMI Display**
8	EDID LED Indicator	• Indicates **EDID Mode**
9	EDID Button	• **EDID Copy** or **Auto EDID** from the **Console HDMI Display**
10	Firmware Upgrade Port	• Used to upgrade the **Firmware**. Use with **Firmware** from StarTech.com only.
11	PC HDMI Input Ports	• Connect to an **HDMI Port** on **PCs 1-4**
12	Power Input Port	• Connect a **DC 12V Power Source** to power the **KVM Switch**
13	Console Audio Port	• Connect an **Audio Device** (Stereo Speakers or a Microphone)
14	PC USB Ports	• Connect to a **SuperSpeed USB 5Gbps (USB 3.2 Gen 1) Port** on **PCs 1-4**
15	PC Audio Ports	• Connect to an **Audio Port** (for Stereo Speakers or a Microphone) on **PCs 1-4**

Requirements

For the latest requirements and to view detailed instructions on all product functionality in a full user manual, please visit: www.startech.com/SV431HU34K6.

Source PCs

- Computers (HDMI enabled) x 4
- HDMI Cables x 4
- SuperSpeed USB 5Gbps (USB 3.2 Gen 1) Cables (Type-A Male to Type-B Male) x 4
- (Optional) 3.5 mm Audio Cables (Male to Male) x 4

Console

- HDMI Display x 1
- HDMI Cable x 1

Manual Revision: October 15, 2020

- USB Keyboard x 1
- USB Mouse x 1
- (Optional) Audio Device (e.g. Headphones, Microphone, etc.) x 1
- (Optional) USB HID Devices x 2
- (Optional) SuperSpeed USB 5Gbps (USB 3.2 Gen 1) Peripheral Devices x 2

Installation

Connect the Console

1. Power off your **HDMI Display** and any **Peripherals** before connecting to the **KVM Switch**.
2. Connect an **HDMI Display** to the **Console HDMI Output Port** on the rear of the **KVM Switch**.
3. Connect a **USB Keyboard** and a **USB Mouse** to the **Console USB HID Ports** on the rear of the **KVM Switch**.
4. (Optional) Connect an additional **USB HID Device** to the remaining **Console USB HID Port** on the front of the **KVM Switch**.
5. (Optional) Connect the **Audio Device** to the **Console Audio Port** on the rear of the **KVM Switch**.
6. (Optional) Connect up to two **SuperSpeed USB 5Gbps (USB 3.2 Gen 1) Peripheral Devices** to the **Console USB Hub Ports** on the front and rear of the **KVM Switch**.

Connect the PCs

1. Power off your **Computer** and any **Peripherals** before connecting to the **KVM Switch**.
2. Connect an **HDMI Cable** from the **HDMI Port** on the **Computer** to the **PC 1 HDMI Input Port** on the rear of the **KVM Switch**.
3. Connect a **SuperSpeed USB 5Gbps (USB 3.2 Gen 1) Cable (Type-A Male to Type-B Male)** from the **USB-A Port** on the **Computer** to the **PC 1 USB Port** on the rear of the **KVM Switch**.

   Note: A **SuperSpeed USB 5Gbps** (or better) **Cable** is recommended for optimal performance.
4. (Optional) Connect a **3.5 mm Audio Cable** from the **Audio Port** on your **Computer** to the corresponding **PC Audio Port** on the rear of the **KVM Switch**.
5. Repeat steps 1 to 4 for **Source PCs 2-4**.

Operation

Power-On Sequence

1. Connect the **Universal Power Adapter** from a **Wall Outlet** to the **Power Input Port** on the rear of the **KVM Switch**.
2. Power on all **Peripherals**.
3. Select **PC 1** and power on the corresponding **Computer**.

   Note: Ensure that the **Computer** connected to the **PC 1** ports has fully booted to the operating system before proceeding.
4. Repeat step 3 for **Source PCs 2-4**.

FCC Compliance Statement

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Changes or modifications not expressly approved by StarTech.com could void the user's authority to operate the equipment.

Industry Canada Statement

This Class A digital apparatus complies with Canadian ICES-003.
Cet appareil numérique de la classe [A] est conforme à la norme NMB-003 du Canada.
CAN ICES-3 (A)/NMB-3(A)
This device complies with Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions:
(1) This device may not cause interference, and (2) This device must accept any interference, including interference that may cause undesired operation of the device.
Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes:
(1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

Use of Trademarks, Registered Trademarks, and other Protected Names and Symbols

This manual may make reference to trademarks, registered trademarks, and other protected names and/or symbols of third-party companies not related in any way to StarTech.com. Where they occur these references are for illustrative purposes only and do not represent an endorsement of a product or service by StarTech.com, or an endorsement of the product(s) to which this manual applies by the third-party company in question. StarTech.com hereby acknowledges that all trademarks, registered trademarks, service marks, and other protected names and/or symbols contained in this manual and related documents are the property of their respective holders.

Warranty Information

This product is backed by a two-year warranty.
For further information on product warranty terms and conditions, please refer to www.startech.com/warranty.

Limitation of Liability

In no event shall the liability of StarTech.com Ltd. and StarTech.com USA LLP (or their officers, directors, employees or agents) for any damages (whether direct or indirect, special, punitive, incidental, consequential, or otherwise), loss of profits, loss of business, or any pecuniary loss, arising out of or related to the use of the product exceed the actual price paid for the product. Some states do not allow the exclusion or limitation of incidental or consequential damages. If such laws apply, the limitations or exclusions contained in this statement may not apply to you.

Safety Measures

- If product has an exposed circuit board, do not touch the product under power.

Mesures de sécurité

- Si l'un des circuits imprimés du produit est visible, ne pas touchez le produit lorsqu'il est sous tension.

安全対策

- 製品に露出した状態の回路基盤が含まれる場合、電源が入っている状態で製品に触らないでください。

Misure di sicurezza

- Se il prodotto ha un circuito stampato visibile, non toccare il prodotto quando è acceso.

Säkerhetsåtgärder

- Rör aldrig vid enheter med oskyddade kretskort när strömmen är påslagen.

StarTech.com Ltd.
45 Artisans Cres
London, Ontario
N5V 5E9
Canada

StarTech.com LLP
4490 South Hamilton Road
Groveport, Ohio
43125
U.S.A.

StarTech.com Ltd.
Unit B, Pinnacle 15
Gowerton Rd,
Brackmills
Northampton
NN4 7BW
United Kingdom

FR: fr.startech.com
DE: de.startech.com
ES: es.startech.com
NL: nl.startech.com
IT: it.startech.com
JP: jp.startech.com