

**NWEAR**  
BY NEWLAND

# WD2-BS50

Wearable Scanner

User Guide



# Disclaimer

© 2018 Newland EMEA. All rights reserved.

Please read through the manual carefully before using the product and operate it according to the manual. It is advised that you should keep this manual for future reference.

Do not disassemble the device or remove the seal label from the device, doing so will void the product warranty provided by Newland EMEA.

All pictures in this manual are for reference only and actual product may differ. Regarding to the product modification and update, Newland EMEA. reserves the right to make changes to any software or hardware to improve reliability, function, or design at any time without notice. The information contained herein is subject to change without prior notice.

The products depicted in this manual may include software copyrighted by Newland EMEA, or third party. The user, corporation or individual, shall not duplicate, in whole or in part, distribute, modify, decompile, disassemble, decode, reverse engineer, rent, transfer or sublicense such software without prior written consent from the copyright holders.

This manual is copyrighted. No part of this publication may be reproduced, distributed or used in any form without written permission from Newland EMEA.

Newland EMEA reserves the right to make final interpretation of the statement above.

Newland EMEA  
Rolweg 25, 4104 AV Culemborg, The Netherlands

# Revision History

| Version | Description                                      | Date         |
|---------|--------------------------------------------------|--------------|
| 1.0.0   | Initial release.                                 | Oct 1, 2021  |
| 1.0.1   | Added Batch Mode and Retransmission in Chapter 5 | Nov 30, 2021 |

# Table of Contents

|                                                         |          |
|---------------------------------------------------------|----------|
| <b>Revision History .....</b>                           | <b>3</b> |
| <b>Preface .....</b>                                    | <b>1</b> |
| Introduction .....                                      | 1        |
| Chapter Description.....                                | 1        |
| Explanation of Icons .....                              | 2        |
| <b>Chapter 1 Getting Started .....</b>                  | <b>3</b> |
| Introduction .....                                      | 3        |
| <b>Chapter 2 Easyset .....</b>                          | <b>4</b> |
| <b>Chapter 3 System Setting .....</b>                   | <b>5</b> |
| Introduction .....                                      | 5        |
| Barcode Programming .....                               | 5        |
| Command Programming .....                               | 5        |
| EasySet Programming .....                               | 5        |
| Programming Barcode/ Programming Command/Function ..... | 6        |
| Use of Programming Command .....                        | 6        |
| Use of Programming Barcodes .....                       | 6        |
| Illumination .....                                      | 7        |
| Aiming .....                                            | 8        |
| Power On Beep .....                                     | 8        |
| Good Read Beep .....                                    | 9        |
| Good Read Beep Duration .....                           | 10       |
| Good Read Beep Frequency .....                          | 11       |
| Good Read Beep Volume .....                             | 12       |
| Vibration .....                                         | 13       |
| Good Read Vibration.....                                | 13       |
| Good Read Vibration Duration .....                      | 13       |
| Vibration Duration .....                                | 13       |
| Scan Mode .....                                         | 14       |
| Decode Session Timeout .....                            | 16       |
| Image Stabilization Timeout (Sense Mode).....           | 17       |

|                                                                   |           |
|-------------------------------------------------------------------|-----------|
| Reread Timeout .....                                              | 18        |
| Good Read Delay.....                                              | 20        |
| Image Decoding Timeout .....                                      | 21        |
| Make a Beeping Sound .....                                        | 22        |
| Lighting LED.....                                                 | 23        |
| Vibration Duration.....                                           | 23        |
| Scanning Preference.....                                          | 24        |
| Surround GS1 Application Identifiers (AI's) with Parentheses..... | 25        |
| Sensitivity .....                                                 | 26        |
| Trigger Commands.....                                             | 27        |
| Modify Start Scanning Command.....                                | 27        |
| Modify Stop Scanning Command.....                                 | 28        |
| Read Barcode after Power On .....                                 | 29        |
| Read Barcode On/Off.....                                          | 29        |
| Decode Area .....                                                 | 30        |
| Image Flipping.....                                               | 33        |
| Bad Read Message.....                                             | 34        |
| Set Bad Read Message .....                                        | 34        |
| Power Off .....                                                   | 35        |
| Default Settings.....                                             | 35        |
| Factory Defaults .....                                            | 35        |
| Custom Defaults.....                                              | 35        |
| Query Product Information .....                                   | 36        |
| Query Product Name .....                                          | 36        |
| Query Firmware Version .....                                      | 37        |
| Query Decoder Version.....                                        | 37        |
| Query Bluetooth Version .....                                     | 37        |
| Query Hardware Version.....                                       | 37        |
| Query Product Serial Number .....                                 | 37        |
| Query OEM Serial Number .....                                     | 38        |
| Query Manufacturing Date .....                                    | 38        |
| Query Data Formatter Version .....                                | 38        |
| <b>Chapter 4 USB Interface .....</b>                              | <b>39</b> |
| Introduction .....                                                | 39        |
| USB HID Keyboard .....                                            | 39        |
| USB Country Keyboard Types .....                                  | 40        |

|                                                    |           |
|----------------------------------------------------|-----------|
| Beep on Unknown Character .....                    | 44        |
| Emulate ALT+Keypad .....                           | 44        |
| Function Key Mapping .....                         | 50        |
| ASCII Function Key Mapping Table .....             | 52        |
| ASCII Function Key Mapping Table (Continued) ..... | 54        |
| Inter-Keystroke Delay.....                         | 55        |
| Caps Lock .....                                    | 55        |
| Convert Case .....                                 | 57        |
| Emulate Numeric Keypad .....                       | 57        |
| Fast Mode .....                                    | 60        |
| Polling Rate.....                                  | 60        |
| USB CDC .....                                      | 63        |
| VID/PID .....                                      | 63        |
| <b>Chapter 5 Wireless Communication .....</b>      | <b>64</b> |
| Operating Modes.....                               | 64        |
| Clear Pairing Info on Scanner .....                | 64        |
| Batch Mode .....                                   | 66        |
| Batch Mode Options.....                            | 66        |
| Prevent Same Barcode Storage.....                  | 67        |
| Batch Mode Transmit Delay .....                    | 68        |
| End of Transmission Message for Batch Mode.....    | 69        |
| Transmit Stored Data .....                         | 71        |
| Query/Clear Stored Data in Flash .....             | 72        |
| Retransmission .....                               | 73        |
| Transmission Timeout.....                          | 74        |
| Retransmission Count.....                          | 75        |
| Auto Power-Off Timeout.....                        | 76        |
| Set Scanner Name .....                             | 77        |
| <b>Chapter 6 Symbologies.....</b>                  | <b>78</b> |
| Introduction .....                                 | 78        |
| Global Settings .....                              | 78        |
| Enable/Disable All Symbologies.....                | 78        |
| Enable/Disable 1D Symbologies .....                | 78        |
| Enable/Disable 2D Symbologies .....                | 79        |
| Enable/Disable Postal Symbologies.....             | 79        |

|                                                          |     |
|----------------------------------------------------------|-----|
| Code 128.....                                            | 80  |
| Restore Factory Defaults .....                           | 80  |
| Enable/Disable Code 128 .....                            | 80  |
| Set Length Range for Code 128.....                       | 80  |
| EAN-8.....                                               | 82  |
| Restore Factory Defaults .....                           | 82  |
| Enable/Disable EAN-8 .....                               | 82  |
| Transmit Check Character .....                           | 82  |
| 2-Digit Add-On Code.....                                 | 83  |
| 5-Digit Add-On Code.....                                 | 84  |
| Add-On Code Required.....                                | 85  |
| Convert EAN-8 to EAN-13 .....                            | 85  |
| EAN-13.....                                              | 87  |
| Restore Factory Defaults .....                           | 87  |
| Enable/Disable EAN-13.....                               | 87  |
| Transmit Check Character .....                           | 87  |
| 2-Digit Add-On Code.....                                 | 88  |
| 5-Digit Add-On Code.....                                 | 88  |
| EAN-13 Beginning with 290 Add-On Code Required .....     | 90  |
| EAN-13 Beginning with 378/379 Add-On Code Required ..... | 91  |
| EAN-13 Beginning with 414/419 Add-On Code Required ..... | 92  |
| EAN-13 Beginning with 434/439 Add-On Code Required ..... | 93  |
| EAN-13 Beginning with 977 Add-On Code Required .....     | 94  |
| EAN-13 Beginning with 978 Add-On Code Required .....     | 95  |
| EAN-13 Beginning with 979 Add-On Code Required .....     | 96  |
| UPC-E .....                                              | 97  |
| Restore Factory Defaults .....                           | 97  |
| Enable/Disable UPC-E .....                               | 97  |
| Transmit Check Character .....                           | 99  |
| 2-Digit Add-On Code.....                                 | 99  |
| 5-Digit Add-On Code.....                                 | 100 |
| Add-On Code Required.....                                | 101 |
| Transmit Preamble Character .....                        | 101 |
| Convert UPC-E to UPC-A .....                             | 102 |
| UPC-A .....                                              | 103 |
| Restore Factory Defaults .....                           | 103 |

|                                                    |     |
|----------------------------------------------------|-----|
| Enable/Disable UPC-A .....                         | 103 |
| Transmit Check Character .....                     | 103 |
| 2-Digit Add-On Code .....                          | 104 |
| 5-Digit Add-On Code .....                          | 105 |
| Add-On Code Required .....                         | 105 |
| Transmit Preamble Character .....                  | 106 |
| Coupon .....                                       | 107 |
| UPC-A/EAN-13 with Extended Coupon Code .....       | 107 |
| Coupon GS1 Databar Output .....                    | 108 |
| Interleaved 2 of 5 .....                           | 109 |
| Restore Factory Defaults .....                     | 109 |
| Enable/Disable Interleaved 2 of 5 .....            | 109 |
| Set Length Range for Interleaved 2 of 5 .....      | 110 |
| Check Character Verification .....                 | 112 |
| ITF-14 .....                                       | 113 |
| Restore Factory Defaults .....                     | 113 |
| Enable/Disable ITF-14 .....                        | 113 |
| ITF-6 .....                                        | 114 |
| Restore Factory Defaults .....                     | 114 |
| Enable/Disable ITF-6 .....                         | 114 |
| Matrix 2 of 5 .....                                | 116 |
| Restore Factory Defaults .....                     | 116 |
| Enable/Disable Matrix 2 of 5 .....                 | 116 |
| Set Length Range for Matrix 2 of 5 .....           | 117 |
| Check Character Verification .....                 | 119 |
| Code 39 .....                                      | 120 |
| Restore Factory Defaults .....                     | 120 |
| Enable/Disable Code 39 .....                       | 120 |
| Set Length Range for Code 39 .....                 | 120 |
| Check Character Verification .....                 | 122 |
| Transmit Start/Stop Character .....                | 124 |
| Enable/Disable Code 39 Full ASCII .....            | 124 |
| Enable/Disable Code 32 (Italian Pharma Code) ..... | 124 |
| Code 32 Prefix .....                               | 126 |
| Transmit Code 32 Start/Stop Character .....        | 126 |
| Transmit Code 32 Check Character .....             | 127 |

|                                           |     |
|-------------------------------------------|-----|
| Codabar .....                             | 128 |
| Restore Factory Defaults .....            | 128 |
| Enable/Disable Codabar .....              | 128 |
| Set Length Range for Codabar .....        | 129 |
| Check Character Verification .....        | 131 |
| Start/Stop Character .....                | 133 |
| Code 93.....                              | 134 |
| Restore Factory Defaults .....            | 134 |
| Enable/Disable Code 93 .....              | 134 |
| Set Length Range for Code 93.....         | 134 |
| Check Character Verification .....        | 135 |
| China Post 25.....                        | 137 |
| Restore Factory Defaults .....            | 137 |
| Enable/Disable China Post 25 .....        | 137 |
| Set Length Range for China Post 25.....   | 137 |
| Check Character Verification .....        | 138 |
| GS1-128 (UCC/EAN-128) .....               | 140 |
| Restore Factory Defaults .....            | 140 |
| Enable/Disable GS1-128.....               | 140 |
| Set Length Range for GS1-128.....         | 140 |
| GS1 Databar (RSS).....                    | 142 |
| Restore Factory Defaults .....            | 142 |
| Enable/Disable GS1 Databar .....          | 142 |
| Transmit Application Identifier "01"..... | 142 |
| GS1 Composite (EAN-UCC Composite) .....   | 143 |
| Restore Factory Defaults .....            | 143 |
| Enable/Disable GS1 Composite.....         | 143 |
| Enable/Disable UPC/EAN Composite .....    | 143 |
| Code 11.....                              | 145 |
| Restore Factory Defaults .....            | 145 |
| Enable/Disable Code 11 .....              | 145 |
| Set Length Range for Code 11.....         | 145 |
| Check Character Verification .....        | 146 |
| Transmit Check Character .....            | 147 |
| ISBN.....                                 | 149 |
| Restore Factory Defaults .....            | 149 |

|                                         |     |
|-----------------------------------------|-----|
| Enable/Disable ISBN.....                | 149 |
| Set ISBN Format.....                    | 149 |
| ISSN.....                               | 151 |
| Restore Factory Defaults .....          | 151 |
| Enable/Disable ISSN.....                | 151 |
| Industrial 25.....                      | 152 |
| Restore Factory Defaults .....          | 152 |
| Enable/Disable Industrial 25 .....      | 152 |
| Set Length Range for Industrial 25..... | 152 |
| Check Character Verification .....      | 153 |
| Standard 25.....                        | 155 |
| Restore Factory Defaults .....          | 155 |
| Enable/Disable Standard 25 .....        | 155 |
| Set Length Range for Standard 25.....   | 155 |
| Check Character Verification .....      | 156 |
| Plessey.....                            | 158 |
| Restore Factory Defaults .....          | 158 |
| Enable/Disable Plessey .....            | 158 |
| Set Length Range for Plessey .....      | 158 |
| Check Character Verification .....      | 159 |
| MSI-Plessey .....                       | 161 |
| Restore Factory Defaults .....          | 161 |
| Enable/Disable MSI-Plessey.....         | 161 |
| Set Length Range for MSI-Plessey .....  | 161 |
| Check Character Verification .....      | 162 |
| Transmit Check Character .....          | 163 |
| AIM 128.....                            | 165 |
| Restore Factory Defaults .....          | 165 |
| Enable/Disable AIM 128.....             | 165 |
| Set Length Range for AIM 128.....       | 165 |
| ISBT 128 .....                          | 167 |
| Restore Factory Defaults .....          | 167 |
| Enable/Disable ISBT 128.....            | 167 |
| COOP 25.....                            | 168 |
| Restore Factory Defaults .....          | 168 |
| Enable/Disable COOP 25 .....            | 168 |

|                                         |     |
|-----------------------------------------|-----|
| Set Length Range for COOP 25.....       | 169 |
| Check Character Verification .....      | 170 |
| PDF417 .....                            | 171 |
| Restore Factory Defaults .....          | 171 |
| Enable/Disable PDF417 .....             | 171 |
| Set Length Range for PDF417 .....       | 171 |
| PDF417 Twin Code.....                   | 172 |
| PDF417 Inverse .....                    | 173 |
| Character Encoding .....                | 174 |
| PDF417 ECI Output .....                 | 174 |
| Micro PDF417 .....                      | 176 |
| Restore Factory Defaults .....          | 176 |
| Enable/Disable Micro PDF417 .....       | 176 |
| Set Length Range for Micro PDF417 ..... | 176 |
| QR Code .....                           | 178 |
| Restore Factory Defaults .....          | 178 |
| Enable/Disable QR Code .....            | 178 |
| Set Length Range for QR Code .....      | 178 |
| QR Twin Code.....                       | 180 |
| QR Inverse .....                        | 180 |
| Character Encoding .....                | 181 |
| QR ECI Output .....                     | 181 |
| Micro QR Code .....                     | 183 |
| Restore Factory Defaults .....          | 183 |
| Enable/Disable Micro QR.....            | 183 |
| Set Length Range for Micro QR.....      | 183 |
| Aztec .....                             | 185 |
| Restore Factory Defaults .....          | 185 |
| Enable/Disable Aztec Code .....         | 185 |
| Set Length Range for Aztec Code.....    | 185 |
| Read Multi-barcodes on an Image .....   | 186 |
| Set the Number of Barcodes.....         | 187 |
| Character Encoding .....                | 188 |
| Aztec ECI Output .....                  | 189 |
| Data Matrix.....                        | 190 |
| Restore Factory Defaults .....          | 190 |

|                                                 |     |
|-------------------------------------------------|-----|
| Enable/Disable Data Matrix.....                 | 190 |
| Set Length Range for Data Matrix.....           | 190 |
| Data Matrix Twin Code.....                      | 191 |
| Rectangular Barcode .....                       | 192 |
| Data Matrix Inverse .....                       | 193 |
| Character Encoding .....                        | 193 |
| Data Matrix ECI Output .....                    | 194 |
| Maxicode.....                                   | 195 |
| Restore Factory Defaults .....                  | 195 |
| Enable/Disable Maxicode.....                    | 195 |
| Set Length Range for Maxicode.....              | 196 |
| Chinese Sensible Code.....                      | 197 |
| Restore Factory Defaults .....                  | 197 |
| Enable/Disable Chinese Sensible Code.....       | 197 |
| Set Length Range for Chinese Sensible Code..... | 198 |
| Chinese Sensible Twin Code .....                | 199 |
| Chinese Sensible Code Inverse .....             | 200 |
| USPS Postnet .....                              | 201 |
| Restore Factory Defaults .....                  | 201 |
| Enable/Disable USPS Postnet .....               | 201 |
| Transmit Check Character .....                  | 201 |
| USPS Intelligent Mail.....                      | 202 |
| Restore Factory Defaults .....                  | 202 |
| Enable/Disable USPS Intelligent Mail .....      | 202 |
| Royal Mail .....                                | 203 |
| Restore Factory Defaults .....                  | 203 |
| Enable/Disable Royal Mail .....                 | 203 |
| USPS Planet .....                               | 204 |
| Restore Factory Defaults .....                  | 204 |
| Enable/Disable USPS Planet .....                | 204 |
| Transmit Check Character .....                  | 204 |
| KIX Post .....                                  | 205 |
| Restore Factory Defaults .....                  | 205 |
| Enable/Disable KIX Post.....                    | 205 |
| Australian Postal .....                         | 206 |
| Restore Factory Defaults .....                  | 206 |

|                                            |            |
|--------------------------------------------|------------|
| Enable/Disable Australian Postal .....     | 206        |
| Japan Post .....                           | 207        |
| Restore Factory Defaults .....             | 207        |
| Enable/Disable Japan Post .....            | 207        |
| GM Code .....                              | 208        |
| Restore Factory Defaults .....             | 208        |
| Enable/Disable GM .....                    | 208        |
| Set Length Range for GM .....              | 209        |
| <b>Chapter 7 Data Formatter.....</b>       | <b>210</b> |
| Introduction .....                         | 210        |
| Add a Data Format.....                     | 210        |
| Programming with Barcodes .....            | 210        |
| Programming with Serial Commands .....     | 212        |
| Enable/Disable Data Formatter .....        | 213        |
| Non-Match Error Beep .....                 | 216        |
| Data Format Selection.....                 | 216        |
| Change Data Format for a Single Scan.....  | 217        |
| Clear Data Format.....                     | 217        |
| Query Data Formats.....                    | 218        |
| <b>Chapter 8 Prefix &amp; Suffix.....</b>  | <b>219</b> |
| Introduction .....                         | 219        |
| Global Settings.....                       | 219        |
| Enable/Disable All Prefixes/Suffixes ..... | 219        |
| Prefix Sequence.....                       | 220        |
| Custom Prefix.....                         | 220        |
| Enable/Disable Custom Prefix .....         | 220        |
| Set Custom Prefix .....                    | 220        |
| AIM ID Prefix .....                        | 222        |
| Code ID Prefix.....                        | 223        |
| Restore All Default Code IDs .....         | 224        |
| Modify Code ID .....                       | 224        |
| Modify 1D symbologies .....                | 225        |
| Modify 2D symbologies: .....               | 231        |
| Custom Suffix.....                         | 233        |
| Enable/Disable Custom Suffix.....          | 233        |
| Set Custom Suffix .....                    | 233        |

|                                                  |            |
|--------------------------------------------------|------------|
| Data Packing .....                               | 234        |
| Introduction .....                               | 234        |
| Data Packing Options .....                       | 234        |
| Terminating Character Suffix.....                | 235        |
| Enable/Disable Terminating Character Suffix..... | 235        |
| Set Terminating Character Suffix .....           | 236        |
| <b>Chapter 9 Batch Programming.....</b>          | <b>237</b> |
| Introduction .....                               | 237        |
| Create a Batch Command.....                      | 237        |
| Create a Batch Barcode .....                     | 238        |
| Use Batch Barcode .....                          | 238        |
| <b>Appendix .....</b>                            | <b>240</b> |
| Digit Barcodes .....                             | 240        |
| Save/Cancel Barcodes .....                       | 242        |
| Factory Defaults Table .....                     | 244        |
| AIM ID Table .....                               | 257        |
| Code ID Table .....                              | 260        |
| Symbology ID Number .....                        | 263        |
| ASCII Table .....                                | 266        |
| Unicode Key Maps .....                           | 274        |

---

## Preface

### Introduction

This manual provides detailed instructions for setting up and using the WD2 wireless barcode scanner (hereinafter referred to as “**the scanner**”).

### Chapter Description

|                                         |                                                                                                                       |
|-----------------------------------------|-----------------------------------------------------------------------------------------------------------------------|
| <i>Chapter 1 Getting Started</i>        | : Gives a general description of WD2 scanner.                                                                         |
| <i>Chapter 2 EasySet</i>                | : Introduces a useful tool you can use to set up WD2 scanner and develop new applications.                            |
| <i>Chapter 3 System Settings</i>        | : Introduces three configuration methods and describes how to configure general parameters of WD2 scanner.            |
| <i>Chapter 4 USB Interface</i>          | : Describes how to configure USB communication parameters.                                                            |
| <i>Chapter 5 Wireless Communication</i> | : Describes how to configure the parameters necessary for wireless communication between the scanner and host device. |
| <i>Chapter 6 Symbolologies</i>          | : Lists all compatible symbolologies and describes how to configure the relevant parameters.                          |
| <i>Chapter 7 Data Formatter</i>         | : Explains how to customize scanned data with the data formatter.                                                     |
| <i>Chapter 8 Prefix &amp; Suffix</i>    | : Describes how to use prefix and suffix to customize scanned data.                                                   |
| <i>Chapter 9 Batch Programming</i>      | : Explains how to integrate a complex programming task into a single barcode.                                         |
| <i>Appendix</i>                         | : Provides factory defaults table and a bunch of frequently used programming barcodes.                                |

---

## Explanation of Icons



This icon indicates something relevant to this manual.



This icon indicates this information requires extra attention from the reader.



This icon indicates handy tips that can help you use or configure the scanner with ease.



This icon indicates practical examples that can help you to acquaint yourself with operations.

---

## Chapter 1 Getting Started

### Introduction

The scanner reads a 1D or 2D barcode by capturing its image. Adopting the advanced technology independently developed by Newland Auto-ID Tech and 2d image embedding application barcode engine, it begins a new era of 2d image embedding application barcode engine.


Newland 2D decode IC combines advanced UIMG and IC designation and manufacturing technology, simplifying the difficulties of designation of 2d decode products, establishing remarks of high quality, high reliability and low consumption products.

The scanner can read kinds of mainstream 1D barcodes, standard 2D barcodes.( all versions of PDF417,QR Code M1/M2/Micro and Data Matrix) and GS1-DataBar™ (RSS) barcodes, including Limited, Stacked, Expanded and so on.

The scanner can read barcodes in papers, plastic cards, LCD and other kinds of mediums of printing and displaying. It has great performance. All-in-one design is extremely light and only needs small operation space It can be embedded in varieties of application.

## Chapter 2 Easyset

EasySet supports Windows operating systems. EasySet, developed by Newland EMEA, is a configuration tool for Newland's 1D/2D handheld barcode scanner, fixed mount barcode scanners and OEM scan engines. Its main features include View device & configuration information of online device and send serial commands to online device and receive device response.



---

## Chapter 3 System Setting

### Introduction

There are three ways to configure the scanner: barcode programming, command programming and EasySet programming.

#### Barcode Programming

The scanner can be configured by scanning programming barcodes. All user programmable features/options are described along with their programming barcodes/commands in the following sections.

This programming method is most straightforward. However, it requires manually scanning barcodes. As a result, errors are more likely to occur.

#### Command Programming

The scanner can also be configured by serial commands sent from the host device.

Users can design an application program to send those command strings to the scanners to perform device configuration.

#### EasySet Programming

Besides the two methods mentioned above, you can conveniently perform scanner configuration through EasySet too. EasySet is a Windows-based configuration tool particularly designed for Newland products, enabling users to gain access to decoded data and captured images and to configure scanners. For more information about this tool, refer to the *EasySet User Guide*.



#SETUPE1  
Enter Setup

## Programming Barcode/ Programming Command/Function



The figure above is an example that shows you the programming barcode and command for the Enter Setup function:

1. The **No Case Conversion** barcode.
2. The **No Case Conversion** command.
3. The description of feature/option.

\*\* indicates factory default setting

## Use of Programming Command

Besides the barcode programming method, the scanner can also be configured by serial commands (HEX) sent from the host device. **All commands must be entered in uppercase letters.**

## Use of Programming Barcodes

Scanning the **Enter Setup** barcode can enable the scanner to enter the setup mode. Then you can scan a number of programming barcodes to configure your scanner. To exit the setup mode, scan the **Exit Setup** barcode or a non-programming barcode, or reboot the scanner.



@SETUPE0  
\*\* Exit Setup



@SETUPE1  
Enter Setup



#SETUPE0  
Exit Setup



#SETUPE1  
**Enter Setup**

---

Programming barcode data (i.e. the characters under programming barcode) can be transmitted to the host device. You may scan the appropriate barcode below to enable or disable the transmission of programming barcode data to the host device.



#SETUPT0

**\*\* Do Not Transmit Programming Barcode Data**



#SETUPT1

**Transmit Programming Barcode Data**

## **Illumination**



@ILLSCN1

**\*\* On**



@ILLSCN0

**Off**



#SETUPE0  
**Exit Setup**



#SETUPE1  
Enter Setup

---

## Aiming



@AMLENA1  
\*\* On



@AMLENA0  
Off



@AMLENA2  
Always lighting

## Power On Beep

The scanner can be programmed to beep when it is powered on. Scan the **Off** barcode if you do not want a power on beep.



@PWBENA1  
\*\* On



@PWBENA0  
Off



#SETUPE0  
Exit Setup



#SETUPE1  
**Enter Setup**

---

## Good Read Beep

Scanning the **Off** barcode can turn off the beep that indicates successful decode; scanning the **On** barcode can turn it back on.



@GRBENA1  
**\*\* On**



@GRBENA0  
**Off**



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---

## Good Read Beep Duration

This parameter sets the length of the beep the scanner emits on a good read. It is programmable in 1ms increments from 20ms to 300ms.



@GRBDUR40

**Short (40ms)**



@GRBDUR80

**\*\* Medium (80ms)**



@GRBDUR120

**Long (120ms)**



@GRBDUR

**Custom (20 – 300ms)**

**E**  
*xample*

### Set the Good Read Beep duration to 200ms:

1. Scan the **Enter Setup** barcode.
2. Scan the **Custom** barcode.
3. Scan the numeric barcodes “2”, “0” and “0” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Exit Setup** barcode.



#SETUPE0

**Exit Setup**



#SETUPE1  
**Enter Setup**

### Good Read Beep Frequency


This parameter is programmable in 1Hz increments from 20Hz to 20,000Hz. The default setting is 4000Hz



@GRBFRQ800  
**Extra Low (800Hz)**



@GRBFRQ1600  
**Medium (2730Hz)**



@GRBFRQ  
**Custom (20 - 20,000Hz)**



@GRBFRQ1600  
**Low (1600Hz)**



@GRBFRQ4200  
**High (4200Hz)**

**E**  
*xample*

#### Set the Good Read Beep frequency to 2,000Hz:

1. Scan the **Enter Setup** barcode.
2. Scan the **Custom** barcode.
3. Scan the numeric barcodes “2”, “0”, “0” and “0” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Exit Setup** barcode.



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---

## Good Read Beep Volume

This parameter is programmable in 1 increments from 1 to 20



@GRBVLL20

**\*\* Loud**



@GRBVLL7

**Medium**



@GRBVLL2

**Low**



@GRBVLL

**Custom(1-20)**



#SETUPE0

**Exit Setup**



#SETUPE1  
Enter Setup

## Vibration

### Good Read Vibration



@GRVENA1  
\*\* On



@GRVENA0  
Off

### Good Read Vibration Duration

This parameter is programmable in 1ms increments from 100ms to 2000ms. The default setting is 100ms



@GRVDUR  
Vibration Duration



#SETUPE0  
Exit Setup



#SETUPE1

Enter Setup

---

## Scan Mode

- ✧ **Level Mode:** A trigger pull activates a decode session. The decode session continues until a barcode is decoded or you release the trigger.
- ✧ **Sense Mode:** The scanner waits for the image stabilization timeout to expire before activating a decode session everytime it detects a change in ambient illumination. Decode session continues until a barcode is decoded or the decode session timeout expires. In this mode, a trigger pull can also activate a decode session. The decode session continues until a barcode is decoded or the trigger is released. When the session ends, the scanner continues to monitor ambient illumination. **Timeout between Decodes (Same Barcode)** can avoid undesired rereading of same barcode in a given period of time. **Sensitivity** can change the Sense Mode's sensibility to changes in ambient illumination.
- ✧ **Continuous Mode:** The scanner automatically starts one decode session after another. To suspend/resume barcode reading, simply press the trigger. **Timeout between Decodes (Same Barcode)** can avoid undesired rereading of same barcode in a given period of time.
- ✧ **Pulse Mode:** When the trigger is pulled and released, scanning is activated until a barcode is decoded or the decode session timeout expires (The decode session timeout begins when the trigger is released).
- ✧ **Batch Mode:** When the trigger is pulled and released, scanning is activated until the trigger is released. During pulling the trigger, good read barcodes will beep and output barcode information. As long as unrelease the trigger, it will continues decoding. During pulling the trigger, same code can be read only once.



#SETUPE0

Exit Setup



#SETUP1  
**Enter Setup**

---



@SCNMOD0  
**\*\* Level Mode**



@SCNMOD2  
**Sense Mode**



@SCNMOD4  
**Pulse Mode**



@SCNMOD3  
**Continuous Mode**



@SCNMOD7  
**Batch Mode**



#SETUP0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---

## Decode Session Timeout

This parameter sets the maximum time decode session continues during a scan attempt. It is programmable in 1ms increments from 1ms to 3,600,000ms. When it is set to 0, the timeout is infinite. The default setting is 3,000ms.



@ORTSET

**Decode Session Timeout**

**E**  
*xample*

**Set the decode session timeout to 1,500ms:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Decode Session Timeout** barcode.
3. Scan the numeric barcodes “1”, “5”, “0” and “0” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Exit Setup** barcode.



#SETUPE0

**Exit Setup**



#SETUPE1  
**Enter Setup**

## Image Stabilization Timeout (Sense Mode)

This parameter defines the amount of time the scanner will spend adapting to ambient environment after it decodes a barcode and “looks” for another. It is programmable in 1ms increments from 0ms to 3,000ms. The default setting is 200ms.



@SENIST

**Image Stabilization Timeout**

**E**  
*xample*

**Set the image stabilization timeout to 800ms:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Image Stabilization Timeout** barcode.
3. Scan the numeric barcodes “8”, “0” and “0” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Exit Setup** barcode.



#SETUPE0  
**Exit Setup**



#SETUPE1  
Enter Setup

## Reread Timeout

Reread Timeout can avoid undesired rereading of same barcode in a given period of time. This feature is only applicable to the Sense and Continuous modes.

**Enable Reread Timeout:** Do not allow the scanner to reread same barcode before the reread timeout expires.

**Disable Reread Timeout:** Allow the scanner to reread same barcode.



@RRDENA1  
**\*\*Enable Reread Timeout**



@RRDENA0  
**Disable Reread Timeout**

The following parameter sets the timeout between decodes for same barcode. It is programmable in 1ms increments from 1ms to 3,600,000ms. When it is set to a value greater than 3,000, the timeout for rereading same programming barcode is limited to 3,000ms. The default setting is 300ms.



@RRDDUR  
**Set Reread Timeout**

**E**  
*xample*

### Set the reread timeout to 1,000ms:

1. Scan the **Enter Setup** barcode.
2. Scan the **Timeout between Decodes (Same Barcode)** barcode.
3. Scan the numeric barcodes "1", "0", "0" and "0" from the "Digit Barcodes" section in Appendix.
4. Scan the **Save** barcode from the "Save/Cancel Barcodes" section in Appendix.
5. Scan the **Exit Setup** barcode.

You may wish to restart the reread timeout when the scanner encounters the same barcode that was decoded in the last scan session before the reread timeout expires. To enable this feature, scan the **Reread Timeout Reset On** barcode. This feature is only effective when **Reread Timeout** is enabled.



#SETUPE0  
Exit Setup



#SETUPE1  
**Enter Setup**


---



@RRDREN1  
**Reread Timeout Reset On**



@RRDREN0  
**\*\* Reread Timeout Reset Off**



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

---

## Good Read Delay

Good Read Delay sets the minimum amount of time before the scanner can read another barcode. This parameter is programmable in 1ms increments from 1ms to 3,600,000ms. The default setting is 500ms. Scan the appropriate barcode below to enable or disable the delay.



@GRDENA1

Enable Good Read Delay



@GRDENA0

\*\* Disable Good Read Delay

To set the good read delay, scan the barcode below, then set the delay (from 1 to 3,600,000ms) by scanning the digit barcode(s) then scanning the **Save** barcode from the Appendix.



@GRDDUR

Good Read Delay

**E**  
*xample*

**Set the good read delay to 1,000ms:**

1. Scan the **Good Read Delay** barcode.
2. Scan the numeric barcodes "1", "0", "0" and "0" from the "Digit Barcodes" section in Appendix.
3. Scan the **Save** barcode from the "Save/Cancel Barcodes" section in Appendix.



#SETUPE0

Exit Setup



#SETUPE1  
**Enter Setup**

## Image Decoding Timeout

Image Decoding Timeout specifies the maximum time the scanner will spend decoding an image. This parameter is programmable in 1ms increments from 1ms to 3,000ms. The default timeout is 500ms.



**Image Decoding Timeout**

**E**  
*xample*

**Set the image decoding timeout to 1,000ms:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Image Decoding Timeout** barcode.
3. Scan the numeric barcodes “1”, “0”, “0” and “0” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Exit Setup** barcode.



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

---

## Make a Beeping Sound

You may wish to force the scanner to beep upon a command sent from the host. A beeping sound is made to gain a user's attention to an error or other important event.

BEEPONxxxFyyyTnnV (xxx: The desired frequency, 1-20,000Hz; yyy: The desired duration, 1-10,000ms; nn: The desired volume, 1~20)

**Example: Make a 50ms beep at 2,000Hz, 20V**

Enter:        ~<SOH>0000#BEEPON2000F50T20V;<ETX>

Response: <STX><SOH>0000#BEEPON2000F50T20V <ACK>;<ETX>



#SETUPE0

Exit Setup



#SETUPE1  
Enter Setup

---

## Lighting LED

You may wish to force the scanner to light for a while.

LEDONIxCyyyD (xC: The desired LED color, 0C: red; 1C: white; 2C: green; 3C: blue. The supported color can be required in the Easyset. The desired duration, 10-3,600,000ms)

Example: Lighting red LED in 1 minute

Enter: ~<SOH>0000#LEDONS0C60000D;<ETX>

Response: <STX><SOH>0000#LEDONS0C60000D<ACK>;<ETX>

## Vibration Duration

You may wish to force the scanner to vibrate for a while.

VIBRATxxx (xxx: the desired vibration duration, 50 ~ 3000ms)

Example: Vibration during 1000ms

Enter: ~<SOH>0000#VIBRAT1000;<ETX>

Response: <STX><SOH>0000VIBRAT1000<ACK>;<ETX>



#SETUPE0  
Exit Setup



#SETUPE1

**Enter Setup**

---

## Scanning Preference

**Normal Mode:** Select this mode when reading barcodes on paper.

**Screen Mode:** Select this mode when reading barcodes on the screen.



@EXPLVL0

**\*\* Normal Mode**




@EXPLVL2

**Screen Mode**



#SETUPE0

**Exit Setup**



#SETUPE1  
Enter Setup

## Surround GS1 Application Identifiers (AI's) with Parentheses

When **Surround GS1 AI's with Parentheses** is selected, each application identifier (AI) contained in scanned data will be enclosed in parentheses in the output message.



@GS1AIP0


**\*\* Do Not Surround GS1 AI's with Parentheses**



@GS1AIP1

**Surround GS1 AI's with Parentheses**

**E**  
*sample*



(01) 0 0614141 99999 6 (10) 10ABCEDF123456

If **Surround GS1 AI's with Parentheses** is selected, the barcode above is output as

(01)00614141999996(10)10ABCEDF123456.

If **Do Not Surround GS1 AI's with Parentheses** is selected, the barcode above is output as

01006141419999961010ABCEDF123456.



#SETUPE0  
Exit Setup



#SETUPE1

**Enter Setup**

---

## Sensitivity

Sensitivity specifies the degree of acuteness of the scanner's response to changes in images captured.

The higher the sensitivity, the lower requirement in image change to trigger the scanner. You can select an appropriate degree of sensitivity that fits the application environment. The feature is only applicable to the Sense mode. It is programmable from 1 to 20. The default setting is Medium (5).



@SENLVL14

**Low Sensitivity**



@SENLVL11

**\*\* Medium Sensitivity**



@SENLVL8

**High Sensitivity**



@SENLVL5

**Enhanced Sensitivity**



@SENLVL

**Custom Sensitivity (1-20)**

**E**  
*xample*

### Set the sensitivity to Level 10:

1. Scan the **Enter Setup** barcode.
2. Scan the **Custom Sensitivity** barcode.
3. Scan the numeric barcodes "1" and "0" from the "Digit Barcodes" section in Appendix.
4. Scan the **Save** barcode from the "Save/Cancel Barcodes" section in Appendix.
5. Scan the **Exit Setup** barcode.



#SETUPE0

**Exit Setup**



#SETUPE1  
Enter Setup

## Trigger Commands

When **Enable Trigger Commands** is selected, you can activate and deactivate the scanner in the Level mode with serial trigger commands. Sending the **Start Scanning** command (default: **<SOH> T <EOT>**, user-programmable) to the scanner in the Level mode activates a decode session. The decode session continues until a barcode is decoded or the decode session timeout or the scanner receives the **Stop Scanning** command (default: **<SOH> P <EOT>**, user-programmable).



@SCNTCE0  
\*\* Disable Trigger Commands



@SCNTCE1  
Enable Trigger Commands

## Modify Start Scanning Command

The **Start Scanning Command** can stimulate the trigger unreleased and consist of 1-10 characters (HEX values from 0x01 to 0xFF). In this command, the character “?” (HEX: 0x3F) cannot be the first character. The default **Start Scanning** command is **<SOH> T <EOT>**.



@SCNTCT  
Modify Start Scanning Command

**E**  
*xample*

Set the **Start Scanning** command to “\*T”:

1. Scan the **Enter Setup** barcode.
2. Scan the **Modify Start Scanning Command** barcode.
3. Scan the numeric barcodes “2”, “A”, “5” and “4” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Exit Setup** barcode.



#SETUPE0  
Exit Setup



#SETUPE1

Enter Setup

---

## Modify Stop Scanning Command

The **Stop Scanning Command** can stimulate the trigger unreleased and consist of 1-10 characters (HEX values from 0x01 to 0xFF). In this command, the character “?” (HEX: 0x3F) cannot be the first character. The default **Stop Scanning** command is **<SOH> P <EOT>**.



@SCNTCP

Modify Stop Scanning Command



#SETUPE0

Exit Setup



#SETUPE1  
Enter Setup

## Read Barcode after Power On

**Disable:** The scanner can not decode barcodes after power on. The illumination and aiming are off. You can send Read Barcode Command to the scanner to activate it.

**Enable:** The scanner can decode barcodes after power on.

This feature is disabled when the interface is USB Keyboard



@SCNPEN1  
\*\* Enable



@SCNPEN0  
Disable

## Read Barcode On/Off

Sending the Read Barcode Off command ~<SOH>0000#SCNENA0;<ETX> to the scanner can disable it from reading barcode, and the scanner is unable to scan barcode unless you send the Read Barcode On command ~<SOH>0000#SCNENA1;<ETX> to it or power cycle it. By default, Read Barcode is On.



#SETUPE0  
Exit Setup



#SETUPE1  
Enter Setup

## Decode Area

**Whole Area Decoding:** The scanner attempts to decode barcode(s) within its field of view, from the center to the periphery, and transmits the barcode that has been first decoded.

**Specific Area Decoding:** The scanner attempts to read barcode(s) within a specified decoding area and transmits the barcode that has been first decoded. This option allows the scanner to narrow its field of view to make sure it reads only those barcodes intended by the user. For instance, if multiple barcodes are placed closely together, specific area decoding in conjunction with appropriate pre-defined decoding area will insure that only the desired barcode is read.



@CADENA0  
\*\* Whole Area Decoding



@CADENA1  
Specific Area Decoding



@CADENA2  
Aimed Area Decoding(only WD2-BS50-SR supports)

If **Specific Area Decoding** is enabled, the scanner only reads barcodes that intersect the predefined decoding area. The default decoding area is an area of 40% top, 60% bottom, 40% left and 60% right of the scanner's field of view. You can define the decoding area using the **Top of Decoding Area**, **Bottom of Decoding Area**, **Left of Decoding Area** and **Right of Decoding Area** barcodes as well as numeric barcode(s) that represent(s) a desired percentage (0-100). The value of Bottom must be greater than that of Top; the value of Right must be greater than that of Left.



@CADTOP  
Top of Decoding Area



@CADBOT  
Bottom of Decoding Area



#SETUPE0  
Exit Setup




#SETUPE1  
Enter Setup



@CADLEF  
Left of Decoding Area



@CADRIG  
Right of Decoding Area



**E**  
xample

Program the scanner to only read Barcode 1 in the figure above by setting the decoding area to 10% top, 45% bottom, 15% left and 30% right:

1. Scan the **Enter Setup** barcode.
2. Scan the **Top of Decoding Area** barcode.
3. Scan the numeric barcode "0" from the "Digit Barcodes" section in Appendix.
4. Scan the **Save** barcode from the "Save/Cancel Barcodes" section in Appendix.
5. Scan the **Bottom of Decoding Area** barcode.
6. Scan the numeric barcodes "4" and "5" from the "Digit Barcodes" section in Appendix.
7. Scan the **Save** barcode from the "Save/Cancel Barcodes" section in Appendix.
8. Scan the **Top of Decoding Area** barcode.
9. Scan the numeric barcodes "1" and "0" from the "Digit Barcodes" section in Appendix.
10. Scan the **Save** barcode from the "Save/Cancel Barcodes" section in Appendix.
11. Scan the **Left of Decoding Area** barcode.
12. Scan the numeric barcode "0" from the "Digit Barcodes" section in Appendix.



#SETUPE0  
Exit Setup



#SETUPE1

## Enter Setup

---

13. Scan the **Save** barcode from the "Save/Cancel Barcodes" section in Appendix.
14. Scan the **Right of Decoding Area** barcode.
15. Scan the numeric barcodes "3" and "0" from the "Digit Barcodes" section in Appendix.
16. Scan the **Save** barcode from the "Save/Cancel Barcodes" section in Appendix.
17. Scan the **Left of Decoding Area** barcode.
18. Scan the numeric barcodes "1" and "5" from the "Digit Barcodes" section in Appendix.
19. Scan the **Save** barcode from the "Save/Cancel Barcodes" section in Appendix.
20. Scan the **Exit Setup** barcode.



#SETUPE0

## Exit Setup



#SETUPE1  
Enter Setup

## Image Flipping



@MIRROR0

**\*\* Do Not Flip**



@MIRROR1

**Flip Horizontally**



@MIRROR2

**Flip Vertically**



@MIRROR3

**Flip Horizontally & Vertically**

Example of image not flipped



Example of image flipped vertically



Example of image flipped horizontally



Example of image flipped horizontally & vertically



#SETUPE0  
Exit Setup



#SETUPE1  
Enter Setup

## Bad Read Message

Scan the appropriate barcode below to select whether or not to send a bad read message (user-programmable) when a good read does not occur before trigger release, or the decode session timeout expires, or the scanner receives the **Stop Scanning** command (For more information, see the “Serial Trigger Command” section in this chapter).



@NGRENA0  
**\*\* Bad Read Message OFF**



@NGRENA1  
**Bad Read Message ON**

## Set Bad Read Message

A bad read message can contain up to 7 characters (HEX values from 0x00 to 0xFF). To set a bad read message, scan the **Set Bad Read Message** barcode, the numeric barcodes representing the hexadecimal values of desired character(s) and the **Save** barcode. The default setting is “NG”.



@NGRSET  
**Set Bad Read Message**

**E**  
*xample*

**Set the bad read message to “F” (HEX: 0x46):**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set Bad Read Message** barcode.
3. Scan the numeric barcodes “4” and “6” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Exit Setup** barcode.



#SETUPE0  
Exit Setup



#SETUPE1  
Enter Setup

## Power Off



@PWROFF

**Power Off Scanner**

## Default Settings

### Factory Defaults

Scanning the following barcode can restore the scanner to the factory defaults. You may need to reset all parameters to the factory defaults when:

1. The scanner is not properly configured so that it fails to decode barcodes.
2. You forget previous configuration and want to avoid its impact.



@FACDEF

**\*\*Restore All Factory Defaults**

### Custom Defaults

Scanning the **Restore All Custom Defaults** barcode can reset all parameters to the custom defaults. Scanning the **Save as Custom Defaults** barcode can set the current settings as custom defaults.

Custom defaults are stored in the non-volatile memory.



@CUSSAV

**Save as Custom Defaults**



#SETUPE0

**Exit Setup**



#SETUPE1

**Enter Setup**

---



@CUSDEF

**Restore All Custom Defaults**



Restoring the scanner to the factory defaults will not remove the custom defaults from the scanner.

## Query Product Information

After scanning the barcode below, the product information (including product name, firmware version, decoder version, hardware version, product serial number, OEM serial number, manufacturing date and data formatter version) will be sent to the host device.



@QRYSYS

**Query Product Information**

## Query Product Name



@QRYPDN

**Query Product Name**



#SETUPE0

**Exit Setup**



#SETUPE1  
**Enter Setup**


---

### **Query Firmware Version**



@QRYFW  
**Query Firmware Version**

### **Query Decoder Version**



@QRYDCV  
**Query Decoder Version**

### **Query Bluetooth Version**




#QRYBFW  
**Query Bluetooth Version**

### **Query Hardware Version**



@QRYHWW  
**Query Hardware Version**

### **Query Product Serial Number**



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---



@QRYPSN

**Query Product Serial Number**

**Query OEM Serial Number**



@QRYESN

**Query OEM Serial Number**

**Query Manufacturing Date**



@QRYDAT

**Query Manufacturing Date**

**Query Data Formatter Version**



@QRYDFM

**Query Data Formatter Version**



#SETUPE0

**Exit Setup**



#SETUPE1  
Enter Setup

## Chapter 4 USB Interface

### Introduction

There are four options for USB connection:

- ✧ USB HID Keyboard: The scanner's transmission is simulated as USB keyboard input with no need for command configuration or a driver. Barcode data could be entered by the virtual keyboard directly and it is also convenient for the host device to receive data.
- ✧ USB CDC: It is compliant with the standard USB CDC class specifications defined by the USB-IF and allows the host device to receive data in the way as a serial port does. A driver is needed when using this feature.

### USB HID Keyboard

When the scanner is connected to the USB port on a host device, you can enable the USB HID Keyboard feature by scanning the barcode below. Then scanner's transmission will be simulated as USB keyboard input. The Host receives keystrokes on the virtual keyboard. It works on a Plug and Play basis and no driver is required.



@INTERF3  
\*\* USB HID Keyboard



If the host device allows keyboard input, then no extra software is needed for HID Keyboard input.



#SETUPE0  
Exit Setup



#SETUPE1

Enter Setup

---

## USB Country Keyboard Types

Keyboard layouts vary from country to country. The default setting is U.S. keyboard.



@KBWCTY0

\*\* U.S. (English)



@KBWCTY2

Brazil



@KBWCTY4

Czechoslovakia



@KBWCTY6

Finland (Swedish)



@KBWCTY1

Belgium



@KBWCTY3

Canada (French)



@KBWCTY5

Denmark



#SETUPE0

Exit Setup



#SETUPE1  
**Enter Setup**

---



@KBWCTY7  
**France**



@KBWCTY8  
**Germany/ Australia**



@KBWCTY9  
**Greece**



@KBWCTY10  
**Hungary**



@KBWCTY11  
**Israel (Hebrew)**



@KBWCTY12  
**Italy**



@KBWCTY13  
**Latin America/ South America**



@KBWCTY14  
**Netherlands (Dutch)**



#SETUPE0  
**Exit Setup**



#SETUPE1  
**Enter Setup**

---



@KBWCTY16  
**Poland**



@KBWCTY18  
**Romania**



@KBWCTY21  
**Slovakia**



@KBWCTY23  
**Sweden**



@KBWCTY15  
**Norway**



@KBWCTY17  
**Portugal**



@KBWCTY19  
**Russia**



@KBWCTY22  
**Spain**



#SETUPE0  
**Exit Setup**




#SETUPE1  
**Enter Setup**

---



@KBWCTY24  
**Switzerland (German)**



@KBWCTY25  
**Turkey F**



@KBWCTY26  
**Turkey Q**



@KBWCTY27  
**Britain**



@KBWCTY28  
**Japan**



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

## Beep on Unknown Character

Due to the differences in keyboard layouts, some characters contained in barcode data may be unavailable on the selected keyboard. As a result, the scanner fails to transmit the unknown characters.

Scan the appropriate barcode below to enable or disable the emission of beep when an unknown character is detected.



@KBWBUC0

**\*\* Do Not Beep on Unknown Character**



@KBWBUC1

**Beep on Unknown Character**

**E**  
*xample*

Supposing French keyboard (Country Code: 7) is selected and barcode data "ADF" is being dealt with, the keyboard will fail to locate the "Ð" (0xD0) character and the scanner will ignore the character and continue to process the next one.

**Do Not Beep on Unknown Character:** The scanner does not beep and the Host receives "AF".

**Beep on Unknown Character:** The scanner beeps and the Host still receives "AF".



If **Emulate ALT+Keypad ON** is selected, **Beep on Unknown Character** does not function.

## Emulate ALT+Keypad

When **Emulate ALT+Keypad** is turned on, any character is sent via the numeric keypad and overlook USB country keyboard type. This mode need to set **Code Page Option** and **Unicode Output**. **Code Page** determines the target



@SETUPE1

Enter Setup



#SETUPE1  
Enter Setup

language. **Unicode Output** determines the ASCII input to the host device.



@KBWALT0

**\*\* Emulate ALT+Keypad OFF**



@KBWALT1

**Emulate ALT+Keypad ON**



ASCII characters between 0x00~0x1F will be input in way of Function Key Mapping Set.



Since sending a character involves multiple keystroke emulations, this method appears less efficient.



Supposing **Emulate ALT+Keypad** is ON, **Unicode Encoding** is Off, and **Code Page 1252 (West European Latin)** is selected, barcode data "AÐF" (65/208/70) is sent as below:

"A" -- "ALT Make" + "065" + "ALT

Break" "Ð" -- "ALT Make" + "208"

+ "ALT Break"

"F" -- "ALT Make" + "070" + "ALT Break"



#SETUPE0  
Exit Setup



#SETUPE1

Enter Setup

## Code Page

Code pages define the mapping of character codes to characters. If the data received does not display with the proper characters, it may be because the barcode being scanned was created using a code page that is different from the one the host program is expecting. If this is the case, select the code page with which the barcodes were created by scanning the appropriate barcode below. For PDF417, QR Code, Aztec and Data Matrix, besides setting the code page, you also need to set the character encoding in the “Character Encoding” section in Chapter 6. This feature is only effective when **Emulate ALT+Keypad** is turned on. The default setting is Code Page 1252(West European, Latin)



@KBWCPG0

**\*\* Code Page 1252 (West European Latin)**



@KBWCPG1

**Code Page 1251 (Cyrillic)**



@KBWCPG2

**Code Page 1250 (Central and East European Latin)**



@KBWCPG3

**Code Page 1253 (Greek)**



@KBWCPG4

**Code Page 1254 (Turkish)**



@KBWCPG5

**Code Page 1255 (Hebrew)**



@SETUPE1

Enter Setup



#SETUPE1

**Enter Setup**

---



#SETUPE0

**Exit Setup**



#SETUPE1

Enter Setup

---



@KBWCPG6

Code Page 1256 (Arabic)



@KBWCPG7

Code Page 1257 (Baltic)




@KBWCPG8

Code Page 1258 (Vietnamese)



@KBWCPG9

Code Page 936 (Simplified Chinese,  
GB2312,GBK)



@KBWCPG10

Code Page 950 (Traditional Chinese,  
Big5)



@KBWCPG11

Code Page 874(Thai)



@KBWCPG12

Code Page 932 (Japanese,Shift-JIS)



@SETUPE1

Enter Setup




#SETUPE1  
Enter Setup

## Unicode Encoding

Different host program may use different character encodings for handling incoming barcode data. For instance, Microsoft Office Word uses Unicode encoding and therefore you should turn **Unicode Encoding** on, whereas Microsoft Office Excel or Notepad uses Code Page encoding and therefore you should turn **Unicode Encoding** off. This feature is only effective when **Emulate ALT+Keypad** is turned on. The default setting is Off



@KBWCPU0  
\*\* Off



@KBWCPU1  
On

## Emulate Keypad with Leading Zero

You may turn this feature on to send character sequences sent over the numeric keypad as ISO characters which have a leading zero. For example, ASCII A transmits as "ALT MAKE" 0065 "ALT BREAK". This feature is only effective when **Emulate ALT+Keypad** is enabled.



@KBWALZ1  
\*\* On



@KBWALZ0  
Off



#SETUPE0  
Exit Setup



#SETUPE1

Enter Setup

## Function Key Mapping

When **Ctrl+ASCII Mode** is selected, function characters (0x00 - 0x1F) are sent as ASCII sequences. The default setting is Off.



@KBWFKM0

\*\* Disable



@KBWFKM1

**Ctrl+ASCII Mode**



@KBWFKM2

**Alt+Keypad Mode**

**E**  
*sample*

If **Ctrl+ASCII Mode** is selected and other parameters of USB HID Keyboard adopt factory defaults, barcode data "A<HT> (i.e. Horizontal Tab) F" (0x41/0x09/0x46) is sent as below:

"A" - Keystroke "A".

<HT> - "Ctrl Make" + Keystroke "I" + "Ctrl

Break" "F" - Keystroke "F"

For some text editors, "Ctrl I" means italic convert. So the output may be "AF".

If **Alt+Keypad Mode** is selected and other parameters of USB HID Keyboard adopt factory defaults, the data above is sent as below:

"A" - Keystroke "A".

<HT> - "Alt Make" + Keystrokes "009" + "Alt

Break" "F" - Keystroke "F"



@SETUPE1

Enter Setup



#SETUPE1

**Enter Setup**

---



#SETUPE0

**Exit Setup**



#SETUPE1

Enter Setup

**ASCII Function Key Mapping Table**

| ASCII Function | ASCII Value (HEX) | Function Key Mapping Disabled | Ctrl+ASCII |
|----------------|-------------------|-------------------------------|------------|
| NUL            | 00                | Null                          | Ctrl+@     |
| SOH            | 01                | Keypad Enter                  | Ctrl+A     |
| STX            | 02                | Caps Lock                     | Ctrl+B     |
| ETX            | 03                | ALT                           | Ctrl+C     |
| EOT            | 04                | Null                          | Ctrl+D     |
| ENQ            | 05                | CTRL                          | Ctrl+E     |
| ACK            | 06                | Null                          | Ctrl+F     |
| BEL            | 07                | Enter                         | Ctrl+G     |
| BS             | 08                | Left Arrow                    | Ctrl+H     |
| HT             | 09                | Horizontal Tab                | Ctrl+I     |
| LF             | 0A                | Down Arrow                    | Ctrl+J     |
| VT             | 0B                | Vertical Tab                  | Ctrl+K     |
| FF             | 0C                | Delete                        | Ctrl+L     |
| CR             | 0D                | Enter                         | Ctrl+M     |
| SO             | 0E                | Insert                        | Ctrl+N     |
| SI             | 0F                | Esc                           | Ctrl+O     |
| DLE            | 10                | F11                           | Ctrl+P     |
| DC1            | 11                | Home                          | Ctrl+Q     |
| DC2            | 12                | PrintScreen                   | Ctrl+R     |
| DC3            | 13                | Backspace                     | Ctrl+S     |
| DC4            | 14                | tab+shift                     | Ctrl+T     |
| NAK            | 15                | F12                           | Ctrl+U     |
| SYN            | 16                | F1                            | Ctrl+V     |
| ETB            | 17                | F2                            | Ctrl+W     |
| CAN            | 18                | F3                            | Ctrl+X     |
| EM             | 19                | F4                            | Ctrl+Y     |
| SUB            | 1A                | F5                            | Ctrl+Z     |
| ESC            | 11                | F6                            | Ctrl+[     |
| FS             | 1C                | F7                            | Ctrl+\     |
| GS             | 1D                | F8                            | Ctrl+]     |
| RS             | 1E                | F9                            | Ctrl+6     |
| US             | 1F                | F10                           | Ctrl+-     |



@SETUPE1

Enter Setup



#SETUPE1

**Enter Setup**

---



#SETUPE0

**Exit Setup**



#SETUPE1

Enter Setup

---

### ASCII Function Key Mapping Table (Continued)

The last five characters (0x1B~0x1F) in the table above apply to US keyboard layout only. The following chart provides the equivalents of these five characters for other countries.

| Country        | Ctrl+ASCII |        |         |        |        |  |
|----------------|------------|--------|---------|--------|--------|--|
| United States  | Ctrl+[     | Ctrl+\ | Ctrl+]  | Ctrl+6 | Ctrl+- |  |
| Belgium        | Ctrl+[     | Ctrl+< | Ctrl+]  | Ctrl+6 | Ctrl+- |  |
| Scandinavia    | Ctrl+8     | Ctrl+< | Ctrl+9  | Ctrl+6 | Ctrl+- |  |
| France         | Ctrl+^     | Ctrl+8 | Ctrl+\$ | Ctrl+6 | Ctrl+= |  |
| Germany        |            | Ctrl+Ã | Ctrl++  | Ctrl+6 | Ctrl+- |  |
| Italy          |            | Ctrl+\ | Ctrl++  | Ctrl+6 | Ctrl+- |  |
| Switzerland    |            | Ctrl+< | Ctrl+.. | Ctrl+6 | Ctrl+- |  |
| United Kingdom | Ctrl+[     | Ctrl+Ø | Ctrl+]  | Ctrl+6 | Ctrl+- |  |
| Denmark        | Ctrl+8     | Ctrl+\ | Ctrl+9  | Ctrl+6 | Ctrl+- |  |
| Norway         | Ctrl+8     | Ctrl+\ | Ctrl+9  | Ctrl+6 | Ctrl+- |  |
| Spain          | Ctrl+[     | Ctrl+\ | Ctrl+]  | Ctrl+6 | Ctrl+- |  |



@SETUPE1

Enter Setup



#SETUPE1  
Enter Setup

## Inter-Keystroke Delay


This parameter specifies the delay between emulated keystrokes. Scanning below barcodes to delay longer when the host device needs slower data transmission. The default setting is No Delay.



@KBWDLY0  
\*\* No Delay



@KBWDLY40  
Long Delay (40ms)



@KBWDLY20  
Short Delay (20ms)

## Caps Lock

The **Caps Lock ON** option can invert upper and lower case characters contained in barcode data. This inversion occurs regardless of the state of Caps Lock key on the host device's keyboard.



@KBWCAP0  
\*\* Caps Lock OFF (Non-Japanese keyboard)



@KBWCAP1  
Caps Lock ON (Non-Japanese keyboard)



Emulate ALT+Keypad ON/ Convert All to Upper Case/ Convert All to Lower Case prevails over Caps Lock ON.



#SETUPE0  
Exit Setup



#SETUPE1

Enter Setup

---

When the **Caps Lock ON** feature is selected, barcode data “AbC” is transmitted as “aBc”.



@SETUPE1

Enter Setup



#SETUPE1  
Enter Setup

## Convert Case

Scan the appropriate barcode below to convert all barcode data to your desired case.



@KBWCAS0  
\*\* No Case Conversion



@KBWCAS1  
Convert All to Upper Case



@KBWCAS2  
Convert All to Lower Case

**E**  
xample

When the **Convert All to Lower Case** feature is enabled, barcode data “AbC” is transmitted as “abc”.



If **Emulate ALT+Keypad ON** is selected, **Convert All to Lower Case** and **Convert All to Upper Case** do not function.

## Emulate Numeric Keypad



#SETUPE0  
Exit Setup



#SETUPE1  
Enter Setup

---



**Do Not Emulate Numeric Keypad 1:** Sending a number (0-9) is emulated as keystroke(s) on main keyboard.

**Emulate Numeric Keypad 1:** Sending a number (0-9) is emulated as keystroke(s) on numeric keypad. The state of Num Lock on the simulated numeric keypad is determined by its equivalent on the host device. If Num Lock on the host device is turned off, the output of simulated numeric keypad is function key instead of number.

**Do Not Emulate Numeric Keypad 2:** Sending “+”, “—”, “\*” and “/” is emulated as keystroke(s) on main keyboard.

**Emulate Numeric Keypad 2:** Sending “+”, “—”, “\*” and “/” is emulated as keystroke(s) on numeric keypad.



@KBWNUM0

**\*\* Do Not Emulate Numeric Keypad 1**



@KBWNUM1

**Emulate Numeric Keypad 1**



@KBWNCH0



@SETUPE1  
Enter Setup



#SETUPE1  
Enter Setup

---

**\*\* Do Not Emulate Numeric Keypad 2**



@KBWNCH1

**Emulate Numeric Keypad 2**



**Emulate ALT+Keypad ON** prevails over **Emulate Numeric Keypad**.

**E**  
*xample*

Supposing the **Emulate Numeric Keypad 1** and **Emulate Numeric Keypad 2** features are enabled: if Num Lock on the host device is ON, "A4.5" is transmitted as "A4.5";

if Num Lock on the host device is OFF, "A4.5" is transmitted as follows:

1. "A" is sent as is because it is not included in numeric keypad;
2. "4" is sent as the function key "Cursor Move to Left";
3. "." is sent;
4. "5" is not sent as it does not correspond to any function key.

Finally the host device will get ".A"



#SETUPE0  
Exit Setup



#SETUPE1

Enter Setup

---

## Character "+", "-", "\*", "/" Adopt Numeric Keypad



@KBWNCH0

\*\* Off



@KBWNCH1

On

## Fast Mode

When **Fast Mode On** is selected, the scanner sends characters to the host faster. If the host drops characters, turn the Fast Mode off or change the polling rate to a bigger value.



@KBWFAS0

\*\* Fast Mode Off



@KBWFAS1

Fast Mode On

## Polling Rate

This parameter specifies the polling rate for a USB keyboard. The smaller value rate is, the faster characters transmission from scanner to the host. If the host drops characters, change the polling rate to a bigger value.



@SETUPE1


Enter Setup



#SETUPE1  
**Enter Setup**




@KBWPOR0  
**1ms**



@KBWPOR1  
**2ms**



@KBWPOR2  
**3ms**



@KBWPOR3  
**\*\* 4ms**



@KBWPOR4  
**5ms**



@KBWPOR5  
**6ms**



@KBWPOR6  
**7ms**



@KBWPOR7  
**8ms**



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---



@KBWPOR8

**9ms**



@KBWPOR9

**10ms**



@SETUPE1

**Enter Setup**



#SETUPE1  
Enter Setup

## USB CDC

If your scanner is connected to the USB port on a host device, the USB CDC feature allows the host device to receive data in the way as a serial port does. A driver is needed when using this feature. You may download it from our website at [www.newlandaidc.com](http://www.newlandaidc.com).



@INTERF8  
USB CDC

## VID/PID

USB uses VID (Vendor ID) and PID (Product ID) to identify and locate a device. The VID is assigned by USB Implementers Forum. Newland's vendor ID is 1EAB (Hex). A range of PIDs are used for each Newland product family. Every PID contains a base number and interface type (keyboard, COM port, etc.).

| Product | Interface        | PID (Hex) | PID (Dec) |
|---------|------------------|-----------|-----------|
| WD2     | USB HID Keyboard | 0022      | 0034      |
|         | USB CDC          | 0006      | 0006      |



#SETUPE0  
Exit Setup



#SETUPE1  
Enter Setup

## Chapter 5 Wireless Communication

### Operating Modes

The scanner provides the following operating modes. Scanning the Enter Setup Barcode to change the operating mode.

**Bluetooth HID Mode** allows your scanner to communicate with a remote host using Bluetooth. You must first pair your scanner to the host before these two Bluetooth devices can communicate with each other. All features available for USB HID Keyboard are applicable to Bluetooth HID.

**Note:** The pairing information in the scanner and the host need to be cleared before connecting with other Bluetooth devices

**Bluetooth BLE Mode** is Bluetooth low power consumption communication mode that communicates with the applications in the host based on Bluetooth SDK. In this mode, the scanner provides a serial transparent transmission service based on GATT service.



@INTERF10  
\*\*Bluetooth HID



@INTERF11  
Bluetooth BLE

### Clear Pairing Info on Scanner



@WLSCLP  
Clear Pairing Info on Scanner



@SETUPE1  
Enter Setup



#SETUPE1

**Enter Setup**

---



#SETUPE0

**Exit Setup**



#SETUPE1

Enter Setup

---

## Batch Mode

### Batch Mode Options

**Off:** The scanner attempts to transmit every barcode you scan. When you are out of service range, the scanned data will be lost.

**Automatic Batch Mode:** When in service range, the scanner attempts to transmit every barcode you scan. When out of range, the scanner stores the scanned data in the flash memory. Once you are back to service range, the scanner will automatically transmit the stored data and then remove it from the flash memory after transmission is done.

**Manual Batch Mode:** Scanned data will be stored in the flash memory no matter whether you are in service range or not. You may send the stored data to the host in the following ways: scan the Transmit Stored Data barcode. The scanner will automatically remove the stored data from the flash memory after transmission is done if the Auto Clear Stored Data after Transmission feature is turned on.



@VLSBAT0

\*\* Off



@VLSBAT2

Manual Batch Mode



@VLSBAT1

Automatic Batch Mode



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

---

## Prevent Same Barcode Storage

This feature is available only when scanning barcodes in the Automatic or Manual Batch mode.

**On:** The scanner discards the data and generates an error beep when encountering a barcode that has existed in the flash memory.

**Off:** The scanner stores the data when encountering a barcode that has existed in the flash memory.



@WLSSE0  
**\*\* Off**



@WLSSE1  
**On**



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

---


### Batch Mode Transmit Delay

Sometimes when multiple barcodes stored in the flash memory are sent to the host, the transmission of those barcodes is too fast for the application to process. To program a transmit delay between barcodes, scan one of the following delays.



@WLSBTD0

**\*\* No Transmit Delay (0ms)**



@WLSBTD50

**Short Transmit Delay (50ms)**



@WLSBTD100

**Medium Transmit Delay (100ms)**



@WLSBTD150

**Long Transmit Delay (150ms)**



@WLSBTD

**Custom Transmit Delay (0-10,000ms)**



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

## Example

### Set the batch mode transmit delay to 200ms:

1. Scan the **Enter Setup** barcode.
2. Scan the **Custom Transmit Delay** barcode.
3. Scan the numeric barcodes “2”, “0” and “0” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Exit Setup** barcode.

### End of Transmission Message for Batch Mode

You may scan the appropriate barcode below to select whether or not to send an end of transmission message (user-programmable) to notify the host when transmission of all stored data is done. This feature is only available to data transmission initiated manually under the Manual Batch mode.



@WLSBTT0

**\*\* End of Transmission Message Off**



@WLSBTT1

**End of Transmission Message On**

An end of transmission message can contain up to 10 characters (HEX values from 0x00 to 0xFF). To set an end of transmission message, scan the **Set End of Transmission Message** barcode, the numeric barcodes representing the hexadecimal values of desired character(s) and the **Save** barcode. The default setting is “EOT”.



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---



@WLSBTC

**Set End of Transmission Message**

**E**  
*xample*

Set the end of transmission message to “END” (HEX: 0x45, 0x4E, 0x44):

1. Scan the **Enter Setup** barcode.
2. Scan the **Set End of Transmission Message** barcode.
3. Scan the numeric barcodes “4”, “5”, “4”, “E”, “4” and “4” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Exit Setup** barcode.



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**

---

## Transmit Stored Data

You may scan the barcode below to send the stored data in the flash memory to the host. This feature is only available to the Manual Batch mode.



@WLSSBT

## Transmit Stored Data

You may scan the appropriate barcode below to choose whether to clear or keep the stored data in the flash memory after transmission. This feature is only available to the Manual Batch mode.



@WLSCLE0

**\*\* Off**



@WLSCLE1

**On**



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---

## Query/Clear Stored Data in Flash



@WLSQFC

**Query the Number of Stored Barcodes**



@WLSCLF

**Clear All Stored Data**



@SETUPE1

**Enter Setup**



#SETUPE1

**Enter Setup**

---

## Retransmission

If the Transmission feature is on, the scanner awaits an ACK response from the host following a data packet transmission, and resends the packet when it receives an NAK response or the retransmission timeout expires. Note that Data Packing must be enabled for this feature to function (See the “Data Packing Options” in Chapter 9 to learn how to enable it).



@WLSRTE0

**\*\* Retransmission Off**



@WLSRTE1

**Retransmission On**



#SETUPE0

**Exit Setup**



#SETUPE1

**Enter Setup**

---

## Transmission Timeout

This specifies the amount of time the scanner waits for an ACK response from the host following a data packet transmission. It is programmable in 1ms increments from 200ms to 10,000ms. The default value is 200ms. Note that the Retransmission feature must be turned on for this to function.



@WLSRTT

**Set Transmission Timeout**

**E**  
*xample*

**Set the transmission timeout to 300ms:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set Transmission Timeout** barcode.
3. Scan the numeric barcodes “3”, “0” and “0” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Exit Setup** barcode.



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**

## Retransmission Count

This parameter specifies the number of times the scanner resends a data packet when it awaits an ACK response from the host. The selection range is from 1 to 10 retransmissions. The default value is 3 (retransmissions). Note that the Retransmission feature must be turned on for this to function.



@WLSRTN  
**Set Retransmission Count**

**E**  
*sample*

**Set the retransmission count to 5:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set Retransmission Timeout** barcode.
3. Scan the numeric barcodes "3", "0" and "0" from the "Digit Barcodes" section in Appendix.
4. Scan the **Save** barcode from the "Save/Cancel Barcodes" section in Appendix.
5. Scan the **Exit Setup** barcode.



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

---

## Auto Power-Off Timeout

Auto Power-off Timeout specifies the amount of time it takes before the scanner automatically powers off from inactivity.



@WLSAPO0

**\*\* 5 Minutes**



@WLSAPO2

**20 Mintues**



@WLSAPO4

**60 Minutes**



@WLSAPO1

**10 Minutes**



@WLSAPO3

**30 Mintues**



@WLSAPO5

**Disable Auto Power-off**



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

## Set Scanner Name

You may scan the below barcode to set the name of your scanner. The maximum length is 5 characters (HEX values from 0x20 to 0x7E). The default scanner name is "00000".



@WLSNAM  
Scanner Name

**E**  
*xample*

If setting the scanner name as "0AB00":

1. Scan the Enter Setup barcode
2. Scan the Scanner Name barcode
3. Scan the numeric barcode "3" "0" "4" "1" "4" "2" from the "Digit Barcodes" section in Appendix
4. Scan the **Save** barcode from the "Save/Cancel Barcodes" section in Appendix
5. Scan the Exit Setup barcode



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

## Chapter 6 Symbologies

### Introduction

Every symbology (barcode type) has its own unique attributes. This chapter provides programming barcodes for configuring the scanner so that it can identify various symbologies. It is recommended to disable those that are rarely used to increase the efficiency of the scanner.

### Global Settings

#### Enable/Disable All Symbologies

If the **Disable All Symbologies** feature is enabled, the scanner will not be able to read any non-programming barcodes except the programming barcodes.



@ALLENA1

Enable All Symbologies



@ALLENA0

Disable All Symbologies

#### Enable/Disable 1D Symbologies



@ALL1DC1

Enable 1D Symbologies



@ALL1DC0



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

**Disable 1D Symbolologies**

## **Enable/Disable 2D Symbolologies**



@ALL2DC1

**Enable 2D Symbolologies**



@ALL2DC0

**Disable 2D Symbolologies**

## **Enable/Disable Postal Symbolologies**



@ALLPST1

**Enable Postal Symbolologies**



@ALLPST0

**Disable Postal Symbolologies**



#SETUPE0

**Exit Setup**



#SETUPE1

**Enter Setup**

---

## Code 128

### Restore Factory Defaults



@128DEF

**Restore the Factory Defaults of Code 128**

### Enable/Disable Code 128



@128ENA1

**\*\* Enable Code 128**



@128ENA0

**Disable Code 128**



If the scanner fails to identify Code 128 barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable Code 128** barcode.

### Set Length Range for Code 128

The scanner can be configured to only decode Code 128 barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**



@128MIN

**Set the Minimum Length (Default: 1)**



@128MAX

**Set the Maximum Length (Default: 48)**



If minimum length is set to be greater than maximum length, the scanner only decodes Code 128 barcodes with either the minimum or maximum length. If minimum length is same as maximum length, only Code 128 barcodes with that length are to be decoded.



**Set the scanner to decode Code 128 barcodes containing between 8 and 12 characters:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---

## **EAN-8**

### **Restore Factory Defaults**



@EA8DEF

**Restore the Factory Defaults of EAN-8**

### **Enable/Disable EAN-8**



@EA8ENA1

**\*\* Enable EAN-8**



@EA8ENA0

**Disable EAN-8**



If the scanner fails to identify EAN-8 barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable EAN-8** barcode.

### **Transmit Check Character**

EAN-8 is 8 digits in length with the last one as its check character used to verify the integrity of the data.



@EA8CHK2

**\*\* Transmit EAN-8 Check Character**




@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**



@EA8CHK1

**Do Not Transmit EAN-8 Check Character**

## 2-Digit Add-On Code

An EAN-8 barcode can be augmented with a two-digit add-on code to form a new one. In the example below, the part surrounded by blue dotted line is an EAN-8 barcode while the part circled by red dotted line is a two-digit add-on code.



@EA8AD20

**\*\* Disable 2-Digit Add-On Code**



@EA8AD21

**Enable 2-Digit Add-On Code**



**Disable 2-Digit Add-On Code:** The scanner decodes EAN-8 and ignores the add-on code when presented with an EAN-8 plus 2-digit add-on barcode. It can also decode EAN-8 barcodes without 2-digit add-on codes.

**Enable 2-Digit Add-On Code:** The scanner decodes a mix of EAN-8 barcodes with and without 2-digit add-on codes.



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

---

### 5-Digit Add-On Code

An EAN-8 barcode can be augmented with a five-digit add-on code to form a new one. In the example below, the part surrounded by blue dotted line is an EAN-8 barcode while the part circled by red dotted line is a five-digit add-on code.



@EA8AD50

**\*\* Disable 5-Digit Add-On Code**



@EA8AD51

**Enable 5-Digit Add-On Code**



**Disable 5-Digit Add-On Code:** The scanner decodes EAN-8 and ignores the add-on code when presented with an EAN-8 plus 5-digit add-on barcode. It can also decode EAN-8 barcodes without 5-digit add-on codes.

**Enable 5-Digit Add-On Code:** The scanner decodes a mix of EAN-8 barcodes with and without 5-digit add-on codes.



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

### Add-On Code Required

When **EAN-8 Add-On Code Required** is selected, the scanner will only read EAN-8 barcodes that contain add-on codes.



@EA8REQ0

**\*\* EAN-8 Add-On Code Not Required**



@EA8REQ1

**EAN-8 Add-On Code Required**

### Convert EAN-8 to EAN-13

**Convert EAN-8 to EAN-13:** Convert EAN-8 decoded data to EAN-13 format before transmission. After conversion, the data follows EAN-13 format and is affected by EAN-13 programming selections (e.g., Check Character).

**Do Not Convert EAN-8 to EAN-13:** EAN-8 decoded data is transmitted as EAN-8 data, without conversion.



@EA8EXP0

**\*\* Do Not Convert EAN-8 to EAN-13**



@EA8EXP1

**Convert EAN-8 to EAN-13**



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**

## EAN-13

### Restore Factory Defaults



@E13DEF

**Restore the Factory Defaults of EAN-13**

### Enable/Disable EAN-13



@E13ENA1

**\*\* Enable EAN-13**



@E13ENA0

**Disable EAN-13**



If the scanner fails to identify EAN-13 barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable EAN-13** barcode.

### Transmit Check Character



@E13CHK2



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

**\*\* Transmit EAN-13 Check Character**



@E13CHK1

**Do Not Transmit EAN-13 Check Character**

## 2-Digit Add-On Code

An EAN-13 barcode can be augmented with a two-digit add-on code to form a new one. In the example below, the part surrounded by blue dotted line is an EAN-13 barcode while the part circled by red dotted line is a two-digit add-on code.



@E13AD20

**\*\* Disable 2-Digit Add-On Code**



@E13AD21

**Enable 2-Digit Add-On Code**



**Disable 2-Digit Add-On Code:** The scanner decodes EAN-13 and ignores the add-on code when presented with an EAN-13 plus 2-digit add-on barcode. It can also decode EAN-13 barcodes without 2-digit add-on codes.

**Enable 2-Digit Add-On Code:** The scanner decodes a mix of EAN-13 barcodes with and without 2-digit add-on codes.

## 5-Digit Add-On Code

An EAN-13 barcode can be augmented with a five-digit add-on code to form a new one. In the example below, the



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

part surrounded by blue dotted line is an EAN-13 barcode while the part circled by red dotted line is a five-digit add-on code.



@E13AD50

**\*\* Disable 5-Digit Add-On Code**



@E13AD51

**Enable 5-Digit Add-On Code**



**Disable 5-Digit Add-On Code:** The scanner decodes EAN-13 and ignores the add-on code when presented with an EAN-13 plus 5-digit add-on barcode. It can also decode EAN-13 barcodes without 5-digit add-on codes.

**Enable 5-Digit Add-On Code:** The scanner decodes a mix of EAN-13 barcodes with and without 5-digit add-on codes.



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

## Add-On Code Required

When **EAN-13 Add-On Code Required** is selected, the scanner will only read EAN-13 barcodes that contain add-on codes.



@E13REQ0

**\*\* EAN-13 Add-On Code Not  
Required**



@E13REQ1

**EAN-13 Add-On Code Required**

## EAN-13 Beginning with 290 Add-On Code Required

This setting programs the scanner to require an add-on code (2-digit or 5-digit) on EAN-13 barcodes that begin with "290". The following settings can be programmed:

**Require Add-On Code:** All EAN-13 barcodes that begin with "290" must have a 2-digit or 5-digit add-on code. The EAN-13 barcode with the add-on code is then transmitted. If the required add-on code is not found, the EAN-13 barcode is discarded.

**Do Not Require Add-On Code:** If you have selected **Require Add-On Code**, and you want to disable this feature, scan **Do Not Require Add-On Code**. EAN-13 barcodes are handled, depending on your selection for the "Add-On Code Required" feature.



@E132900

**\*\* Do Not Require Add-On Code**



@E132901

**Require Add-On Code**



@SETUPE1

Enter Setup



#SETUPE1  
Enter Setup

## EAN-13 Beginning with 378/379 Add-On Code Required

This setting programs the scanner to require an add-on code (2-digit or 5-digit) on EAN-13 barcodes that begin with a “378” or “379”. The following settings can be programmed:

**Require Add-On Code:** All EAN-13 barcodes that begin with a “378” or “379” must have a 2-digit or 5-digit add-on code. The EAN-13 barcode with the add-on code is then transmitted. If the required add-on code is not found, the EAN-13 barcode is discarded.

**Do Not Require Add-On Code:** If you have selected **Require Add-On Code**, and you want to disable this feature, scan **Do Not Require Add-On Code**. EAN-13 barcodes are handled, depending on your selection for the “Add-On Code Required” feature.



@E133780

\*\* Do Not Require Add-On Code



@E133781

Require Add-On Code



#SETUPE0  
Exit Setup



#SETUPE1

Enter Setup

---

## EAN-13 Beginning with 414/419 Add-On Code Required

This setting programs the scanner to require an add-on code (2-digit or 5-digit) on EAN-13 barcodes that begin with a “414” or “419”. The following settings can be programmed:

**Require Add-On Code:** All EAN-13 barcodes that begin with a “414” or “419” must have a 2-digit or 5-digit add-on code. The EAN-13 barcode with the add-on code is then transmitted. If the required add-on code is not found, the EAN-13 barcode is discarded.

**Do Not Require Add-On Code:** If you have selected **Require Add-On Code**, and you want to disable this feature, scan **Do Not Require Add-On Code**. EAN-13 barcodes are handled, depending on your selection for the “Add-On Code Required” feature.



@E134140

**\*\* Do Not Require Add-On Code**



@E134141

**Require Add-On Code**



@SETUPE1

Enter Setup



#SETUPE1  
Enter Setup

## EAN-13 Beginning with 434/439 Add-On Code Required

This setting programs the scanner to require an add-on code (2-digit or 5-digit) on EAN-13 barcodes that begin with a “434” or “439”. The following settings can be programmed:

**Require Add-On Code:** All EAN-13 barcodes that begin with a “434” or “439” must have a 2-digit or 5-digit add-on code. The EAN-13 barcode with the add-on code is then transmitted. If the required add-on code is not found, the EAN-13 barcode is discarded.

**Do Not Require Add-On Code:** If you have selected **Require Add-On Code**, and you want to disable this feature, scan **Do Not Require Add-On Code**. EAN-13 barcodes are handled, depending on your selection for the “Add-On Code Required” feature.



@E134340

**\*\* Do Not Require Add-On Code**



@E134341

**Require Add-On Code**



#SETUPE0  
Exit Setup



#SETUPE1

Enter Setup

---

### **EAN-13 Beginning with 977 Add-On Code Required**

This setting programs the scanner to require an add-on code (2-digit or 5-digit) on EAN-13 barcodes that begin with “977”. The following settings can be programmed:

**Require Add-On Code:** All EAN-13 barcodes that begin with “977” must have a 2-digit or 5-digit add-on code. The EAN-13 barcode with the add-on code is then transmitted. If the required add-on code is not found, the EAN-13 barcode is discarded.

**Do Not Require Add-On Code:** If you have selected **Require Add-On Code**, and you want to disable this feature, scan **Do Not Require Add-On Code**. EAN-13 barcodes are handled, depending on your selection for the “Add-On Code Required” feature.



@E139770

**\*\* Do Not Require Add-On Code**



@E139771

**Require Add-On Code**



@SETUPE1

Enter Setup



#SETUPE1  
Enter Setup

---

### **EAN-13 Beginning with 978 Add-On Code Required**

This setting programs the scanner to require an add-on code (2-digit or 5-digit) on EAN-13 barcodes that begin with “978”. The following settings can be programmed:

**Require Add-On Code:** All EAN-13 barcodes that begin with “978” must have a 2-digit or 5-digit add-on code. The EAN-13 barcode with the add-on code is then transmitted. If the required add-on code is not found, the EAN-13 barcode is discarded.

**Do Not Require Add-On Code:** If you have selected **Require Add-On Code**, and you want to disable this feature, scan **Do Not Require Add-On Code**. EAN-13 barcodes are handled, depending on your selection for the “Add-On Code Required” feature.



@E139780

**\*\* Do Not Require Add-On Code**



@E139781

**Require Add-On Code**



#SETUPE0  
Exit Setup



#SETUPE1

Enter Setup

---

### **EAN-13 Beginning with 979 Add-On Code Required**

This setting programs the scanner to require an add-on code (2-digit or 5-digit) on EAN-13 barcodes that begin with "979". The following settings can be programmed:

**Require Add-On Code:** All EAN-13 barcodes that begin with "979" must have a 2-digit or 5-digit add-on code. The EAN-13 barcode with the add-on code is then transmitted. If the required add-on code is not found, the EAN-13 barcode is discarded.

**Do Not Require Add-On Code:** If you have selected **Require Add-On Code**, and you want to disable this feature, scan **Do Not Require Add-On Code**. EAN-13 barcodes are handled, depending on your selection for the "Add-On Code Required" feature.



@E139790

**\*\* Do Not Require Add-On Code**



@E139791

**Require Add-On Code**



@SETUPE1


Enter Setup



#SETUPE1  
**Enter Setup**

## UPC-E

### Restore Factory Defaults



@UPEDEF

Restore the Factory Defaults of UPC-E

### Enable/Disable UPC-E



@UPEENA1

**\*\* Enable UPC-E**



@UPEEN11

**Enable UPC-E1**



@UPEEN00

**Disable UPC-E0**



@UPEEN01

**\*\* Enable UPC-E0**



@UPEENA0

**Disable UPC-E**



@UPEEN10



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---

**\*\*Disable UPC-E1**



If the scanner fails to identify **UPC-E/UPC-E0/UPC-E1** barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable UPC-E/UPC-E0/UPC-E1** barcode.



@SETUPE1

**Enter Setup**



#SETUPE1  
Enter Setup

## Transmit Check Character

UPC-E is 8 digits in length with the last one as its check character used to verify the integrity of the data.



@UPECHK2

**\*\* Transmit UPC-E Check Character**



@UPECHK1

**Do Not Transmit UPC-E Check Character**

## 2-Digit Add-On Code

A UPC-E barcode can be augmented with a two-digit add-on code to form a new one. In the example below, the part surrounded by blue dotted line is a UPC-E barcode while the part circled by red dotted line is a two-digit add-on code.



@UPEAD20

**\*\* Disable 2-Digit Add-On Code**



@UPEAD21

**Enable 2-Digit Add-On Code**



**Disable 2-Digit Add-On Code:** The scanner decodes UPC-E and ignores the add-on code when presented with a UPC-E plus 2-digit add-on barcode. It can also decode UPC-E barcodes without 2-digit add-on codes.



#SETUPE0  
Exit Setup



#SETUPE1

Enter Setup

**Enable 2-Digit Add-On Code:** The scanner decodes a mix of UPC-E barcodes with and without 2-digit add-on codes.

### 5-Digit Add-On Code

A UPC-E barcode can be augmented with a five-digit add-on code to form a new one. In the example below, the part surrounded by blue dotted line is a UPC-E barcode while the part circled by red dotted line is a five-digit add-on code.



@UPEAD50

**\*\* Disable 5-Digit Add-On Code**



@UPEAD51

**Enable 5-Digit Add-On Code**



**Disable 5-Digit Add-On Code:** The scanner decodes UPC-E and ignores the add-on code when presented with a UPC-E plus 5-digit add-on barcode. It can also decode UPC-E barcodes without 5-digit add-on codes.

**Enable 5-Digit Add-On Code:** The scanner decodes a mix of UPC-E barcodes with and without 5-digit add-on codes



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

### Add-On Code Required

When **UPC-E Add-On Code Required** is selected, the scanner will only read UPC-E barcodes that contain add-on codes.



@UPAREQ0

**\*\* UPC-E Add-On Code Not Required**



@UPAREQ1

**UPC-E Add-On Code Required**


### Transmit Preamble Character

Preamble characters (Country Code and System Character) can be transmitted as part of a UPC-E barcode. Select one of the following options for transmitting UPC-E preamble to the host device: transmit system character only, transmit system character and country code ("0" for USA), or transmit no preamble.



@UPEPRE1

**\*\* System Character**



@UPEPRE0

**No Preamble**



@UPEPRE2

**System Character & Country Code**



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

---

### Convert UPC-E to UPC-A

**Convert UPC-E to UPC-A:** Convert UPC-E (zero suppressed) decoded data to UPC-A format before transmission. After conversion, the data follows UPC-A format and is affected by UPC-A programming selections (e.g., Preamble, Check Character).

**Do Not Convert UPC-E to UPC-A:** UPC-E decoded data is transmitted as UPC-E data, without conversion.



@UPEEXP0

**\*\* Do Not Convert UPC-E to UPC-A**



@UPEEXP1

**Convert UPC-E to UPC-A**



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

## UPC-A

### Restore Factory Defaults



@UPADEF

**Restore the Factory Defaults of UPC-A**

### Enable/Disable UPC-A



@UPAENA1

**\*\* Enable UPC-A**



@UPAENA0

**Disable UPC-A**



If the scanner fails to identify UPC-A barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable UPC-A** barcode.

### Transmit Check Character

UPC-A is 13 digits in length with the last one as its check character used to verify the integrity of the data.



@UPACHK2

**\*\* Transmit UPC-A Check Character**



#SETUPE0  
**Exit Setup**



#SETUPE1  
Enter Setup



@UPACHK1

**Do Not Transmit UPC-A Check Character**

## 2-Digit Add-On Code

A UPC-A barcode can be augmented with a two-digit add-on code to form a new one. In the example below, the part surrounded by blue dotted line is a UPC-A barcode while the part circled by red dotted line is a two-digit add-on code.



@UPAAD20

**\*\* Disable 2-Digit Add-On Code**



@UPAAD21

**Enable 2-Digit Add-On Code**



**Disable 2-Digit Add-On Code:** The scanner decodes UPC-A and ignores the add-on code when presented with a UPC-A plus 2-digit add-on barcode. It can also decode UPC-A barcodes without 2-digit add-on codes.

**Enable 2-Digit Add-On Code:** The scanner decodes a mix of UPC-A barcodes with and without 2-digit add-on codes.



@SETUPE1

**Enter Setup**



#SETUPE1  
Enter Setup

## 5-Digit Add-On Code

A UPC-A barcode can be augmented with a five-digit add-on code to form a new one. In the example below, the part surrounded by blue dotted line is a UPC-A barcode while the part circled by red dotted line is a five-digit add-on code.



@UPAAD50  
**\*\* Disable 5-Digit Add-On Code**



@UPAAD51  
**Enable 5-Digit Add-On Code**



**Disable 5-Digit Add-On Code:** The scanner decodes UPC-A and ignores the add-on code when presented with a UPC-A plus 5-digit add-on barcode. It can also decode UPC-A barcodes without 5-digit add-on codes.

**Enable 5-Digit Add-On Code:** The scanner decodes a mix of UPC-A barcodes with and without 5-digit add-on codes.

## Add-On Code Required

When **UPC-A Add-On Code Required** is selected, the scanner will only read UPC-A barcodes that contain add-on codes.



#SETUPE0  
Exit Setup



#SETUPE1

Enter Setup

---



@UPAREQ0

**\*\* UPC-A Add-On Code Not Required**



@UPAREQ1

**UPC-A Add-On Code Required**

### Transmit Preamble Character

Preamble characters (Country Code and System Character) can be transmitted as part of a UPC-A barcode. Select one of the following options for transmitting UPC-A preamble to the host device: transmit system character only, transmit system character and country code ("0" for USA), or transmit no preamble.



@UPAPRE0

**No Preamble**



@UPAPRE1

**\*\* System Character**



@UPAPRE2

**System Character & Country Code**



@SETUPE1

Enter Setup



#SETUPE1  
Enter Setup

## Coupon

### UPC-A/EAN-13 with Extended Coupon Code

The following three types of coupon code + extended coupon code are supported:

1. UPC-A (starting with "5") + GS1-128
2. UPC-A (starting with "5") + GS1 Databar
3. EAN-13 (starting with "99") + GS1-128

Use the appropriate barcode below to enable or disable UPC-A/EAN-13 with Extended Coupon Code. When left on the default setting (**Off**), the scanner treats Coupon Codes and Extended Coupon Codes as single bar codes.

If you scan the **Allow Concatenation** code, when the scanner sees the coupon code and the extended coupon code in a single scan, it transmits both as separate symbologies. Otherwise, it transmits the first coupon code it reads.

If you scan the **Require Concatenation** code, the scanner must see and read the coupon code and extended coupon code in a single read to transmit the data. No data is output unless both codes are read.



@CPNENA0  
\*\* Off



@CPNENA1

**Allow Concatenation**



@CPNENA2

**Require Concatenation**



When using the UPC-A Coupon feature, please ensure that **System Character** or **System**



#SETUPE0  
Exit Setup



#SETUPE1

Enter Setup

**Character & Country Code** is selected for the “Transmit UPC-A Preamble Character” feature.

### Coupon GS1 Databar Output

If you scan coupons that have both UPC and GS1 Databar codes, you may wish to scan and output only the data from the GS1 Databar code. Scan the **GS1 Output On** barcode below to scan and output only the GS1 Databar code data.

When **GS1 Output Off** is selected, coupons that have both UPC and GS1 Databar codes are transmitted depending on your selection for the “UPC-A/EAN-13 with Extended Coupon Code” feature.



@CPNGS10

**\*\* GS1 Output Off**



@CPNGS11

**GS1 Output On**



When using the UPC-A Coupon feature, please ensure that **System Character** or **System Character & Country Code** is selected for the “Transmit UPC-A Preamble Character” feature.



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

## Interleaved 2 of 5

### Restore Factory Defaults



@I25DEF

**Restore the Factory Defaults of Interleaved 2 of 5**

### Enable/Disable Interleaved 2 of 5



@I25ENA1

**\*\* Enable Interleaved 2 of 5**



@I25ENA0

**Disable Interleaved 2 of 5**



If the scanner fails to identify Interleaved 2 of 5 barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable Interleaved 2 of 5** barcode.



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

---

## Set Length Range for Interleaved 2 of 5

The scanner can be configured to only decode Interleaved 2 of 5 barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.



@I25MIN

Set the Minimum Length (Default: 6)



@I25MAX

Set the Maximum Length (Default: 80)



If minimum length is set to be greater than maximum length, the scanner only decodes Interleaved 2 of 5 barcodes with either the minimum or maximum length. If minimum length is same as maximum length, only Interleaved 2 of 5 barcodes with that length are to be decoded.



**Set the scanner to decode Interleaved 2 of 5 barcodes containing between 8 and 12 characters:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.



@SETUPE1

Enter Setup



#SETUPE1

**Enter Setup**

---



#SETUPE0

**Exit Setup**



#SETUPE1

Enter Setup

## Check Character Verification

A check character is optional for Interleaved 2 of 5 and can be added as the last character. It is a calculated value used to verify the integrity of the data.

**Disable:** The scanner transmits Interleaved 2 of 5 barcodes as is.

**Do Not Transmit Check Character After Verification:** The scanner checks the integrity of all Interleaved 2 of 5 barcodes to verify that the data complies with the check character algorithm. Barcodes passing the check will be transmitted except the last digit, whereas those failing it will not be transmitted.

**Transmit Check Character After Verification:** The scanner checks the integrity of all Interleaved 2 of 5 barcodes to verify that the data complies with the check character algorithm. Barcodes passing the check will be transmitted, whereas those failing it will not be transmitted.

Since Interleaved 2 of 5 must always have an even number of digits, a zero may need to be added as the first digit when the check character is added. The check character is automatically generated when making Interleaved 2 of 5 barcodes.



@I25CHK0

**\*\*Disable**



@I25CHK1

**Do Not Transmit Check Character After Verification**



@I25CHK2

**Transmit Check Character After Verification**



If the **Do Not Transmit Check Character After Verification** option is enabled, Interleaved 2 of 5 barcodes with a length that is less than the configured minimum length after having the check character excluded will not be decoded. (For example, when the **Do Not Transmit Check Character After Verification** option is enabled and the minimum length is set to 4, Interleaved 2 of 5 barcodes



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

with a total length of 4 characters including the check character cannot be read.)

## ITF-14

ITF-14 is a special kind of Interleaved 2 of 5 with a length of 14 characters and the last character as the check character.

ITF-14 priority principle: For the Interleaved 2 of 5 barcodes with a length of 14 characters and the last character as the check character, the ITF-14 configurations shall take precedence over the Interleaved 2 of 5 settings.

### Restore Factory Defaults



@I14DEF

**Restore the Factory Defaults of ITF-14**

### Enable/Disable ITF-14



@I14ENA0

**\*\* Disable ITF-14**



@I14ENA1

**Enable ITF-14 But Do Not Transmit Check Character**



@I14ENA2

**Enable ITF-14 and Transmit Check Character**



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup



An example of the ITF-14 priority principle: when ITF-14 is enabled and Interleaved 2 of 5 is disabled, the scanner only decodes Interleaved 2 of 5 barcodes with a length of 14 characters and the last character as the check character.

## ITF-6

ITF-6 is a special kind of Interleaved 2 of 5 with a length of 6 characters and the last character as the check character.

ITF-6 priority principle: For the Interleaved 2 of 5 barcodes with a length of 6 characters and the last character as the check character, the ITF-6 configurations shall take precedence over the Interleaved 2 of 5 settings.

### Restore Factory Defaults



@IT6DEF

Restore the Factory Defaults of ITF-6

### Enable/Disable ITF-6



@IT6ENA0

\*\* Disable ITF-6



@IT6ENA1

Enable ITF-6 But Do Not Transmit Check Character



@IT6ENA2



@SETUPE1

Enter Setup



#SETUPE1

**Enter Setup**

---

### Enable ITF-6 and Transmit Check Character



An example of the ITF-6 priority principle: when ITF-6 is enabled and Interleaved 2 of 5 is disabled, the scanner only decodes Interleaved 2 of 5 barcodes with a length of 6 characters and the last character as the check character.



#SETUPE0

**Exit Setup**



#SETUPE1

**Enter Setup**

---

## Matrix 2 of 5

### Restore Factory Defaults



@M25DEF

**Restore the Factory Defaults of Matrix 2 of 5**

### Enable/Disable Matrix 2 of 5



@M25ENA1

**\*\* Enable Matrix 2 of 5**



@M25ENA0

**Disable Matrix 2 of 5**



If the scanner fails to identify Matrix 2 of 5 barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable Matrix 2 of 5** barcode.



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**

## Set Length Range for Matrix 2 of 5

The scanner can be configured to only decode Matrix 2 of 5 barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.



@M25MIN

**Set the Minimum Length (Default: 4)**



@M25MAX

**Set the Maximum Length (Default: 80)**



If minimum length is set to be greater than maximum length, the scanner only decodes Matrix 2 of 5 barcodes with either the minimum or maximum length. If minimum length is same as maximum length, only Matrix 2 of 5 barcodes with that length are to be decoded.

**E**  
*xample*

**Set the scanner to decode Matrix 2 of 5 barcodes containing between 8 and 12 characters:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---



@SETUPE1

**Enter Setup**



#SETUPE1  
Enter Setup

## Check Character Verification

A check character is optional for Matrix 2 of 5 and can be added as the last character. It is a calculated value used to verify the integrity of the data.

**Disable:** The scanner transmits Matrix 2 of 5 barcodes as is.

**Do Not Transmit Check Character After Verification:** The scanner checks the integrity of all Matrix 2 of 5 barcodes to verify that the data complies with the check character algorithm. Barcodes passing the check will be transmitted except the last digit, whereas those failing it will not be transmitted.

**Transmit Check Character After Verification:** The scanner checks the integrity of all Matrix 2 of 5 barcodes to verify that the data complies with the check character algorithm. Barcodes passing the check will be transmitted, whereas those failing it will not be transmitted.

Since Matrix 2 of 5 must always have an even number of digits, a zero may need to be added as the first digit when the check character is added. The check character is automatically generated when making Matrix 2 of 5 barcodes.



@M25CHK0  
\*\* Disable



@M25CHK1

**Do Not Transmit Check Character After Verification**



@M25CHK2

**Transmit Check Character After Verification**



If the **Do Not Transmit Check Character After Verification** option is enabled, Matrix 2 of 5 barcodes with a length that is less than the configured minimum length after having the check character excluded will not be decoded. (For example, when the **Do Not Transmit Check Character After Verification** option is enabled and the minimum length is set to 4, Matrix 2 of 5 barcodes with a total length of 4



#SETUPE0  
Exit Setup



#SETUPE1

**Enter Setup**

characters including the check character cannot be read.)

## Code 39

### Restore Factory Defaults



@C39DEF

**Restore the Factory Defaults of Code 39**

### Enable/Disable Code 39



@C39ENA1

**\*\* Enable Code 39**



@C39ENA0

**Disable Code 39**



If the scanner fails to identify Code 39 barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable Code 39** barcode.

### Set Length Range for Code 39

The scanner can be configured to only decode Code 39 barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**



@C39MIN

**Set the Minimum Length (Default: 1)**



@C39MAX

**Set the Maximum Length (Default: 48)**



If minimum length is set to be greater than maximum length, the scanner only decodes Code 39 barcodes with either the minimum or maximum length. If minimum length is same as maximum length, only Code 39 barcodes with that length are to be decoded.



**Set the scanner to decode Code 39 barcodes containing between 8 and 12 characters:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

---

## Check Character Verification

A check character is optional for Code 39 and can be added as the last character. It is a calculated value used to verify the integrity of the data.

**Disable:** The scanner transmits Code 39 barcodes as is.

**Do Not Transmit Check Character After Verification:** The scanner checks the integrity of all Code 39 barcodes to verify that the data complies with the check character algorithm. Barcodes passing the check will be transmitted except the last digit, whereas those failing it will not be transmitted.

**Transmit Check Character After Verification:** The scanner checks the integrity of all Code 39 barcodes to verify that the data complies with the check character algorithm. Barcodes passing the check will be transmitted, whereas those failing it will not be transmitted.



@C39CHK0

**\*\* Disable**



@C39CHK1

**Do Not Transmit Check Character After Verification**



@C39CHK2

**Transmit Check Character After Verification**



If the **Do Not Transmit Check Character After Verification** option is enabled, Code 39 barcodes with a length that is less than the configured minimum length after having the check character excluded will not be decoded. (For example, when the **Do Not Transmit Check Character After Verification** option is enabled and the minimum length is set to 4, Code 39 barcodes with a total length of 4 characters including the check character cannot be read.)

---



@SETUPE1

Enter Setup



#SETUPE1

**Enter Setup**

---



#SETUPE0

**Exit Setup**



#SETUPE1

Enter Setup

---

### Transmit Start/Stop Character

Code 39 uses an asterisk (\*) for both the start and the stop characters. You can choose whether or not to transmit the start/stop characters by scanning the appropriate barcode below.



@C39TSC0

**\*\* Do Not Transmit Start/Stop Character**



@C39TSC1

**Transmit Start/Stop Character**

### Enable/Disable Code 39 Full ASCII

The scanner can be configured to identify all ASCII characters by scanning the appropriate barcode below.



@C39ASC0

**\*\* Disable Code 39 Full ASCII**



@C39ASC1

**Enable Code 39 Full ASCII**

### Enable/Disable Code 32 (Italian Pharma Code)

Code 32 is a variant of Code 39 used by the Italian pharmaceutical industry. Scan the appropriate bar code below to enable or disable Code 32. Code 39 must be enabled and Code 39 check character verification must be disabled for this parameter to function.



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

---



@C39E320  
**\*\* Disable Code 32**



@C39E321  
**Enable Code 32**



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

---

## Code 32 Prefix

Scan the appropriate barcode below to enable or disable adding the prefix character "A" to all Code 32 barcodes.

Code 32 must be enabled for this parameter to function.



@C39S320

**\*\* Disable Code 32 Prefix**



@C39S321

**Enable Code 32 Prefix**

## Transmit Code 32 Start/Stop Character

Code 32 must be enabled for this parameter to function.



@C39T320

**\*\* Do Not Transmit Code 32 Start/Stop Character**



@C39T321

**Transmit Code 32 Start/Stop Character**



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

---

### **Transmit Code 32 Check Character**

Code 32 must be enabled for this parameter to function.




@C39C320

**\*\* Do Not Transmit Code 32 Check Character**



@C39C321

**Transmit Code 32 Check Character**



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---

## Codabar

### Restore Factory Defaults



@CBADEF

**Restore the Factory Defaults of Codabar**

### Enable/Disable Codabar



@CBAENA1

**\*\* Enable Codabar**



@CBAENA0

**Disable Codabar**



If the scanner fails to identify Codabar barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable Codabar** barcode.



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**

## Set Length Range for Codabar

The scanner can be configured to only decode Codabar barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.



**Set the Minimum Length (Default: 2)**



**Set the Maximum Length (Default: 60)**



If minimum length is set to be greater than maximum length, the scanner only decodes Codabar barcodes with either the minimum or maximum length. If minimum length is same as maximum length, only Codabar barcodes with that length are to be decoded.



### Set the scanner to decode Codabar barcodes containing between 8 and 12 characters:

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---



@SETUPE1

**Enter Setup**



#SETUPE1  
Enter Setup

## Check Character Verification

A check character is optional for Codabar and can be added as the last character. It is a calculated value used to verify the integrity of the data.

**Disable:** The scanner transmits Codabar barcodes as is.

**Do Not Transmit Check Character After Verification:** The scanner checks the integrity of all Codabar barcodes to verify that the data complies with the check character algorithm. Barcodes passing the check will be transmitted except the last digit, whereas those failing it will not be transmitted.

**Transmit Check Character After Verification:** The scanner checks the integrity of all Codabar barcodes to verify that the data complies with the check character algorithm. Barcodes passing the check will be transmitted, whereas those failing it will not be transmitted.



@CBACHK0  
\*\* Disable



@CBACHK1

Do Not Transmit Check Character After Verification



@CBACHK2

Transmit Check Character After Verification



If the **Do Not Transmit Check Character After Verification** option is enabled, Codabar barcodes with a length that is less than the configured minimum length after having the check character excluded will not be decoded. (For example, when the **Do Not Transmit Check Character After Verification** option is enabled and the minimum length is set to 4, Codabar barcodes with a total length of 4 characters including the check character cannot be read.)



#SETUPE0  
Exit Setup



#SETUPE1

**Enter Setup**

---



@SETUPE1

**Enter Setup**



#SETUPE1  
Enter Setup

## Start/Stop Character

You can set the start/stop characters and choose whether or not to transmit the start/stop characters by scanning the appropriate barcode below.



@CBATSC0

**\*\* Do Not Transmit Start/Stop Character**



@CBATSC1

**Transmit Start/Stop Character**



@CBASCF0

**\*\* ABCD/ABCD as the Start/Stop Character**



@CBASCF1

**ABCD/TN\*E as the Start/Stop Character**



@CBASCF2

**abcd/abcd as the Start/Stop Character**



@CBASCF3

**abcd/tn\*e as the Start/Stop Character**



#SETUPE0  
Exit Setup



#SETUPE1

**Enter Setup**

---

## Code 93

### Restore Factory Defaults



@C93DEF

**Restore the Factory Defaults of Code 93**

### Enable/Disable Code 93



@C93ENA1

**Enable Code 93**



@C93ENA0

**\*\* Disable Code 93**



If the scanner fails to identify Code 93 barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable Code 93** barcode.

### Set Length Range for Code 93

The scanner can be configured to only decode Code 93 barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**



**Set the Minimum Length (Default: 1)**



**Set the Maximum Length (Default: 48)**



If minimum length is set to be greater than maximum length, the scanner only decodes Code 93 barcodes with either the minimum or maximum length. If minimum length is same as maximum length, only Code 93 barcodes with that length are to be decoded.



**Set the scanner to decode Code 93 barcodes containing between 8 and 12 characters:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.

## Check Character Verification

Check characters are optional for Code 93 and can be added as the last two characters, which are calculated values used to verify the integrity of the data.



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

**Disable:** The scanner transmits Code 93 barcodes as is.

**Do Not Transmit Check Character After Verification:** The scanner checks the integrity of all Code 93 barcodes to verify that the data complies with the check character algorithm. Barcodes passing the checks will be transmitted except the last two digits, whereas those failing them will not be transmitted.

**Transmit Check Character After Verification:** The scanner checks the integrity of all Code 93 barcodes to verify that the data complies with the check character algorithm. Barcodes passing the checks will be transmitted, whereas those failing them will not be transmitted.



@C93CHK0

**Disable**



@C93CHK1

**\*\* Do Not Transmit Check Character After Verification**



@C93CHK2

**Transmit Check Character After Verification**



If the **Do Not Transmit Check Character After Verification** option is enabled, Code 93 barcodes with a length that is less than the configured minimum length after having the two check characters excluded will not be decoded. (For example, when the **Do Not Transmit Check Character After Verification** option is enabled and the minimum length is set to 4, Code 93 barcodes with a total length of 4 characters including the two check characters cannot be read.)



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

## China Post 25


### Restore Factory Defaults



@CHPDEF

**Restore the Factory Defaults of China Post 25**

### Enable/Disable China Post 25



@CHPEN A1

**Enable China Post 25**



@CHPEN A0

**\*\* Disable China Post 25**



If the scanner fails to identify China Post 25 barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable China Post 25** barcode.

### Set Length Range for China Post 25

The scanner can be configured to only decode China Post 25 barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.




#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---



@CHPMIN

**Set the Minimum Length (Default: 1)**



@CHPMAX

**Set the Maximum Length (Default: 48)**



If minimum length is set to be greater than maximum length, the scanner only decodes China Post 25 barcodes with either the minimum or maximum length. If minimum length is same as maximum length, only China Post 25 barcodes with that length are to be decoded.



**Set the scanner to decode China Post 25 barcodes containing between 8 and 12 characters:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.

## Check Character Verification

A check character is optional for China Post 25 and can be added as the last character. It is a calculated value used to verify the integrity of the data.

---



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**

**Disable:** The scanner transmits China Post 25 barcodes as is.

**Do Not Transmit Check Character After Verification:** The scanner checks the integrity of all China Post 25 barcodes to verify that the data complies with the check character algorithm. Barcodes passing the check will be transmitted except the last digit, whereas those failing it will not be transmitted.

**Transmit Check Character After Verification:** The scanner checks the integrity of all China Post 25 barcodes to verify that the data complies with the check character algorithm. Barcodes passing the check will be transmitted, whereas those failing it will not be transmitted.



@CHPCHK0  
**\*\* Disable**



@CHPCHK1

**Do Not Transmit Check Character After Verification**



@CHPCHK2

**Transmit Check Character After Verification**



If the **Do Not Transmit Check Character After Verification** option is enabled, China Post 25 barcodes with a length that is less than the configured minimum length after having the check character excluded will not be decoded. (For example, when the **Do Not Transmit Check Character After Verification** option is enabled and the minimum length is set to 4, China Post 25 barcodes with a total length of 4 characters including the check character cannot be read.)



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---

## GS1-128 (UCC/EAN-128)

### Restore Factory Defaults



@GS1DEF

**Restore the Factory Defaults of GS1-128**

### Enable/Disable GS1-128



@GS1ENA1

**\*\* Enable GS1-128**



@GS1ENA0

**Disable GS1-128**



If the scanner fails to identify GS1-128 barcodes, you may first try this solution by scanning the **EnterSetup** barcode and then **Enable GS1-128** barcode.

### Set Length Range for GS1-128

The scanner can be configured to only decode GS1-128 barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**



@GS1MIN

**Set the Minimum Length (Default: 1)**



@GS1MAX

**Set the Maximum Length (Default: 48)**



If minimum length is set to be greater than maximum length, the scanner only decodes GS1-128 barcodes with either the minimum or maximum length. If minimum length is same as maximum length, only GS1-128 barcodes with that length are to be decoded.



**Set the scanner to decode GS1-128 barcodes containing between 8 and 12 characters:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---

## GS1 Databar (RSS)

### Restore Factory Defaults



@RSSDEF

**Restore the Factory Defaults of GS1 Databar**

### Enable/Disable GS1 Databar



@RSSENA1

**\*\* Enable GS1 Databar**



@RSSENA0

**Disable GS1 Databar**



If the scanner fails to identify GS1 Databar barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable GS1 Databar** barcode.

### Transmit Application Identifier "01"



@RSSTAI1

**\*\* Transmit Application Identifier "01"**



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**



@RSSTAI0

**Do Not Transmit Application Identifier "01"**

## GS1 Composite (EAN-UCC Composite)

### Restore Factory Defaults



@CPTDEF

**Restore the Factory Defaults of GS1 Composite**

### Enable/Disable GS1 Composite



@CPTENA1

**Enable GS1 Composite**



@CPTENA0

**\*\* Disable GS1 Composite**



If the scanner fails to identify GS1 Composite barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable GS1 Composite** barcode.

### Enable/Disable UPC/EAN Composite



#SETUPE0

**Exit Setup**



#SETUPE1

**Enter Setup**

---



@CPTUPC1

**Enable UPC/EAN Composite**



@CPTUPC0

**\*\* Disable UPC/EAN Composite**



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**

## Code 11

### Restore Factory Defaults



@C11DEF

**Restore the Factory Defaults of Code 11**

### Enable/Disable Code 11



@C11ENA1

**\*\* Enable Code 11**



@C11ENA0

**Disable Code 11**



If the scanner fails to identify Code 11 barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable Code 11** barcode.

### Set Length Range for Code 11

The scanner can be configured to only decode Code 11 barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---



@C11MIN

**Set the Minimum Length (Default: 4)**



@C11MAX

**Set the Maximum Length (Default: 48)**



If minimum length is set to be greater than maximum length, the scanner only decodes Code 11 barcodes with either the minimum or maximum length. If minimum length is same as maximum length, only Code 11 barcodes with that length are to be decoded.



**Set the scanner to decode Code 11 barcodes containing between 8 and 12 characters:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.

## Check Character Verification

Check characters are optional for Code 11 and can be added as the last one or two characters, which are calculated



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**

values used to verify the integrity of the data.

If the **Disable** option is enabled, the scanner transmits Code 11 barcodes as is.



@C11CHK0  
**Disable**



@C11CHK1  
**\*\* One Check Character, MOD11**



@C11CHK2  
**Two Check Characters, MOD11/MOD11**



@C11CHK3  
**Two Check Characters, MOD11/MOD9**



@C11CHK4  
**One Check Character, MOD11  
(Len<=10) Two Check Characters,  
MOD11/MOD11(Len>10)**



@C11CHK5  
**One Check Character, MOD11  
(Len<=10) Two Check Characters,  
MOD11/MOD9 (Len>10)**

**Transmit Check Character**



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

---



@C11TCK0

**\*\* Do Not Transmit Code 11 Check Character**



@C11TCK1

**Transmit Code 11 Check Character**



If you select a check character algorithm and the **Do Not Transmit Check Character** option, Code 11 barcodes with a length that is less than the configured minimum length after having the check character(s) excluded will not be decoded. (For example, when the **One Check Character**, **MOD11** and **Do Not Transmit Check Character** options are enabled and the minimum length is set to 4, Code 11 barcodes with a total length of 4 characters including the check character cannot be read.)



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

## ISBN

### Restore Factory Defaults



@ISBDEF

**Restore the Factory Defaults of ISBN**

### Enable/Disable ISBN



@ISBENA1

**Enable ISBN**



@ISBENA0

**\*\*Disable ISBN**



If the scanner fails to identify ISBN barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable ISBN** barcode.

### Set ISBN Format



@ISBT101

**\*\* ISBN-10**



@ISBT100



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

---

ISBN-13



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

## ISSN

### Restore Factory Defaults



@ISSDEF

**Restore the Factory Defaults of ISSN**

### Enable/Disable ISSN



@ISSENA1

**Enable ISSN**



@ISSENA0

**\*\* Disable ISSN**



If the scanner fails to identify ISSN barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable ISSN** barcode.



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---

## Industrial 25

### Restore Factory Defaults



@L25DEF

**Restore the Factory Defaults of Industrial 25**

### Enable/Disable Industrial 25



@L25ENA1

**Enable Industrial 25**



@L25ENA0

**\*\*Disable Industrial 25**



If the scanner fails to identify Industrial 25 barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable Industrial 25** barcode.

### Set Length Range for Industrial 25

The scanner can be configured to only decode Industrial 25 barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.

---



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**



**Set the Minimum Length (Default: 6)**



**Set the Maximum Length (Default: 48)**



If minimum length is set to be greater than maximum length, the scanner only decodes Industrial 25 barcodes with either the minimum or maximum length. If minimum length is same as maximum length, only Industrial 25 barcodes with that length are to be decoded.



**Set the scanner to decode Industrial 25 barcodes containing between 8 and 12 characters:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.

## Check Character Verification

A check character is optional for Industrial 25 and can be added as the last character. It is a calculated value used to verify the integrity of the data.



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

**Disable:** The scanner transmits Industrial 25 barcodes as is.

**Do Not Transmit Check Character After Verification:** The scanner checks the integrity of all Industrial 25 barcodes to verify that the data complies with the check character algorithm. Barcodes passing the check will be transmitted except the last digit, whereas those failing it will not be transmitted.

**Transmit Check Character After Verification:** The scanner checks the integrity of all Industrial 25 barcodes to verify that the data complies with the check character algorithm. Barcodes passing the check will be transmitted, whereas those failing it will not be transmitted.



@L25CHK0

**\*\* Disable**



@L25CHK1

**Do Not Transmit Check Character After Verification**



@L25CHK2

**Transmit Check Character After Verification**



If the **Do Not Transmit Check Character After Verification** option is enabled, Industrial 25 barcodes with a length that is less than the configured minimum length after having the check character excluded will not be decoded. (For example, when the **Do Not Transmit Check Character After Verification** option is enabled and the minimum length is set to 4, Industrial 25 barcodes with a total length of 4 characters including the check character cannot be read.)



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

## Standard 25

### Restore Factory Defaults



@S25DEF

**Restore the Factory Defaults of Standard 25**

### Enable/Disable Standard 25



@S25ENA1

**Enable Standard 25**



@S25ENA0

**\*\* Disable Standard 25**



If the scanner fails to identify Standard 25 barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable Standard 25** barcode.

### Set Length Range for Standard 25

The scanner can be configured to only decode Standard 25 barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---



@S25MIN

**Set the Minimum Length (Default: 6)**



@S25MAX

**Set the Maximum Length (Default: 48)**



If minimum length is set to be greater than maximum length, the scanner only decodes Standard 25 barcodes with either the minimum or maximum length. If minimum length is same as maximum length, only Standard 25 barcodes with that length are to be decoded.



**Set the scanner to decode Standard 25 barcodes containing between 8 and 12 characters:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.

### **Check Character Verification**

A check character is optional for Standard 25 and can be added as the last character. It is a calculated value used to verify the integrity of the data.

---



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**

**Disable:** The scanner transmits Standard 25 barcodes as is.

**Do Not Transmit Check Character After Verification:** The scanner checks the integrity of all Standard 25 barcodes to verify that the data complies with the check character algorithm. Barcodes passing the check will be transmitted except the last digit, whereas those failing it will not be transmitted.

**Transmit Check Character After Verification:** The scanner checks the integrity of all Standard 25 barcodes to verify that the data complies with the check character algorithm. Barcodes passing the check will be transmitted, whereas those failing it will not be transmitted.



@S25CHK0  
**\*\* Disable**



@S25CHK1

**Do Not Transmit Check Character After Verification**



@S25CHK2

**Transmit Check Character After Verification**



If the **Do Not Transmit Check Character After Verification** option is enabled, Standard 25 barcodes with a length that is less than the configured minimum length after having the check character excluded will not be decoded. (For example, when the **Do Not Transmit Check Character After Verification** option is enabled and the minimum length is set to 4, Standard 25 barcodes with a total length of 4 characters including the check character cannot be read.)



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---

## Plessey

### Restore Factory Defaults



@PLYDEF

**Restore the Factory Defaults of Plessey**

### Enable/Disable Plessey



@PLYENA1

**Enable Plessey**



@PLYENA0

**\*\* Disable Plessey**



If the scanner fails to identify Plessey barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable Plessey** barcode.

### Set Length Range for Plessey

The scanner can be configured to only decode Plessey barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**



@PLYMIN

**Set the Minimum Length (Default: 4)**



@PLYMAX

**Set the Maximum Length (Default: 48)**



If minimum length is set to be greater than maximum length, the scanner only decodes Plessey barcodes with either the minimum or maximum length. If minimum length is same as maximum length, only Plessey barcodes with that length are to be decoded.



**Set the scanner to decode Plessey barcodes containing between 8 and 12 characters:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.

## Check Character Verification

Check characters are optional for Plessey and can be added as the last two characters, which are calculated values used to verify the integrity of the data.



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

**Disable:** The scanner transmits Plessey barcodes as is.

**Do Not Transmit Check Character After Verification:** The scanner checks the integrity of all Plessey barcodes to verify that the data complies with the check character algorithm. Barcodes passing the checks will be transmitted except the last two digits, whereas those failing them will not be transmitted.

**Transmit Check Character After Verification:** The scanner checks the integrity of all Plessey barcodes to verify that the data complies with the check character algorithm. Barcodes passing the checks will be transmitted, whereas those failing them will not be transmitted.



@PLYCHK0

**\*\* Disable**



@PLYCHK1

**Do Not Transmit Check Character After Verification**



@PLYCHK2

**Transmit Check Character After Verification**



If the **Do Not Transmit Check Character After Verification** option is enabled, Plessey barcodes with a length that is less than the configured minimum length after having the check characters excluded will not be decoded. (For example, when the **Do Not Transmit Check Character After Verification** option is enabled and the minimum length is set to 4, Plessey barcodes with a total length of 4 characters including the check characters cannot be read.)



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

## MSI-Plessey

### Restore Factory Defaults



@MSIDEF

**Restore the Factory Defaults of MSI-Plessey**

### Enable/Disable MSI-Plessey



@MSIENA1

**Enable MSI-Plessey**



@MSIENA0

**\*\*Disable MSI-Plessey**



If the scanner fails to identify MSI-Plessey barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable MSI-Plessey** barcode.

### Set Length Range for MSI-Plessey

The scanner can be configured to only decode MSI-Plessey barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---



@MSIMIN

**Set the Minimum Length (Default: 4)**



@MSIMAX

**Set the Maximum Length (Default: 48)**



If minimum length is set to be greater than maximum length, the scanner only decodes MSI-Plessey barcodes with either the minimum or maximum length. If minimum length is same as maximum length, only MSI-Plessey barcodes with that length are to be decoded.

**E**  
*xample*

**Set the scanner to decode MSI-Plessey barcodes containing between 8 and 12 characters:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.

### Check Character Verification

Check characters are optional for MSI-Plessey and can be added as the last one or two characters, which are calculated values used to verify the integrity of the data.

---



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**

If the **Disable** option is enabled, the scanner transmits MSI-Plessey barcodes as is.



@MSICLK0  
**Disable**



@MSICLK1

**\*\* One Check Character, MOD10**



@MSICLK2

**Two Check Characters, MOD10/MOD10**



@MSICLK3

**Two Check Characters, MOD10/MOD11**

### **Transmit Check Character**



@MSITCK1

**Transmit MSI-Plessey Check Character**



@MSITCK0

**\*\* Do Not Transmit MSI-Plessey Check Character**



If you select a check character algorithm and the **Do Not Transmit Check Character** option, MSI-Plessey barcodes with a length that is less than the configured minimum length after having the check



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

---

character(s) excluded will not be decoded. (For example, when the **One Check Character, MOD10** and **Do Not Transmit Check Character** options are enabled and the minimum length is set to 4, MSI-Plessey barcodes with a total length of 4 characters including the check character cannot be read.)



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

## AIM 128

### Restore Factory Defaults



@AIMDEF

**Restore the Factory Defaults of AIM 128**

### Enable/Disable AIM 128



@AIMENA1

**Enable AIM 128**



@AIMENA0

**\*\* Disable AIM 128**



If the scanner fails to identify AIM 128 barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable AIM 128** barcode.

### Set Length Range for AIM 128

The scanner can be configured to only decode AIM 128 barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---



@AIMMIN

**Set the Minimum Length (Default: 1)**



@AIMMAX

**Set the Maximum Length (Default: 48)**



If minimum length is set to be greater than maximum length, the scanner only decodes AIM 128 barcodes with either the minimum or maximum length. If minimum length is same as maximum length, only AIM 128 barcodes with that length are to be decoded.

**E**  
*xample*

**Set the scanner to decode AIM 128 barcodes containing between 8 and 12 characters:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**

## ISBT 128

### Restore Factory Defaults



@IBTDEF

**Restore the Factory Defaults of ISBT 128**

### Enable/Disable ISBT 128



@IBTENA1

**Enable ISBT 128**



@IBTENA0

**\*\* Disable ISBT 128**



If the scanner fails to identify ISBT 128 barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable ISBT 128** barcode.



#SETUPE0  
**Exit Setup**



#SETUPE1  
**Enter Setup**

---

## COOP 25

### Restore Factory Defaults



@COPDEF  
**Restore the Factory Defaults of COOP 25**

### Enable/Disable COOP 25



@COPENA1  
**Enable COOP 25**



@COPENA0  
**\*\* Disable COOP 25**



If the engine fails to identify COOP 25 barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable COOP 25** barcode.



@SETUPE1  
**Enter Setup**




#SETUPE1  
**Enter Setup**

### Set Length Range for COOP 25

The engine can be configured to only decode COOP 25 barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.



@COPMIN  
**Set the Minimum Length (Default: 4)**



@COPMAX  
**Set the Maximum Length (Default: 80)**



If minimum length is set to be greater than maximum length, the engine only decodes COOP 25 barcodes with either the minimum or maximum length. If minimum length is same as maximum length, only COOP 25 barcodes with that length are to be decoded.



#### Set the engine to decode COOP 25 barcodes containing between 8 and 12 characters:

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

---

### Check Character Verification



@COPCHK0

\*\* Disable



@COPCHK1

Do Not Transmit Check Character After Verification



@COPCHK2

Transmit Check Character After Verification



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

## PDF417

### Restore Factory Defaults



@PDFDEF

**Restore the Factory Defaults of PDF417**

### Enable/Disable PDF417



@PDFENA1

**\*\* Enable PDF417**



@PDFENA0

**Disable PDF417**



If the scanner fails to identify PDF417 barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable PDF417** barcode.

### Set Length Range for PDF417

The scanner can be configured to only decode PDF417 barcodes with lengths that fall between (inclusive) the



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.



@PDFMIN

**Set the Minimum Length (Default: 1)**



@PDFMAX

**Set the Maximum Length (Default: 2710)**



Minimum length is not allowed to be greater than maximum length. If you only want to read PDF417 barcodes with a specific length, set both minimum and maximum lengths to be that desired length.

**E**  
*xample*

**Set the scanner to decode PDF417 barcodes containing between 8 and 12 characters:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.

### PDF417 Twin Code

PDF417 twin code is 2 PDF417 barcodes paralleled vertically or horizontally. They must both be either regular or inverse barcodes. They must have similar specifications and be placed closely together.



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**


There are 3 options for reading PDF417 twin codes:

- ✧ **Single PDF417 Only:** Read either PDF417 code.
- ✧ **Twin PDF417 Only:** Read both PDF417 codes.
- ✧ **Both Single & Twin:** Read both PDF417 codes. If successful, transmit as twin PDF417 only. Otherwise, try single PDF417 only.



@PDFDOU0

**\*\* Single PDF417 Only**



@PDFDOU1

**Twin PDF417 Only**




@PDFDOU2

**Both Single & Twin**

## PDF417 Inverse

Regular barcode: Dark bars on a bright background. Inverse barcode: Bright bars on a dark background.



@PDFINV0

**\*\* Decode Regular PDF417 Barcodes Only**



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

---



@PDFINV2

Decode Both

## Character Encoding



@PDFENC0

\*\* Default Character Encoding



@PDFINV1

Decode Inverse PDF417 Barcodes Only



@PDFENC1

UTF-8

## PDF417 ECI Output



@PDFECI0

Disable PDF417 ECI Output



@PDFECI1

\*\* Enable PDF417 ECI Output

---



@SETUPE1

Enter Setup



#SETUPE1

**Enter Setup**

---



#SETUPE0

**Exit Setup**



#SETUPE1

**Enter Setup**

---

## Micro PDF417

### Restore Factory Defaults



@MPDDEF

**Restore the Factory Defaults of Micro PDF417**

### Enable/Disable Micro PDF417



@MPDENA1

**Enable Micro PDF417**



@MPDENA0

**\*\* Disable Micro PDF417**



If the scanner fails to identify Micro PDF417 barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable Micro PDF417** barcode.

### Set Length Range for Micro PDF417

The scanner can be configured to only decode Micro PDF417 barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**



@MPDMIN

**Set the Minimum Length (Default: 1)**



@MPDMAX

**Set the Maximum Length (Default: 366)**



Minimum length is not allowed to be greater than maximum length. If you only want to read Micro PDF417 barcodes with a specific length, set both minimum and maximum lengths to be that desired length.

**E**  
*sample*

**Set the scanner to decode Micro PDF417 barcodes containing between 8 and 12 characters:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---

## QR Code

### Restore Factory Defaults



@QRCDEF

**Restore the Factory Defaults of QR Code**

### Enable/Disable QR Code



@QRCENA1

**\*\* Enable QR Code**



@QRCENA0

**Disable QR Code**



If the scanner fails to identify QR Code barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable QR Code** barcode.

### Set Length Range for QR Code

The scanner can be configured to only decode QR Code barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**



@QRCMIN

**Set the Minimum Length (Default: 1)**



@QRCMAX

**Set the Maximum Length (Default: 7089)**



Minimum length is not allowed to be greater than maximum length. If you only want to read QR Code barcodes with a specific length, set both minimum and maximum lengths to be that desired length.

**E**  
*xample*

**Set the scanner to decode QR Code barcodes containing between 8 and 12 characters:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

---

## QR Twin Code

QR twin code is 2 QR barcodes paralleled vertically or horizontally. They must both be either regular or inverse barcodes. They must have similar specifications and be placed closely together.

There are 3 options for reading QR twin codes:

**Single QR Only:** Read either QR code.

**Twin QR Only:** Read both QR codes. Transmission sequence: left (upper) QR code followed by right (lower) QR code.

**Both Single & Twin:** Read both QR codes. If successful, transmit as twin QR only. Otherwise, try single QR only.



@QRCDU0

**\*\* Single QR Only**



@QRCDU1

**Twin QR Only**



@QRCDU2

**Both Single & Twin**

## QR Inverse

Regular barcode: Dark bars on a bright background. Inverse barcode: Bright bars on a dark background.



@QRCINV0

**\*\* Decode Regular QR Barcodes Only**



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

---



@QRCINV2  
**Decode Both**

### Character Encoding



@QRCENC0  
**\*\* Default Character Encoding**



@QRCINV1  
**Decode Inverse QR Barcodes Only**



@QRCENC1  
**UTF-8**

### QR ECI Output



@QRCEC0  
**Disable QR ECI Output**



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---



@QRCEC1

**\*\* Enable QR ECI Output**



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**

## Micro QR Code

### Restore Factory Defaults



@MQRDEF

**Restore the Factory Defaults of Micro QR**

### Enable/Disable Micro QR



@MQRENA1

**\*\* Enable Micro QR**



@MQRENA0

**Disable Micro QR**



If the scanner fails to identify Micro QR barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable Micro QR** barcode.

### Set Length Range for Micro QR

The scanner can be configured to only decode Micro QR barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---



@MQRMIN

**Set the Minimum Length (Default: 1)**



@MQRMAX

**Set the Maximum Length (Default: 35)**



Minimum length is not allowed to be greater than maximum length. If you only want to read Micro QR barcodes with a specific length, set both minimum and maximum lengths to be that desired length.

**E**  
*sample*

**Set the scanner to decode Micro QR Code barcodes containing between 8 and 12 characters:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**

## Aztec

### Restore Factory Defaults



@AZTDEF

**Restore the Factory Defaults of Aztec Code**

### Enable/Disable Aztec Code



@AZTENA1

**Enable Aztec Code**



@AZTENA0

**\*\* Disable Aztec Code**



If the scanner fails to identify Aztec Code barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable Aztec Code** barcode.

### Set Length Range for Aztec Code

The scanner can be configured to only decode Aztec barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---



@AZTMIN

**Set the Minimum Length (Default: 1)**



@AZTMAX

**Set the Maximum Length (Default: 3832)**



Minimum length is not allowed to be greater than maximum length. If you only want to read Aztec barcodes with a specific length, set both minimum and maximum lengths to be that desired length.



**Set the scanner to decode Aztec barcodes containing between 8 and 12 characters:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.

### **Read Multi-barcodes on an Image**

There are three options:

**Mode 1:** Read one barcode only.

**Mode 2:** Read fixed number of barcodes only.

---



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**

**Mode 3:** Composite Reading. Read fixed number of barcodes first. If unsuccessful, read one barcode only.



@AZTMOD1  
**\*\* Mode 1**



@AZTMOD2  
**Mode 2**



@AZTMOD3  
**Mode 3**

### Set the Number of Barcodes



@AZTMUL1  
**\*\* 1**



@AZTMUL2  
**2**



@AZTMUL3  
**3**



@AZTMUL4



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

---

4




@AZTMUL5

5




@AZTMUL6

6



@AZTMUL7

7



@AZTMUL8

8

## Character Encoding



@AZTENC0

\*\* Default Character Encoding



@AZTENC1

UTF-8



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

---

## Aztec ECI Output



@AZTECI0  
**Disable Aztec ECI Output**



@AZTECI1  
**\*\* Enable Aztec ECI Output**



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---

## Data Matrix

### Restore Factory Defaults



@DMCDEF

**Restore the Factory Defaults of Data Matrix**

### Enable/Disable Data Matrix



@DMCENA1

**\*\* Enable Data Matrix**



@DMCENA0

**Disable Data Matrix**



If the scanner fails to identify Data Matrix barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable Data Matrix** barcode.

### Set Length Range for Data Matrix

The scanner can be configured to only decode Data Matrix barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.

---



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**



@DMCMIN

**Set the Minimum Length (Default: 1)**



@DMCMAX

**Set the Maximum Length (Default: 3116)**



Minimum length is not allowed to be greater than maximum length. If you only want to read Data Matrix barcodes with a specific length, set both minimum and maximum lengths to be that desired length.

**E**  
*xample*

**Set the scanner to decode Data Matrix barcodes containing between 8 and 12 characters:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.

## Data Matrix Twin Code

Data Matrix twin code is 2 Data Matrix barcodes paralleled vertically or horizontally. They must both be either regular or inverse barcodes. They must have similar specifications and be placed closely together.



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

There are 3 options for reading Data Matrix twin codes:

**Single Data Matrix Only:** Read either Data Matrix code.

**Twin Data Matrix Only:** Read both Data Matrix codes. Transmission sequence: left (upper) Data Matrix code followed by right (lower) Data Matrix code.

**Both Single & Twin:** Read both Data Matrix codes. If successful, transmit as twin Data Matrix only. Otherwise, try single Data Matrix only.



@DMCDOU0

**\*\* Single Data Matrix Only**



@DMCDOU1

**Twin Data Matrix Only**



@DMCDOU2

**Both Single & Twin**

## Rectangular Barcode

Data Matrix has two formats:

Square barcodes having the same amount of modules in length and width: 10\*10, 12\*12....

144\*144. Rectangular barcodes having different amounts of models in length and width: 6\*16,

6\*14...14\*22.



@DMCREC1

**\*\* Enable Rectangular Barcode**



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**



@DMCREC0

**Disable Rectangular Barcode**

## Data Matrix Inverse

Regular barcode: Dark bars on a bright background. Inverse barcode: Bright bars on a dark background.



@DMCINV0

**\*\* Decode Regular Data Matrix Barcodes Only**



@DMCINV1

**Decode Inverse Data Matrix Barcodes Only**



@DMCINV2

**Decode Both**

## Character Encoding




@DMCENC0

**\*\* Default Character Encoding**



@DMCENC1

**UTF-8**



#SETUPE0

**Exit Setup**



#SETUPE1

Enter Setup

---

### Data Matrix ECI Output



@DMCECI0

Disable Data Matrix ECI Output



@DMCECI1

**\*\* Enable Data Matrix ECI Output**



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

## Maxicode Restore Factory Defaults



@MXCDEF

**Restore the Factory Defaults of Maxicode**

## Enable/Disable Maxicode



@MXCENA1

**Enable Maxicode**



@MXCENA0

**\*\* Disable Maxicode**



If the scanner fails to identify Maxicode barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable Maxicode** barcode.



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

## Set Length Range for Maxicode

The scanner can be configured to only decode Maxicode barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.



@MXCMIN

**Set the Minimum Length (Default: 1)**



@MXCMAX

**Set the Maximum Length (Default:150)**



Minimum length is not allowed to be greater than maximum length. If you only want to read Maxicode barcodes with a specific length, set both minimum and maximum lengths to be that desired length.



### Set the scanner to decode Maxicode barcodes containing between 8 and 12 characters:

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**

## Chinese Sensible Code Restore Factory Defaults



@CSCDEF

**Restore the Factory Defaults of Chinese Sensible Code**

## Enable/Disable Chinese Sensible Code



@CSCENA1

**Enable Chinese Sensible Code**



@CSCENA0

**\*\* Disable Chinese Sensible Code**



If the scanner fails to identify Chinese Sensible Code barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable Chinese Sensible Code** barcode.



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---

## Set Length Range for Chinese Sensible Code

The scanner can be configured to only decode Chinese Sensible Code barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.



@CSCMIN

**Set the Minimum Length (Default: 1)**



@CSCMAX

**Set the Maximum Length (Default: 7827)**



Minimum length is not allowed to be greater than maximum length. If you only want to read Chinese Sensible Code barcodes with a specific length, set both minimum and maximum lengths to be that desired length.

**Set the scanner to decode Chinese Sensible Code barcodes containing between 8 and 12 characters:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**

## Chinese Sensible Twin Code

Chinese Sensible twin code is 2 Chinese Sensible barcodes paralleled vertically or horizontally. They must both be either regular or inverse barcodes. They must have similar specifications and be placed closely together.

There are 3 options for reading Chinese Sensible twin codes:

**Single Chinese Sensible Code Only:** Read either Chinese Sensible code.

**Twin Chinese Sensible Code Only:** Read both Chinese Sensible codes. Transmission sequence: left (upper) Chinese Sensible code followed by right (lower) Chinese Sensible code.

**Both Single & Twin:** Read both Chinese Sensible codes. If successful, transmit as twin Chinese Sensible Code only. Otherwise, try single Chinese Sensible Code only.



@CSCDOU0

**\*\* Single Chinese Sensible Code Only**



@CSCDOU1

**Twin Chinese Sensible Code Only**



@CSCDOU2

**Both Single & Twin**



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

---

## Chinese Sensible Code Inverse

Regular barcode: Dark bars on a bright background.

Inverse barcode: Bright bars on a dark background.



@CSCINV0

**\*\* Decode Regular Chinese Sensible Barcodes Only**



@CSCINV1

**Decode Inverse Chinese Sensible Barcodes Only**



@CSCINV2

**Decode Both**



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

---

## USPS Postnet

### Restore Factory Defaults



@PNTDEF

**Restore the Factory Defaults of USPS Postnet**

### Enable/Disable USPS Postnet



@PNTENA1

**Enable USPS Postnet**



@PNTENA0

**\*\* Disable USPS Postnet**



If the scanner fails to identify USPS Postnet barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable USPS Postnet** barcode.

### Transmit Check Character



@PNTCHK1

**Do Not Transmit USPS Postnet Check Character**



@PNTCHK2

**\*\* Transmit USPS Postnet Check Character**



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---

## **USPS Intelligent Mail Restore Factory Defaults**



@ILGDEF

**Restore the Factory Defaults of USPS Intelligent Mail**

## **Enable/Disable USPS Intelligent Mail**



@ILGENA1

**Enable USPS Intelligent Mail**



@ILGENA0

**\*\* Disable USPS Intelligent Mail**



If the scanner fails to identify USPS Intelligent Mail barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable USPS Intelligent Mail** barcode.



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**

## Royal Mail

### Restore Factory Defaults



@ROYDEF

**Restore the Factory Defaults of Royal Mail**

## Enable/Disable Royal Mail



@ROYENA1

**Enable Royal Mail**



@ROYENA0

**\*\* Disable Royal Mail**



If the scanner fails to identify Royal Mail barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable Royal Mail** barcode.



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---

## USPS Planet

**Restore Factory Defaults**



@PLADEF

**Restore the Factory Defaults of USPS Planet**

**Enable/Disable USPS Planet**



@PLAENA1

**Enable USPS Planet**



@PLAENA0

**\*\* Disable USPS Planet**



If the scanner fails to identify USPS Planet barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable USPS Planet** barcode.

**Transmit Check Character**



@PLACHK1

**Do Not Transmit USPS Planet Check Character**



@PLACHK2

**\*\* Transmit USPS Planet Check Character**



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**

## KIX Post

### Restore Factory Defaults



@KIXDEF

**Restore the Factory Defaults of KIX Post**

## Enable/Disable KIX Post



@KIXENA1

**Enable KIX Post**



@KIXENA0

**\*\* Disable KIX Post**



If the scanner fails to identify KIX Post barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable KIX Post** barcode.



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---

## Australian Postal Restore Factory Defaults



@APLDEF

**Restore the Factory Defaults of Australian Postal**

## Enable/Disable Australian Postal



@APLENA1

**Enable Australian Postal**



@APLENA0

**\*\* Disable Australian Postal**



If the scanner fails to identify Australian Postal barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable Australian Postal** barcode.



@SETUPE1

**Enter Setup**



#SETUPE1

Enter Setup

---

## Japan Post

### Restore Factory Defaults



@JPPDEF

Restore the Factory Defaults of Japan Post

## Enable/Disable Japan Post



@JPPENA1

Enable Japan Post



@JPPENA0

\*\* Disable Japan Post



#SETUPE0

Exit Setup



#SETUPE1

**Enter Setup**

---

## GM Code

### Restore Factory Defaults



@GMCDEF

Restore the Factory Defaults of GM

## Enable/Disable GM



@GMCENA1

**Enable GM**



@GMCENA0

**\*\* Disable GM**



If the scanner fails to identify GM barcodes, you may first try this solution by scanning the **Enter Setup** barcode and then **Enable GM** barcode.



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**

## Set Length Range for GM

The scanner can be configured to only decode GM barcodes with lengths that fall between (inclusive) the minimum and maximum lengths. To accomplish it, you need to set the minimum and maximum lengths.



@GMCMIN

**Set the Minimum Length (Default: 1)**



@GMC MAX

**Set the Maximum Length (Default: 2751)**



**E**  
*xample*

Minimum length is not allowed to be greater than maximum length. If you only want to read GM barcodes with a specific length, set both minimum and maximum lengths to be that desired length.

### Set the scanner to decode GM barcodes containing between 8 and 12 characters:

1. Scan the **Enter Setup** barcode.
2. Scan the **Set the Minimum Length** barcode.
3. Scan the numeric barcode “8” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Set the Maximum Length** barcode.
6. Scan the numeric barcodes “1” and “2” from the “Digit Barcodes” section in Appendix.
7. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
8. Scan the **Exit Setup** barcode.



#SETUPE0  
**Exit Setup**



#SETUPE1  
Enter Setup

## Chapter 7 Data Formatter

### Introduction

You may use the Data Formatter to modify the scanner's output. For example, you can use the Data Formatter to insert characters at certain points in barcode data or to suppress/ replace/ send certain characters in barcode data as it is scanned.

Normally, when you scan a barcode, it gets outputted automatically; however, when you create a format, you must use a "send" command (see the "Send Commands" section in this chapter) within the format programming to output data. Multiple data formats can be programmed into the scanner. The maximum size of all data formats created is 2048 characters. By default, the data formatter is disabled. Enable it when required. If you have changed data format settings, and wish to clear all formats and return to the factory defaults, scan the **Default Data Format** code below.



**\*\*Default Data Format**

### Add a Data Format

Data format is used to edit barcode data. When you create a data format, you must select one of the four labels (Format\_0, Format\_1, Format\_2 and Format\_3) for your data format, specify the application scope of data format (such as barcode type and data length) and include formatter commands. Multiple data formats may be created using the same label. When scanned data does not match your data format requirements, you will hear the non-match error beep (if the non-match error beep is ON).

There are two methods to program a data format: Programming with barcodes and programming with serial commands.

### Programming with Barcodes

The following explains how to program a data format by scanning the specific barcodes. Scanning any irrelevant barcode or failing to follow the setting procedure will result in programming failure. To find the alphanumeric barcodes needed to create a data format, see the "Digit Barcodes" section in Appendix.

**Step 1:** Scan the **Enter Setup** barcode.



@SETUPE1  
Enter Setup



#SETUPE1  
**Enter Setup**

**Step 2:** Scan the **Add Data Format** barcode.



@DFMADD  
**Add Data Format**

**Step 3:** Select a label (Format\_0 or Format\_1 or Format\_2 or Format\_3).

Scan a numeric barcode **0** or **1** or **2** or **3** to label this data format Format\_0 or Format\_1 or Format\_2 or Format\_3.

**Step 4:** Select formatter command type.

Specify what type of formatter commands will be used. Scan a numeric barcode “6” to select formatter command type 6. (See the “Formatter Command Type 6” section in this chapter for more information)

**Step 5:** Set interface type

Scan **999** for any interface type.

**Step 6:** Set Symbology ID Number

Refer to the “Symbology ID Number” section in Appendix and find the ID number of the symbology to which you want to apply the data format. Scan three numeric barcodes for the symbology ID number. If you wish to create a data format for all symbologies, scan **999**.

**Step 7:** Set barcode data length

Specify what length of data will be acceptable for this symbology. Scan the four numeric barcodes that represent the data length. 9999 is a universal number, indicating all lengths. For example, 32 characters should be entered as 0032.

**Step 8:** Enter formatter command

Refer to the “Formatter Command Type 6” section in this chapter. Scan the alphanumeric barcodes that represent the command you need to edit data. For example, when a command is F141, you should scan F141.

**Step 9:** Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix to save your data format.

## **E** *Example*

Program a Format\_0 data format using formatter command type 6, Code 128 containing 10 characters applicable, send all characters followed by “A”.

1. Scan the **Enter Setup** barcode
2. Scan the **Add Data Format** barcode
3. Scan the **0** barcode



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

4. Scan the **6** barcode
5. Scan the **9** barcode three times
6. Scan the barcodes **002**
7. Scan the barcodes **0010**
8. Scan the alphanumeric barcodes **F141**
9. Scan the **Save** barcode

To streamline the programming process, you may as well generate a batch barcode by inputting the command (e.g. **@DFMADD069990020010F141;**) used to create a data format. See the “Use Batch Barcode” section in Chapter 9 to learn how to put a batch barcode into use.

When creating multiple data formats sharing a label, the formats are separated from each other by a vertical bar (|) in the batch command, e.g. **@DFMADD069990029999F141|069990039999F142|169990049999F143;**.

## Programming with Serial Commands

A data format can also be created by serial commands (HEX) sent from the host device. **All commands must be entered in uppercase letters.**

The syntax consists of the following elements:

**Prefix:** “~<SOH>0000” (HEX: **7E 01 30 30 30 30**), 6 characters.

**Storage type:** “@” (HEX: **40**) or “#” (HEX: **23**), 1 character. “@” means permanent setting which will not be lost by removing power from the scanner or rebooting it; “#” means temporary setting which will be lost by removing power from the scanner or rebooting it.

**Add Data Format Command:** “DFMADD” (HEX: **44 46 4D 41 44 44**), 6 characters.

**Data format label:** “0” (HEX: **30**) or “1” (HEX: **31**) or “2” (HEX: **32**) or “3” (HEX: **33**), 1 character. “0”, “1”, “2” and “3” represent Format\_0, Format\_1, Format\_2 and Format\_3 respectively.

**Formatter command type:** “6” (HEX: **36**), 1 character.

**Interface type:** “999” (HEX: **39 39 39**), 3 characters.

**Symbology ID Number:** The ID number of the symbology to which you want to apply the data format, 3 characters. 999 indicates all symbologies.

**Data length:** The length of data that will be acceptable for this symbology, 4 characters. 9999 indicates all lengths.



@SETUPE1

Enter Setup



#SETUPE1  
Enter Setup

For example, 32 characters should be entered as 0032.

**Formatter commands:** The command string used to edit data. For more information, see the “Formatter Command Type 6” section in this chapter.

**Suffix:** “;<ETX>” (HEX: **3B 03**), 2 characters.

**Example:** Program a Format\_0 data format using formatter command type 6, Code 128 containing 10 characters applicable, send all characters followed by “A”.

Enter: **7E 01 30 30 30 30 40 44 46 4D 41 44 44 30 36 39 39 39 30 30 33 39 39 39 39 46 31 34 31 3B 03**  
(~<SOH>0000@DFMADD069990020010F141;<ETX>)

Response: **02 01 30 30 30 30 40 44 46 4D 41 44 44 30 36 39 39 39 30 30 33 39 39 39 39 46 31 34 31 06 3B 03**  
(<STX><SOH>0000@DFMADD069990020010F141<ACK>;<ETX>)

When creating multiple data formats sharing a label, the formats are separated from each other by a vertical bar (|) in the serial command.

**Example:** ~<SOH>0000@DFMADD069990020010F141|069990039999F142|069990049999F143;<ETX>

## Enable/Disable Data Formatter

When Data Formatter is disabled, the barcode data is outputted to the host as read, including prefixes and suffixes.



**\*\* Disable Data Formatter**

You may wish to require the data to conform to a data format you have created. The following settings can be applied to your data format:

**Enable Data Formatter, Required, Keep Prefix/Suffix:** Scanned data that meets your data format requirements is modified accordingly and gets outputted along with prefixes and suffixes (if prefix and suffix are enabled). Any data that does not match your data format requirements generates an error beep (if Non-Match Error Beep is turned ON) and the data in that barcode is not transmitted.

**Enable Data Formatter, Required, Drop Prefix/Suffix:** Scanned data that meets your data format requirements is



#SETUPE0  
Exit Setup



#SETUPE1

**Enter Setup**

modified accordingly and gets outputted without prefixes and suffixes (even if prefix and suffix are enabled). Any data that does not match your data format requirements generates an error beep (if Non-Match Error Beep is turned ON) and the data in that barcode is not transmitted.

**Enable Data Formatter, Not Required, Keep Prefix/Suffix:** Scanned data that meets your data format requirements is modified accordingly and gets outputted along with prefixes and suffixes (if prefix and suffix are enabled). Barcode data that does not match your data format requirements is transmitted as read along with prefixes and suffixes (if prefix and suffix are enabled).

**Enable Data Formatter, Not Required, Drop Prefix/Suffix:** Scanned data that meets your data format requirements is modified accordingly and gets outputted without prefixes and suffixes (even if prefix and suffix are enabled). Barcode data that does not match your data format requirements is transmitted as read along with prefixes and suffixes (if prefix and suffix are enabled).




@DFMENA1

**Enable Data Formatter, Required, Keep Prefix/Suffix**



@DFMENA3

**Enable Data Formatter, Not Required, Keep Prefix/Suffix**



@DFMENA2

**Enable Data Formatter, Required, Drop Prefix/Suffix**



@DFMENA4

**Enable Data Formatter, Not Required, Drop Prefix/Suffix**



@SETUPE1

**Enter Setup**



#SETUPE1

**Enter Setup**

---



#SETUPE0

**Exit Setup**



#SETUPE1

Enter Setup

---

## Non-Match Error Beep

If Non-Match Error Beep is turned ON, the scanner generates an error beep when a barcode is encountered that does not match your required data format.



@DFMTON0

**Non-Match Error Beep Off**



@DFMTON1

**\*\* Non-Match Error Beep On**

## Data Format Selection

After enabling the Data Formatter, you can select a data format you want to use by scanning the appropriate barcode below.

The default setting is Format\_0.



@DFMUSE0

**\*\* Format\_0**



@DFMUSE1

**Format\_1**



@DFMUSE2

**Format\_2**



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**



@DFMUSE3  
**Format\_3**

## Change Data Format for a Single Scan

You can switch between data formats for a single scan. The next barcode is scanned using the data format selected here, then reverts to the format you have selected above.

For example, you may have set your scanner to use the data format you saved as Format\_3. You can switch to Format\_1 for a single trigger pull by scanning the **Single Scan – Format\_1** barcode below. The next barcode that is scanned uses Format\_1, then reverts back to Format\_3.

Note: This setting will be lost by removing power from the scanner, or turning off/ rebooting the device.



@DFMSIN0  
**Single Scan – Format\_0**



@DFMSIN1  
**Single Scan – Format\_1**



@DFMSIN2  
**Single Scan – Format\_2**



@DFMSIN3  
**Single Scan – Format\_3**

## Clear Data Format

There are two methods to remove data format created from your scanner:



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---


Delete one data format: Scan the **Clear One** barcode, a numeric barcode (0-3) and the **Save** barcode. For example, to delete Format\_2, you should scan the **Clear One** barcode, the **2** barcode and the **Save** barcode

Delete all data formats: Scan the **Clear All** barcode.



@DFMCAL

**Clear All**



@DFMCLR

**Clear One**


## Query Data Formats

You may scan the appropriate barcode below to get the information of data format(s) created by you or preset by manufacturer. For instance, if you have added Format\_0 as per the example in the “Add a Data Format” section in this chapter, scanning the **Query Current Data Formats** barcode, you will get the result: **Data Format0:069990020010F141;**.



@DFMQCU

**Query Current Data Formats**



@DFMQFA

**Query Preset Data Formats**



@SETUPE1

**Enter Setup**



#SETUPE1  
Enter Setup

## Chapter 8 Prefix & Suffix

### Introduction

A 1D barcode could contain digits, letters, symbols, etc. A 2D barcode could contain more data, such as Chinese characters and other multi-byte characters. However, in real applications, they do not and should not have all information we need, such as barcode type, data acquisition time and delimiter, in order to keep the barcodes short and flexible.

Prefix and suffix are how to fulfill the needs mentioned above. They can be added, removed and modified while the original barcode data remains intact.



Barcode processing procedure:

1. Edit data with Data Formatter
2. Append prefix/suffix
3. Pack data
4. Append terminating character

### Global Settings

#### Enable/Disable All Prefixes/Suffixes

**Disable All Prefixes/Suffixes:** Transmit barcode data with no prefix/suffix.

**Enable All Prefixes/Suffixes:** Allow to append Code ID prefix, AIM ID prefix, custom prefix/suffix and terminating character to the barcode data before the transmission.



@APSENA0

**\*\* Disable All Prefixes/Suffixes**



#SETUPE0  
Exit Setup



#SETUPE1

Enter Setup



@APSENA1

Enable All Prefixes/Suffixes

## Prefix Sequence



@PRESEQ0

\*\* Code ID+ Custom +AIM ID



@PRESEQ1

Custom + Code ID + AIM ID

## Custom Prefix

### Enable/Disable Custom Prefix

If custom prefix is enabled, you are allowed to append to the data a user-defined prefix that cannot exceed 10 characters. For example, if the custom prefix is “AB” and the barcode data is “123”, the Host will receive “AB123”.



@CPRENA0

\*\* Disable Custom Prefix



@CPRENA1

Enable Custom Prefix

### Set Custom Prefix

To set a custom prefix, scan the **Set Custom Prefix** barcode then the numeric barcodes corresponding to the hexadecimal value of a desired prefix then the **Save** barcode.



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

---

**Note:** A custom prefix cannot exceed 10 characters.



@CPRSET  
**Set Custom Prefix**

**E**  
*sample*

**Set the custom prefix to “CODE” (HEX: 0x43/0x4F/0x44/0x45):**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set Custom Prefix** barcode.
3. Scan the numeric barcodes “4”, “3”, “4”, “F”, “4”, “4”, “4” and “5” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Enable Custom Prefix** barcode.
6. Scan the **Exit Setup** barcode.



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

---

## AIM ID Prefix

AIM (Automatic Identification Manufacturers) ID defines symbology identifier (For the details, see the “AIM ID Table” section in Appendix). If AIM ID prefix is enabled, the scanner will add the symbology identifier before the scanned data after decoding.



@AIDENA0

**\*\* Disable AIM ID Prefix**



@AIDENA1

**Enable AIM ID Prefix**



AIM ID is not user programmable.



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

---

## Code ID Prefix

Code ID can also be used to identify barcode type. Unlike AIM ID, Code ID is user programmable. Code ID can only consist of one or two English letters.



@CIDENA0  
**\*\* Disable Code ID Prefix**



@CIDENA1  
**Enable Code ID Prefix**



#SETUPE0  
**Exit Setup**



#SETUPE1

**Enter Setup**

---

## Restore All Default Code IDs

For the information of default Code IDs, see the “Code ID Table” section in Appendix.



@CIDDEF

**Restore All Default Code IDs**

## Modify Code ID

See the examples below to learn how to modify a Code ID and restore the default Code IDs of all symbologies.

**E**  
*xample*

### Modify PDF417 Code ID to be “p” (HEX: 0x70):

1. Scan the **Enter Setup** barcode.
2. Scan the **Modify PDF417 Code ID** barcode.
3. Scan the numeric barcodes “7” and “0” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.
5. Scan the **Exit Setup** barcode.

### Restore the default Code IDs of all symbologies:

1. Scan the **Enter Setup** barcode.
2. Scan the **Restore All Default Code IDs** barcode.
3. Scan the **Exit Setup** barcode.



@SETUPE1

**Enter Setup**



#SETUPE1  
Enter Setup

## Modify 1D symbologies



@CID002

Modify Code 128 Code ID



@CID004

Modify EAN-8 Code ID



@CID003

Modify GS1-128 (UCC/EAN-128) Code ID



@CID005

Modify EAN-13 Code ID



@CID006

Modify UPC-E Code ID



@CID007

Modify UPC-A Code ID



@CID008

Modify Interleaved 2 of 5 Code ID



#SETUPE0  
Exit Setup



#SETUPE1

**Enter Setup**

---



@SETUPE1

**Enter Setup**



#SETUPE1  
Enter Setup

---



@CID009  
Modify ITF-14 Code ID



@CID010  
Modify ITF-6 Code ID



@CID011  
Modify Matrix 2 of 5 Code ID



@CID013  
Modify Code 39



@CID015  
Modify Codabar Code ID



@CID017  
Modify Code 93 Code ID



@CID019  
Modify China Post 25 Code ID



@CID020  
Modify AIM 128 Code ID



#SETUPE0  
Exit Setup



#SETUPE1

Enter Setup

---



@CID022

Modify COOP 25 Code ID



@CID023

Modify ISSN Code ID



@CID025

Modify Industrial 25 Code ID



@CID027

Modify Plessey Code ID



@CID029

Modify MSI Plessey Code ID



@CID021

Modify ISBT 128 Code ID



@CID024

Modify ISBN Code ID



@CID026

Modify Standard 25 Code ID



@CID028

Modify Code 11 Code ID



@SETUPE1

Enter Setup



#SETUPE1

**Enter Setup**

---



#SETUPE0

**Exit Setup**



#SETUPE1

**Enter Setup**

---



@CID030

**Modify GS1 Composite Code ID**



@CID031

**Modify GS1 Databar (RSS) Code ID**



@SETUPE1

**Enter Setup**



#SETUPE1  
Enter Setup

## Modify 2D symbologies:



@CID032  
Modify PDF417 Code ID



@CID033  
Modify QR Code ID



@CID034  
Modify Aztec Code ID



@CID035  
Modify Data Matrix Code ID



@CID036  
Modify Maxicode Code ID



@CID039  
Modify Chinese Sensible Code ID



@CID041  
Modify GM Code ID



@CID042  
Modify Micro PDF417 Code ID



@CID043  
Modify Micro QR Code ID



#SETUPE0  
Exit Setup



#SETUPE1

**Enter Setup**

---



@SETUPE1

**Enter Setup**



#SETUPE1  
**Enter Setup**

## Custom Suffix

### Enable/Disable Custom Suffix

If custom suffix is enabled, you are allowed to append to the data a user-defined suffix that cannot exceed 10 characters. For example, if the custom suffix is “AB” and the barcode data is “123”, the Host will receive “123AB”.



@CSUENA0

**\*\* Disable Custom Suffix**



@CSUENA1

**Enable Custom Suffix**

### Set Custom Suffix

To set a custom suffix, scan the **Set Custom Suffix** barcode then the numeric barcodes corresponding to the hexadecimal value of a desired suffix then the **Save** barcode.

**Note:** A custom suffix cannot exceed 10 characters.



@CSUSET

**Set Custom Suffix**

**E**  
*sample*

**Set the custom suffix to “CODE” (HEX: 0x43/0x4F/0x44/0x45):**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set Custom Suffix** barcode.
3. Scan the numeric barcodes “4”, “3”, “4”, “F”, “4”, “4”, “4” and “5” from the “Digit Barcodes” section in Appendix.
4. Scan the **Save** barcode from the “Save/Cancel Barcodes” section in Appendix.



#SETUPE0

**Exit Setup**



#SETUPE1

Enter Setup

5. Scan the **Enable Custom Suffix** barcode.
6. Scan the **Exit Setup** barcode.

## Data Packing

### Introduction

Data packing is designed for a specific group of users who want to have the data packed before transmission. Data packing influences data format, so it is advised to disable this feature when it is not required.

### Data Packing Options

**Disable Data Packing:** Transmit decoded data in raw format (unpacked).

**Enable Data Packing, Format 1:** Transmit decoded data with the packet format 1 defined below.

Packet format 1: [STX + ATTR + LEN] + [AL\_TYPE + DATA] +

[LRC] STX: 0x02

ATTR: 0x00

LEN: Barcode data length is expressed in 2 bytes ranging from 0x0000 (0) to 0xFFFF

(65535). AL\_TYPE: 0x36

DATA: Raw barcode data.

LRC: Check digit.

LRC calculation algorithm: computation sequence: 0xFF+LEN+AL\_TYPE+DATA; computation method is XOR, byte by byte.

**Enable Data Packing, Format 2:** Transmit decoded data with the packet format 2 defined below.

Packet format 2: [STX + ATTR + LEN] + [AL\_TYPE] + [Symbology\_ID + DATA] +

[LRC] STX: 0x02

ATTR: 0x00

LEN: Barcode data length is expressed in 2 bytes ranging from 0x0000 (0) to 0xFFFF

(65535). AL\_TYPE: 0x3B

Symbology\_ID: The ID number of symbology, 1



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

byte. DATA: Raw barcode data.

LRC: Check digit.

LRC calculation algorithm: computation sequence: 0xFF+LEN+AL\_TYPE+Symbology\_ID+DATA; computation method is XOR, byte by byte.



@PACKAG0

**\*\* Disable Data Packing**



@PACKAG1

**Enable Data Packing, Format 1**



@PACKAG2

**Enable Data Packing, Format 2**

## Terminating Character Suffix

### Enable/Disable Terminating Character Suffix

A terminating character such as carriage return (CR) or carriage return/line feed pair (CRLF) can only be used to mark the end of data, which means nothing can be added after it.



@TSUENA0

**Disable Terminating Character Suffix**



@TSUENA1

**\*\* Enable Terminating Character Suffix**



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

## Set Terminating Character Suffix

To set a terminating character suffix, scan the **Set Terminating Character Suffix** barcode then the numeric barcodes corresponding to the hexadecimal value of a desired terminating character then the **Save** barcode.

**Note:** A terminating character suffix cannot exceed 2 characters.



@TSUSET

Set Terminating Character Suffix



@TSUSET0D

**\*\* Set Terminating Character to CR**



@TSUSET0D0A

Set Terminating Character to CRLF (0x0D,0x0A)

(0x0D)

**E**  
*xample*

**Set the terminating character suffix to 0x0A:**

1. Scan the **Enter Setup** barcode.
2. Scan the **Set Terminating Character Suffix** barcode.
3. Scan the numeric barcodes "0" and "A" from the "Digit Barcodes" section in Appendix.
4. Scan the **Save** barcode from the "Save/Cancel Barcodes" section in Appendix.
5. Scan the **Enable Terminating Character Suffix** barcode.
6. Scan the **Exit Setup** barcode.



@SETUPE1

Enter Setup



#SETUPE1  
Enter Setup

## Chapter 9 Batch Programming

### Introduction

Batch programming enables users to integrate a batch of commands into a single batch barcode.

Listed below are batch programming rules:

1. Command format: Command + Parameter Value.
2. Each command is terminated by a semicolon (;). Note that there is no space between a command and its terminator semicolon.
3. Use the barcode generator software to generate a 2D batch barcode.

Example: Create a batch barcode for **Normal Illumination, Sense Mode, Decode Session Timeout = 2s, Disable Interleaved 2 of 5:**

1. Input the commands:

@ILLSCN1;SCNMOD2;ORTSET2000;I25ENA0;

2. Generate a batch barcode.

When setting up a scanner with the above configuration, scan the **Enable Batch Barcode** barcode and then the batch barcode generated.



@BATCHS  
Enable Batch Barcode

### Create a Batch Command

A batch command may contain a number of individual commands each of which is terminated by a semicolon (;). For more information, refer to the "Use of Programming Command" section in Chapter 3.



#SETUPE0  
Exit Setup



#SETUPE1  
Enter Setup

---

## Create a Batch Barcode

Batch barcodes can be produced in the format of PDF417, QR Code or Data Matrix.

Example: Create a batch barcode for **Normal Illumination, Sense Mode, Decode Session Timeout = 2s, Disable Interleaved 2 of 5:**

1. Input the following commands:

@ILLSCN1;SCNMOD2;ORTSET2000;I25ENA0;

2. Generate a PDF417 batch barcode.



## Use Batch Barcode

To put a batch barcode into use, scan the following barcodes. (Use the example above.)



@SETUPE1  
Enter Setup



@BATCHS  
Enable Batch Barcode

---



@SETUPE1  
Enter Setup



#SETUPE1  
**Enter Setup**



**Batch Barcode**



@SETUPE0

**Exit Setup**



#SETUPE0  
**Exit Setup**



#SETUPE1  
Enter Setup

## Appendix

### Digit Barcodes


0~9



@DIGIT0  
0



@DIGIT2  
2




@DIGIT4  
4



@DIGIT1  
1



@DIGIT3  
3



@DIGIT5  
5



@SETUPE1  
Enter Setup



#SETUPE1  
**Enter Setup**

---



@DIGIT6  
**6**



@DIGIT7  
**7**



@DIGIT8  
**8**



@DIGIT9  
**9**

**A~F**



@DIGITA  
**A**



@DIGITB  
**B**



@DIGITC  
**C**



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

---



@DIGITD

D




@DIGITE

E



@DIGITF

F



@DIGIVB

'1'

## Save/Cancel Barcodes

After reading numeric barcode(s), you need to scan the **Save** barcode to save the data. If you scan the wrong digit(s), you can either scan the **Cancel** barcode and then start the configuration all over again, or scan the **Delete the Last Digit** barcode and then the correct digit, or scan the **Delete All Digits** barcode and then the digits you want.

For instance, after reading the **Maximum Length** barcode and numeric barcodes "1", "2" and "3", you scan:

- ✧ **Delete the Last Digit:** The last digit "3" will be removed.
- ✧ **Delete All Digits:** All digits "123" will be removed.
- ✧ **Cancel:** The maximum length configuration will be cancelled. And the scanner is still in the setup mode.



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

---



@DIGSAV  
**Save**



@DIGCAN  
**Cancel**



@DIGDEL  
**Delete the Last Digit**



@DIGDAL  
**Delete All Digits**



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

## Factory Defaults Table

| Parameter                                | Factory Default       | Remark        |
|------------------------------------------|-----------------------|---------------|
| <b>System Settings</b>                   |                       |               |
| Barcode Programming                      | Disabled (Exit Setup) |               |
| Programming Barcode Data                 | Do not transmit       |               |
| Illumination                             | On                    |               |
| Aiming                                   | On                    |               |
| Power On Beep                            | On                    |               |
| Good Read Beep                           | On                    |               |
| Good Read Beep Duration                  | Medium (80ms)         |               |
| Good Read Beep Frequency                 | 4000Hz                |               |
| Good Read Beep Volume                    | Loud                  |               |
| Good Read Vibration                      | On                    |               |
| Good Read Vibration Duration             | 100ms                 |               |
| Scan Mode                                | Level Mode            |               |
| Decode Session Timeout                   | 3,000ms.              | 1-3,600,000ms |
| Image Stabilization Timeout (Sense Mode) | 200ms                 | 0-3,000ms     |
| Reread Timeout                           | Disabled              |               |
|                                          | 300ms                 | 1-3,600,000ms |
| Reset Reread Timeout                     | On                    |               |
| Good Read Delay                          | Off                   |               |
|                                          | 500ms                 |               |
| Image Decoding Timeout                   | 500ms                 | 1-3,000ms     |
| Surround GS1 AI's with Parentheses       | Off                   |               |
| Sensitivity                              | Medium Sensitivity    |               |
| Trigger Commands                         | Disabled              |               |
| Scanning Preference                      | Normal                |               |
| Read Barcode                             | On                    |               |
| Decode Area                              | Whole Area Decoding   |               |
| Image Flipping                           | Do Not Flip           |               |
| Bad Read Message                         | Off                   |               |
|                                          | NG                    |               |
| Operating Mode                           | Bluetooth HID         |               |



@SETUPE1


Enter Setup



#SETUPE1  
**Enter Setup**

---

|                   |                  |  |
|-------------------|------------------|--|
| Default Interface | USB HID Keyboard |  |
|-------------------|------------------|--|



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

|                                  |                                      |                  |
|----------------------------------|--------------------------------------|------------------|
| <b>USB Interface</b>             |                                      |                  |
| USB Country Keyboard             | US keyboard                          | USB HID Keyboard |
| Beep on Unknown Character        | Off                                  | USB HID Keyboard |
| Emulate ALT+Keypad               | Off                                  | USB HID Keyboard |
| Code Page                        | Code Page 1252 (West European Latin) | USB HID Keyboard |
| Unicode Encoding                 | Off                                  | USB HID Keyboard |
| Emulate Keypad with Leading Zero | On                                   | USB HID Keyboard |
| Function Key Mapping             | Disable                              | USB HID Keyboard |
| Inter-Keystroke Delay            | No Delay                             | USB HID Keyboard |
| Caps Lock                        | Off(Non Japanese Keypad)             | USB HID Keyboard |
| Convert Case                     | No Case Conversion                   | USB HID Keyboard |
| Emulate Numeric Keypad 1         | Off                                  | USB HID Keyboard |
| Emulate Numeric Keypad 2         | Off                                  | USB HID Keyboard |
| Fast Mode                        | Off                                  | USB HID Keyboard |
| Polling Rate                     | 4ms                                  | USB HID Keyboard |
| <b>Wireless Communication</b>    |                                      |                  |
| Auto Power-off                   | 5 minutes                            |                  |
| <b>Symbologies</b>               |                                      |                  |
| <b>Code 128</b>                  |                                      |                  |
| Code 128                         | Enabled                              |                  |
| Maximum Length                   | 48                                   |                  |
| Minimum Length                   | 1                                    |                  |
| <b>EAN-8</b>                     |                                      |                  |
| EAN-8                            | Enabled                              |                  |



@SETUPE1

Enter Setup



#SETUPE1

Enter Setup

|                                                    |                            |  |
|----------------------------------------------------|----------------------------|--|
| Check Character                                    | Transmit                   |  |
| 2-Digit Add-On Code                                | Disabled                   |  |
| 5-Digit Add-On Code                                | Disabled                   |  |
| Add-On Code Required                               | Not Required               |  |
| Convert EAN-8 to EAN-13                            | Disabled                   |  |
| <b>EAN-13</b>                                      |                            |  |
| EAN-13                                             | Enabled                    |  |
| Check Character                                    | Transmit                   |  |
| 2-Digit Add-On Code                                | Disabled                   |  |
| 5-Digit Add-On Code                                | Disabled                   |  |
| Add-On Code Required                               | Do Not Require Add-On Code |  |
| EAN-13 Beginning with 290 Add-On Code Required     | Do Not Require Add-On Code |  |
| EAN-13 Beginning with 378/379 Add-On Code Required | Do Not Require Add-On Code |  |
| EAN-13 Beginning with 414/419 Add-On Code Required | Do Not Require Add-On Code |  |
| EAN-13 Beginning with 434/439 Add-On Code Required | Do Not Require Add-On Code |  |
| EAN-13 Beginning with 977 Add-On Code Required     | Do Not Require Add-On Code |  |
| EAN-13 Beginning with 978 Add-On Code Required     | Do Not Require Add-On Code |  |
| EAN-13 Beginning with 979 Add-On Code Required     | Do Not Require Add-On Code |  |
| <b>UPC-E</b>                                       |                            |  |
| <b>UPC-E</b>                                       | Enabled                    |  |
| UPC-E0                                             | Enabled                    |  |
| UPC-E1                                             | Disable                    |  |
| Check Character                                    | Transmit                   |  |
| 2-Digit Add-On Code                                | Disabled                   |  |
| 5-Digit Add-On Code                                | Disabled                   |  |
| Add-On Code Required                               | Not Required               |  |
| Transmit Preamble Character                        | System Character           |  |



#SETUPE0

Exit Setup



#SETUPE1

Enter Setup

|                        |          |  |
|------------------------|----------|--|
| Convert UPC-E to UPC-A | Disabled |  |
| <b>UPC-A</b>           |          |  |
| UPC-A                  | Enabled  |  |



@SETUPE1

Enter Setup



#SETUPE1

Enter Setup

|                                        |                  |                |
|----------------------------------------|------------------|----------------|
| Check Character                        | Transmit         |                |
| 2-Digit Add-On Code                    | Disabled         |                |
| 5-Digit Add-On Code                    | Disabled         |                |
| Add-On Code Required                   | Not Required     |                |
| Transmit Preamble Character            | System Character |                |
| <b>Coupon</b>                          |                  |                |
| UPC-A/EAN-13 with Extended Coupon Code | Off              |                |
| Coupon GS1 DataBar Output              | Off              |                |
| <b>Interleaved 2 of 5</b>              |                  |                |
| Interleaved 2 of 5                     | Enabled          |                |
| Maximum Length                         | 80               |                |
| Minimum Length                         | 6                |                |
| Check Character Verification           | Disabled         |                |
| <b>ITF-14</b>                          |                  |                |
| ITF-14                                 | Disabled         |                |
| <b>ITF-6</b>                           |                  |                |
| ITF-6                                  | Disabled         |                |
| <b>Matrix 2 of 5</b>                   |                  |                |
| Matrix 2 of 5                          | Enabled          |                |
| Maximum Length                         | 80               |                |
| Minimum Length                         | 4                | No less than 4 |
| Check Character Verification           | Disable          |                |
| <b>Code 39</b>                         |                  |                |
| Code 39                                | Enabled          |                |
| Maximum Length                         | 48               |                |
| Minimum Length                         | 1                |                |
| Check Character Verification           | Disabled         |                |
| Start/Stop Character                   | Do not transmit  |                |
| Code 39 Full ASCII                     | Disabled         |                |
| Code 32 Pharmaceutical (PARAF)         | Disabled         |                |



#SETUPE0

Exit Setup



#SETUPE1

Enter Setup

|                              |                                                    |                |
|------------------------------|----------------------------------------------------|----------------|
| Code 32 Prefix               | Disabled                                           |                |
| Code 32 Start/Stop Character | Do not transmit                                    |                |
| Code 32 Check Character      | Do not transmit                                    |                |
| <b>Codabar</b>               |                                                    |                |
| Codabar                      | Enabled                                            |                |
| Maximum Length               | 60                                                 |                |
| Minimum Length               | 2                                                  |                |
| Check Character Verification | Disabled                                           |                |
| Start/Stop Character         | Do not transmit                                    |                |
|                              | ABCD/ABCD                                          | All capital    |
| <b>Code 93</b>               |                                                    |                |
| Code 93                      | Disabled                                           |                |
| Maximum Length               | 48                                                 |                |
| Minimum Length               | 1                                                  |                |
| Check Character Verification | Do Not Transmit Check Character After Verification |                |
| <b>China Post 25</b>         |                                                    |                |
| China Post 25                | Disabled                                           |                |
| Maximum Length               | 48                                                 |                |
| Minimum Length               | 1                                                  |                |
| Check Character Verification | Disabled                                           |                |
| <b>UCC/EAN-128</b>           |                                                    |                |
| UCC/EAN-128                  | Enabled                                            |                |
| Maximum Length               | 48                                                 |                |
| Minimum Length               | 1                                                  |                |
| <b>GS1 Databar</b>           |                                                    |                |
| GS1 Databar                  | Enabled                                            |                |
| Application Identifier "01"  | Transmit                                           |                |
| <b>EAN•UCC Composite</b>     |                                                    |                |
| GS1 Composite                | Disabled                                           |                |
| UPC/EAN Composite            | Disabled                                           |                |
| <b>Code 11</b>               |                                                    |                |
| Code 11                      | Disabled                                           |                |
| Maximum Length               | 48                                                 |                |
| Minimum Length               | 4                                                  | No less than 4 |



@SETUPE1

Enter Setup



#SETUPE1  
**Enter Setup**

---

|                              |                            |  |
|------------------------------|----------------------------|--|
| Check Character Verification | One Check Character, MOD11 |  |
|------------------------------|----------------------------|--|



#SETUPE0  
**Exit Setup**



#SETUPE1

Enter Setup

|                              |                            |                |
|------------------------------|----------------------------|----------------|
| Check Character              | Transmit Check Character   |                |
| <b>ISBN</b>                  |                            |                |
| ISBN                         | Disabled                   |                |
| Set ISBN Format              | ISBN-10                    |                |
| <b>ISSN</b>                  |                            |                |
| <b>Industrial 25</b>         |                            |                |
| Industrial 25                | Disabled                   |                |
| Maximum Length               | 48                         |                |
| Minimum Length               | 6                          | No less than 4 |
| Check Character Verification | Disabled                   |                |
| <b>Standard 25</b>           |                            |                |
| Standard 25                  | Disabled                   |                |
| Maximum Length               | 48                         |                |
| Minimum Length               | 6                          | No less than 4 |
| Check Character Verification | Disabled                   |                |
| <b>Plessey</b>               |                            |                |
| Plessey                      | Disabled                   |                |
| Maximum Length               | 48                         |                |
| Minimum Length               | 4                          | No less than 4 |
| Check Character Verification | Disabled                   |                |
| <b>MSI-Plessey</b>           |                            |                |
| MSI-Plessey                  | Disabled                   |                |
| Maximum Length               | 48                         |                |
| Minimum Length               | 4                          | No less than 4 |
| Check Character Verification | One Check Character, MOD10 |                |
| Check Character              | Transmit                   |                |
| <b>AIM 128</b>               |                            |                |
| AIM 128                      | Disabled                   |                |
| Maximum Length               | 48                         |                |
| Minimum Length               | 1                          |                |
| <b>ISBT 128</b>              |                            |                |
| ISBT 128                     | Disabled                   |                |



@SETUPE1

Enter Setup



#SETUPE1

Enter Setup

|                              |                                     |  |
|------------------------------|-------------------------------------|--|
| <b>COOP 25</b>               |                                     |  |
| COOP 25                      | Disable                             |  |
| Maximum Length               | 80                                  |  |
| Minimum Length               | 4                                   |  |
| Check Character Verification | Disabled                            |  |
| <b>PDF417</b>                |                                     |  |
| PDF417                       | Enabled                             |  |
| Maximum Length               | 2710                                |  |
| Minimum Length               | 1                                   |  |
| PDF417 Twin Code             | Single PDF417 Only                  |  |
| PDF417 Inverse               | Decode Regular PDF417 Barcodes Only |  |
| Character Encoding           | Default Character Encoding          |  |
| PDF417 ECI Output            | Enabled                             |  |
| <b>Micro PDF 417</b>         |                                     |  |
| Micro PDF417                 | Disabled                            |  |
| Maximum Length               | 366                                 |  |
| Minimum Length               | 1                                   |  |
| <b>QR Code</b>               |                                     |  |
| QR Code                      | Enabled                             |  |
| Maximum Length               | 7089                                |  |
| Minimum Length               | 1                                   |  |
| QR Twin Code                 | Single QR Only                      |  |
| QR Inverse                   | Decode Regular QR Barcodes Only     |  |
| Character Encoding           | Default Character Encoding          |  |
| QR ECI Output                | Enabled                             |  |
| <b>Micro QR Code</b>         |                                     |  |
| Micro QR Code                | Enable                              |  |
| Maximum Length               | 35                                  |  |
| Minimum Length               | 1                                   |  |
| <b>Aztec</b>                 |                                     |  |
| Aztec Code                   | Disabled                            |  |
| Maximum Length               | 3832                                |  |
| Minimum Length               | 1                                   |  |



#SETUPE0

Exit Setup



#SETUPE1

**Enter Setup**

---

|                                 |                            |  |
|---------------------------------|----------------------------|--|
| Read Multi-barcodes on an Image | Mode 1                     |  |
| Character Encoding              | Default Character Encoding |  |
| Aztec ECI Output                | Enable                     |  |



@SETUPE1

**Enter Setup**



#SETUPE1

Enter Setup

|                                 |                                          |  |
|---------------------------------|------------------------------------------|--|
| <b>Data Matrix</b>              |                                          |  |
| Data Matrix                     | Enabled                                  |  |
| Maximum Length                  | 3116                                     |  |
| Minimum Length                  | 1                                        |  |
| Data Matrix Twin Code           | Single Data Matrix Only                  |  |
| Rectangular Barcode             | Enabled                                  |  |
| Data Matrix Inverse             | Decode Regular Data Matrix Barcodes Only |  |
| Character Encoding              | Default Character Encoding               |  |
| Data Matrix ECI Output          | Enabled                                  |  |
| <b>Maxicode</b>                 |                                          |  |
| Maxicode                        | Disable                                  |  |
| Maximum Length                  | 150                                      |  |
| Minimum Length                  | 1                                        |  |
| <b>Chinese Sensible Code</b>    |                                          |  |
| Chinese Sensible Code           | Disable                                  |  |
| Maximum Length                  | 7827                                     |  |
| Minimum Length                  | 1                                        |  |
| Chinese Sensible Code Twin Code | Single Data Matrix Only                  |  |
| Chinese Sensible Code Inverse   | Decode Regular Data Matrix Barcodes Only |  |
| <b>USPS Postnet</b>             |                                          |  |
| USPS Postnet                    | Disabled                                 |  |
| Check Character                 | Transmit                                 |  |
| <b>USPS Intelligent Mail</b>    |                                          |  |
| USPS Intelligent Mail           | Disabled                                 |  |
| <b>Royal Mail</b>               |                                          |  |
| Royal Mail                      | Disabled                                 |  |
| <b>USPS Planet</b>              |                                          |  |
| USPS Planet                     | Disabled                                 |  |
| Check Character                 | Transmit                                 |  |
| <b>KIX Post</b>                 |                                          |  |
| KIX Post                        | Disabled                                 |  |
| <b>Australian Postal</b>        |                                          |  |
| Australian Postal               | Disabled                                 |  |



#SETUPE0

Exit Setup



#SETUPE1

Enter Setup

|                              |                         |  |
|------------------------------|-------------------------|--|
| <b>Japan Post</b>            |                         |  |
| Japan Post                   | Disabled                |  |
| <b>GM Code</b>               |                         |  |
| GM Code                      | Disable                 |  |
| Maximum Length               | 2751                    |  |
| Minimum Length               | 1                       |  |
| <b>Data Formatter</b>        |                         |  |
| Data Formatter               | Disabled                |  |
| Data Format Selection        | Format_0                |  |
| Non-Match Error Beep         | On                      |  |
| <b>Prefix &amp; Suffix</b>   |                         |  |
| All Prefixes/Suffixes        | Disabled                |  |
| Prefix Sequence              | Code ID+ Custom +AIM ID |  |
| Custom Prefix                | Disabled                |  |
| AIM ID Prefix                | Disabled                |  |
| Code ID Prefix               | Disabled                |  |
| Custom Suffix                | Disabled                |  |
| Data Packing                 | Disable Data Packing    |  |
| Terminating Character Suffix | Enable                  |  |



@SETUPE1

Enter Setup



#SETUPE1  
Enter Setup

## AIM ID Table

| Symbology             | AIM ID | Possible AIM ID Modifiers (m) |
|-----------------------|--------|-------------------------------|
| Code128               | ]C0    |                               |
| GS1-128 (UCC/EAN-128) | ]C1    |                               |
| EAN-8                 | ]E4    |                               |
| EAN-8 with Addon      | ]E3    |                               |
| EAN-13                | ]E0    |                               |
| EAN-13 with Addon     | ]E3    |                               |
| UPC-E                 | ]E0    |                               |
| UPC-E with Addon      | ]E3    |                               |
| UPC-A                 | ]E0    |                               |
| UPC-A with Addon      | ]E3    |                               |
| Interleaved 2 of 5    | ]Im    | 0, 1, 3                       |
| ITF-14                | ]Im    | 1, 3                          |
| ITF-6                 | ]Im    | 1, 3                          |
| Matrix 2 of 5         | ]X0    |                               |
| Code 39               | ]Am    | 0, 1, 3, 4, 5, 7              |
| Codabar               | ]Fm    | 0, 2, 4                       |
| Code 93               | ]G0    |                               |
| China Post 25         | ]X0    |                               |
| AIM 128               | ]C2    |                               |
| ISBT 128              | ]C4    |                               |
| ISSN                  | ]X0    |                               |
| ISBN                  | ]X0    |                               |
| Industrial 25         | ]S0    |                               |
| Standard 25           | ]R0    |                               |
| Plessey               | ]P0    |                               |
| Code 11               | ]Hm    | 0, 1, 3                       |
| MSI Plessey           | ]Mm    | 0, 1                          |
| GS1 Composite         | ]em    | 0-3                           |
| GS1 Databar (RSS)     | ]e0    |                               |
| Code 49               | ]T0    |                               |



#SETUPE0  
Exit Setup



#SETUPE1

Enter Setup

---

|          |     |  |
|----------|-----|--|
| Code 16K | JK0 |  |
| COOP 25  | JX0 |  |



@SETUPE1

Enter Setup



#SETUPE1

Enter Setup

|                             |     |          |
|-----------------------------|-----|----------|
| PDF417                      | ]Lm | 0-2      |
| QR Code                     | ]Qm | 0-6      |
| Aztec                       | ]zm | 0-9, A-C |
| Data Matrix                 | ]dm | 0-6      |
| Maxicode                    | ]Um | 0-3      |
| 汉信码 (Chinese Sensible Code) | ]X0 |          |
| GM                          | ]gm | (0~9)    |
| Micro PDF417                | ]L0 |          |
| Micro QR                    | ]Q1 |          |
| Code One                    | ]X0 |          |
| DotCode                     | ]Jm | 0~5      |
| USPS Postnet                | ]X0 |          |
| USPS Intelligent Mail       | ]X0 |          |
| Royal Mail                  | ]X0 |          |
| USPS Planet                 | ]X0 |          |
| KIX Post                    | ]X0 |          |
| Australian Postal           | ]X0 |          |
| Japan Post                  | ]X0 |          |
| Specific OCR-B              | ]o2 |          |
| Passport OCR                | ]o2 |          |
| Chinese ID Card             | ]o2 |          |
| China Travel Permit OCR     | ]o2 |          |

**Note:** “m” represents the AIM modifier character.  
Refer to ISO/IEC 15424:2008 Information  
technology – Automatic identification and data  
capture techniques – Data Carrier Identifiers  
(including Symbology Identifiers) for AIM modifier  
character details.



#SETUPE0

Exit Setup



#SETUPE1

Enter Setup

---

## Code ID Table

| Symbology             | Code ID |
|-----------------------|---------|
| Code128               | j       |
| GS1-128 (UCC/EAN-128) | j       |
| EAN-8                 | d       |
| EAN-13                | d       |
| UPC-E                 | c       |
| UPC-A                 | c       |
| Interleaved 2 of 5    | e       |
| ITF-14                | e       |
| ITF-6                 | e       |
| Matrix 2 of 5         | v       |
| Code 39               | b       |
| Codabar               | a       |
| Code 93               | i       |
| China Post 25         | X       |
| AIM 128               | X       |
| ISBT 128              | X       |
| ISSN                  | g       |
| ISBN                  | B       |
| Industrial 25         | l       |
| Standard 25           | f       |
| Plessey               | n       |
| Code 11               | H       |
| MSI Plessey           | m       |
| GS1 Composite         | y       |
| GS1 Databar (RSS)     | R       |
| Code 49               | X       |
| Code 16K              | X       |
| COOP 25               | X       |
| PDF417                | r       |
| QR Code               | s       |



@SETUPE1

Enter Setup



#SETUPE1

**Enter Setup**

---

|             |   |
|-------------|---|
| Aztec       | z |
| Data Matrix | u |



#SETUPE0

**Exit Setup**



#SETUPE1

Enter Setup

|                         |   |
|-------------------------|---|
| MaxiCode                | x |
| Chinese Sensible Code   | h |
| GM Code                 | x |
| Micro PDF417            | R |
| Micro QR                | X |
| Code One                | X |
| DotCode                 | X |
| USPS Postnet            | P |
| USPS Intelligent Mail   | M |
| Royal Mail              | x |
| USPS Planet             | L |
| KIX Post                | K |
| Australian Postal       | A |
| Japan Post              | J |
| Specific OCR-B          | S |
| Passport OCR            | O |
| Chinese ID Card         | S |
| China Travel Permit OCR | S |



@SETUPE1

Enter Setup



#SETUPE1

Enter Setup

## Symbology ID Number

| Symbology             | ID Number |
|-----------------------|-----------|
| Code 128              | 002       |
| GS1-128 (UCC/EAN-128) | 003       |
| EAN-8                 | 004       |
| EAN-13                | 005       |
| UPC-E                 | 006       |
| UPC-A                 | 007       |
| Interleaved 2 OF 5    | 008       |
| ITF-14                | 009       |
| ITF-6                 | 010       |
| Matrix 2 of 5         | 011       |
| Code 39               | 013       |
| Codabar               | 015       |
| Code 93               | 017       |
| China Post 25         | 019       |
| AIM 128               | 020       |
| ISBT 128              | 021       |
| COOP 25               | 022       |
| ISSN                  | 023       |
| ISBN                  | 024       |
| Industrial25          | 025       |
| Standard25            | 026       |
| Plessey               | 027       |
| Code11                | 028       |
| MSI-Plessey           | 029       |
| GS1 Composite         | 030       |
| GS1 Databar (RSS)     | 031       |
| PDF417                | 032       |
| QR Code               | 033       |
| Aztec                 | 034       |
| Data Matrix           | 035       |



#SETUPE0

Exit Setup



#SETUPE1

Enter Setup

---

|                       |     |
|-----------------------|-----|
| Maxicode              | 036 |
| Chinese Sensible Code | 039 |



@SETUPE1

Enter Setup



#SETUPE1

**Enter Setup**

|                         |     |
|-------------------------|-----|
| GM Code                 | 040 |
| Micro PDF417            | 042 |
| Micro QR                | 043 |
| Code One                | 048 |
| DotCode                 | 050 |
| Specific OCR-B          | 064 |
| Chinese ID Card         | 065 |
| Passport OCR            | 066 |
| China Travel Permit OCR | 068 |
| USPS Postnet            | 096 |
| USPS Intelligent Mail   | 097 |
| Royal Mail              | 098 |
| USPS Planet             | 099 |
| KIX Post                | 100 |
| Australian Postal       | 101 |
| Japan Post              | 102 |
| Code 49                 | 132 |
| Code 16K                | 133 |



#SETUPE0

**Exit Setup**



#SETUPE1

Enter Setup

---

## ASCII Table

| Hex | Dec | Char                          |
|-----|-----|-------------------------------|
| 00  | 0   | NUL (Null char.)              |
| 01  | 1   | SOH (Start of Header)         |
| 02  | 2   | STX (Start of Text)           |
| 03  | 3   | ETX (End of Text)             |
| 04  | 4   | EOT (End of Transmission)     |
| 05  | 5   | ENQ (Enquiry)                 |
| 06  | 6   | ACK (Acknowledgment)          |
| 07  | 7   | BEL (Bell)                    |
| 08  | 8   | BS (Backspace)                |
| 09  | 9   | HT (Horizontal Tab)           |
| 0a  | 10  | LF (Line Feed)                |
| 0b  | 11  | VT (Vertical Tab)             |
| 0c  | 12  | FF (Form Feed)                |
| 0d  | 13  | CR (Carriage Return)          |
| 0e  | 14  | SO (Shift Out)                |
| 0f  | 15  | SI (Shift In)                 |
| 10  | 16  | DLE (Data Link Escape)        |
| 11  | 17  | DC1 (XON) (Device Control 1)  |
| 12  | 18  | DC2 (Device Control 2)        |
| 13  | 19  | DC3 (XOFF) (Device Control 3) |
| 14  | 20  | DC4 (Device Control 4)        |
| 15  | 21  | NAK (Negative Acknowledgment) |
| 16  | 22  | SYN (Synchronous Idle)        |
| 17  | 23  | ETB (End of Trans. Block)     |
| 18  | 24  | CAN (Cancel)                  |
| 19  | 25  | EM (End of Medium)            |
| 1a  | 26  | SUB (Substitute)              |
| 1b  | 27  | ESC (Escape)                  |



@SETUPE1

Enter Setup



#SETUPE1

**Enter Setup**

---

|    |    |                     |
|----|----|---------------------|
| 1c | 28 | FS (File Separator) |
|----|----|---------------------|



#SETUPE0

**Exit Setup**



#SETUPE1

Enter Setup

| Hex | Dec | Char                           |
|-----|-----|--------------------------------|
| 1d  | 29  | GS (Group Separator)           |
| 1e  | 30  | RS (Request to Send)           |
| 1f  | 31  | US (Unit Separator)            |
| 20  | 32  | SP (Space)                     |
| 21  | 33  | ! (Exclamation Mark)           |
| 22  | 34  | " (Double Quote)               |
| 23  | 35  | # (Number Sign)                |
| 24  | 36  | \$ (Dollar Sign)               |
| 25  | 37  | % (Percent)                    |
| 26  | 38  | & (Ampersand)                  |
| 27  | 39  | ` (Single Quote)               |
| 28  | 40  | ( (Left/ Opening Parenthesis)  |
| 29  | 41  | ) (Right/ Closing Parenthesis) |
| 2a  | 42  | * (Asterisk)                   |
| 2b  | 43  | + (Plus)                       |
| 2c  | 44  | , (Comma)                      |
| 2d  | 45  | - (Minus/ Dash)                |
| 2e  | 46  | . (Dot)                        |
| 2f  | 47  | / (Forward Slash)              |
| 30  | 48  | 0                              |
| 31  | 49  | 1                              |
| 32  | 50  | 2                              |
| 33  | 51  | 3                              |
| 34  | 52  | 4                              |
| 35  | 53  | 5                              |
| 36  | 54  | 6                              |
| 37  | 55  | 7                              |
| 38  | 56  | 8                              |
| 39  | 57  | 9                              |
| 3a  | 58  | : (Colon)                      |
| 3b  | 59  | ; (Semi-colon)                 |



@SETUPE1

Enter Setup



#SETUPE1

**Enter Setup**

---

|    |    |   |              |
|----|----|---|--------------|
| 3c | 60 | < | (Less Than)  |
| 3d | 61 | = | (Equal Sign) |



#SETUPE0

**Exit Setup**



#SETUPE1

Enter Setup

---

| Hex | Dec | Char                      |
|-----|-----|---------------------------|
| 3e  | 62  | > (Greater Than)          |
| 3f  | 63  | ? (Question Mark)         |
| 40  | 64  | @ (AT Symbol)             |
| 41  | 65  | A                         |
| 42  | 66  | B                         |
| 43  | 67  | C                         |
| 44  | 68  | D                         |
| 45  | 69  | E                         |
| 46  | 70  | F                         |
| 47  | 71  | G                         |
| 48  | 72  | H                         |
| 49  | 73  | I                         |
| 4a  | 74  | J                         |
| 4b  | 75  | K                         |
| 4c  | 76  | L                         |
| 4d  | 77  | M                         |
| 4e  | 78  | N                         |
| 4f  | 79  | O                         |
| 50  | 80  | P                         |
| 51  | 81  | Q                         |
| 52  | 82  | R                         |
| 53  | 83  | S                         |
| 54  | 84  | T                         |
| 55  | 85  | U                         |
| 56  | 86  | V                         |
| 57  | 87  | W                         |
| 58  | 88  | X                         |
| 59  | 89  | Y                         |
| 5a  | 90  | Z                         |
| 5b  | 91  | [ (Left/ Opening Bracket) |
| 5c  | 92  | \ (Back Slash)            |



@SETUPE1

Enter Setup



#SETUPE1

**Enter Setup**

---

|    |    |   |                          |
|----|----|---|--------------------------|
| 5d | 93 | ] | (Right/ Closing Bracket) |
|----|----|---|--------------------------|



#SETUPE0

**Exit Setup**



#SETUPE1

Enter Setup

---

| Hex | Dec | Char                    |
|-----|-----|-------------------------|
| 5e  | 94  | ^ (Caret/ Circumflex)   |
| 5f  | 95  | _ (Underscore)          |
| 60  | 96  | ' (Grave Accent)        |
| 61  | 97  | a                       |
| 62  | 98  | b                       |
| 63  | 99  | c                       |
| 64  | 100 | d                       |
| 65  | 101 | e                       |
| 66  | 102 | f                       |
| 67  | 103 | g                       |
| 68  | 104 | h                       |
| 69  | 105 | i                       |
| 6a  | 106 | j                       |
| 6b  | 107 | k                       |
| 6c  | 108 | l                       |
| 6d  | 109 | m                       |
| 6e  | 110 | n                       |
| 6f  | 111 | o                       |
| 70  | 112 | p                       |
| 71  | 113 | q                       |
| 72  | 114 | r                       |
| 73  | 115 | s                       |
| 74  | 116 | t                       |
| 75  | 117 | u                       |
| 76  | 118 | v                       |
| 77  | 119 | w                       |
| 78  | 120 | x                       |
| 79  | 121 | y                       |
| 7a  | 122 | z                       |
| 7b  | 123 | { (Left/ Opening Brace) |
| 7c  | 124 | (Vertical Bar)          |



@SETUPE1

Enter Setup



#SETUPE1

**Enter Setup**

---

|    |     |     |                        |
|----|-----|-----|------------------------|
| 7d | 125 | }   | (Right/ Closing Brace) |
| 7e | 126 | ~   | (Tilde)                |
| 7f | 127 | DEL | (Delete)               |



#SETUPE0

**Exit Setup**

Unicode Key Maps

|    |    |    |    |    |    |    |    |    |    |    |    |    |    |    |    |    |    |    |    |    |
|----|----|----|----|----|----|----|----|----|----|----|----|----|----|----|----|----|----|----|----|----|
| 6E | 70 | 71 | 72 | 73 | 74 | 75 | 76 | 77 | 78 | 79 | 7A | 7B | 7C | 7D | 7E |    |    |    |    |    |
| 01 | 02 | 03 | 04 | 05 | 06 | 07 | 08 | 09 | 0A | 0B | 0C | 0D | 0F | 4B | 50 | 55 | 5A | 5F | 64 | 69 |
| 10 | 11 | 12 | 13 | 14 | 15 | 16 | 17 | 18 | 19 | 1A | 1B | 1C | 1D | 4C | 51 | 56 | 5B | 60 | 65 | 6A |
| 1E | 1F | 20 | 21 | 22 | 23 | 24 | 25 | 26 | 27 | 28 | 29 | 2B |    |    |    |    | 5C | 61 | 66 |    |
| 2C | 2E | 2F | 30 | 31 | 32 | 33 | 34 | 35 | 36 | 37 | 39 |    |    | 53 |    |    | 5D | 62 | 67 | 6C |
| 3A | 3B | 3C | 3D |    |    |    |    | 3E | 3F | 38 | 40 | 4F | 54 | 59 | 63 | 68 |    |    |    |    |

104 Key U.S. Style Keyboard

|    |    |    |    |    |    |    |    |    |    |    |    |    |    |    |    |    |    |    |    |    |
|----|----|----|----|----|----|----|----|----|----|----|----|----|----|----|----|----|----|----|----|----|
| 6E | 70 | 71 | 72 | 73 | 74 | 75 | 76 | 77 | 78 | 79 | 7A | 7B | 7C | 7D | 7E |    |    |    |    |    |
| 01 | 02 | 03 | 04 | 05 | 06 | 07 | 08 | 09 | 0A | 0B | 0C | 0D | 0F | 4B | 50 | 55 | 5A | 5F | 64 | 69 |
| 10 | 11 | 12 | 13 | 14 | 15 | 16 | 17 | 18 | 19 | 1A | 1B | 1C | 2B | 4C | 51 | 56 | 5B | 60 | 65 | 6A |
| 1E | 1F | 20 | 21 | 22 | 23 | 24 | 25 | 26 | 27 | 28 | 29 | 1D |    |    |    |    | 5C | 61 | 66 |    |
| 2C | 2D | 2E | 2F | 30 | 31 | 32 | 33 | 34 | 35 | 36 | 37 | 39 |    |    | 53 |    | 5D | 62 | 67 | 6C |
| 3A | 3B | 3C | 3D |    |    |    |    | 3E | 3F | 38 | 40 |    | 4F | 54 | 59 | 63 | 68 |    |    |    |

105 Key European Style Keyboard



**Newland**  
SCANNING MADE SIMPLE

**Newland EMEA HQ**  
+31 (0) 345 87 00 33  
[info@newland-id.com](mailto:info@newland-id.com)  
[newland-id.com](http://newland-id.com)

Need more info?  
Contact us or one of our [partners](#)